Renesas Flash Programmer V3

Release Note

R20UT4953EJ2300
Rev.23.00
Oct.01.26

Introduction

Thank you for using the Renesas Flash Programmer (RFP).

This document covers release information on the RFP V3 products. For points for caution, also see the software manual for the RFP. For the target devices supported by the latest version, refer to "List of MCUs supported by Renesas Flash Programmer V3" on the Renesas Web site.

See the following documents for restrictions applying to particular target devices.

- Manuals for the target devices
- Documents in which restrictions applying to particular target devices are listed

Contents

1. Environment 5
1.1 OSs supported 5
1.2 Required software 5
1.3 Restrictions 5

2. Release Information on RFP V3.25.00 6
2.1 Additional target devices 6
2.2 New features 6
2.3 Improvements through changes to features 6

3. Release Information on the Previous RFP V3 Products 8
3.1 Release Information on RFP V3.24.00 8
3.1.1 Additional target devices 8
3.1.2 New features 8
3.1.3 Improvements through changes to features 8
3.2 Release Information on RFP V3.23.00 9
3.2.1 Additional target devices 9
3.2.2 Improvements through changes to features 9
3.3 Release Information on RFP V3.22.00 11
3.3.1 Additional target devices 11
3.3.2 New feature 11
3.3.3 Improvements through changes to features 11
3.4 Release Information on RFP V3.21.00 12
3.4.1 Additional target devices 12
3.4.2 Improvements through changes to features 12
3.5 Release Information on RFP V3.20.00 13
3.5.1 Additional target devices 13

3.5.2 New feature 13
3.5.3 Improvements through changes to features 13
3.6 Release Information on RFP V3.19.00 14
3.6.1 Additional target devices 14
3.6.2 Improvements through changes to features 14
3.7 Release Information on RFP V3.18.00 15
3.7.1 Additional target devices 15
3.7.2 New feature 15
3.7.3 Improvement through changes to a feature 15
3.8 Release Information on RFP V3.17.00 16
3.8.1 Additional target devices 16
3.8.2 Improvement through changes to a feature 16
3.9 Release Information on RFP V3.16.00 16
3.9.1 Additional target devices 16
3.9.2 Improvements through changes to features 16
3.10 Release Information on RFP V3.15.00 17
3.10.1 Additional target devices 17
3.10.2 Improvements through changes to features 17
3.10.3 Removing a restriction 18
3.11 Release Information on RFP V3.14.00 18
3.11.1 Additional target devices 18
3.11.2 New feature 18
3.11.3 Improvements through changes to features 18
3.12 Release Information on RFP V3.13.00 19
3.12.1 Additional target devices 19
3.12.2 New features 19
3.12.3 Improvements through changes to a feature 19
3.13 Release Information on RFP V3.12.00 20
3.13.1 Additional target device 20
3.13.2 Improvements through changes to a feature 20
3.14 Release Information on RFP V3.11.02 20
3.14.1 Additional target devices 20
3.14.2 New features 20
3.14.3 Improvements through changes to a feature 21
3.15 Release Information on RFP V3.11.01 22
3.15.1 Additional target devices 22
3.15.2 New feature 22
3.15.3 Improvements through changes to a feature 22
3.16 Release Information on RFP V3.11.00 23
3.16.1 Additional target devices 23
3.16.2 New feature 23

3.16.3 Improvements through changes to a feature 23
3.16.4 Removing restrictions 23
3.16.5 Errata for User's Manual 23
3.17 Release Information on RFP V3.10.00 23
3.17.1 Additional target devices 23
3.17.2 New feature 23
3.17.3 Improvement through changes to a feature 24
3.18 Release Information on RFP V3.09.02 24
3.18.1 Additional target devices 24
3.18.2 Improvements through changes to a feature 24
3.19 Release Information on RFP V3.09.01 25
3.19.1 Additional target devices 25
3.19.2 New features 25
3.19.3 Improvements through changes to a feature 25
3.19.4 Removing a restriction 25
3.20 Release Information on RFP V3.09.00 26
3.20.1 Additional target devices 26
3.20.2 New features 26
3.20.3 Improvements through changes to a feature 26
3.21 Release Information on RFP V3.08.03 27
3.21.1 Additional target devices 27
3.22 Release Information on RFP V3.08.02 27
3.22.1 Additional target devices 27
3.22.2 New feature 27
3.22.3 Improvement through changes to a feature 27
3.23 Release information on RFP V3.08.01 28
3.23.1 Additional target devices 28
3.23.2 Removing a restriction 28
3.24 Release information on RFP V3.08.00 29
3.24.1 Additional target devices 29
3.24.2 New features 29
3.24.3 Change to a feature 29
3.25 Release information on RFP V3.06.02 30
3.25.1 Additional target devices 30
3.26 Release information on RFP V3.06.01 30
3.26.1 Additional target devices 30
3.27 Release information on RFP V3.06.00 31
3.27.1 Additional target devices 31
3.27.2 New features 31
3.27.3 Removing a restriction 31
3.28 Release information on RFP V3.05.03 31

3.28.1 Additional target devices 31
3.28.2 Removing a restriction 31
3.29 Release information on RFP V3.05.01 32
3.29.1 Additional target devices 32
3.30 Release information on RFP V3.05.00 32
3.30.1 Additional target devices 32
3.30.2 New features 32
3.30.3 Improvement through changes to a feature 33
3.30.4 Removing a restriction 33
3.31 Release information on RFP V3.04.00 33
3.31.1 Additional target devices 33
3.31.2 New features 33
3.32 Release information on RFP V3.03.01 34
3.32.1 Additional target device 34
3.32.2 Removing restrictions 34
3.33 Release information on RFP V3.03.00 34
3.33.1 Additional target devices 34
3.33.2 New features 34
3.33.3 Improvement through changes to a feature 35
3.34 Release information on RFP V3.02.01 35
3.34.1 Additional target devices 35
3.34.2 New feature 35
3.35 Release information on RFP V3.02.00 36
3.35.1 Additional target devices 36
3.35.2 New feature 36
3.36 Release information on RFP V3.01.00 37
3.36.1 Additional target devices 37
3.36.2 New features 37
3.36.3 Improvement through changes to a feature 38
3.36.4 Removing restrictions 38
3.37 Release history of the RFP 39

4. Restrictions 40
4.1 List of restrictions 40
4.2 Details of restrictions 42

1. Environment

1.1 OSs supported

- Windows 10 (32-bit and 64-bit)
- Windows 11
- Linux (Ubuntu 22.04 LTS, x64/ARM32/ARM64) (*1)
- Linux (Ubuntu 24.04 LTS, x64/ARM64) (*1)
- macOS 15 Sequoia (only supported on machines with Apple silicon) (*2)
- macOS 26 Tahoe (only supported on machines with Apple silicon) (*2)

Remarks:
1. We recommend having the latest version of Windows installed.
2. A point for caution applies with regard to the security function of Windows. For details, refer to item (4) in section 4.2, Problems during Operation, in the latest version of the software manual for this product.
3. The GUI (RFPV3.exe) does not run. (*1), (*2)
4. In some cases, the UART (serial port) connection may not correctly operate, or certain restrictions may apply according to the version of the OS. (*2)
5. ARM32 is not supported by Ubuntu 24.04 LTS and later versions.

1.2 Required software

- Linux and macOS: Refer to the guide “rfp-cli.md”, which is separately provided. Note that this is a markdown-format English file.

1.3 Restrictions

- Linux does not support the E1 emulator and E20 emulator.
- macOS does not support the E1 emulator and E20 emulator. It also does not support connection through USB boot mode for RA devices.

2. Release Information on RFP V3.25.00

2.1 Additional target devices

No target devices have been added in this version.

2.2 New features

- Support for the J-Link with RX74x MCUs

Applies to: RX74x

J-Link has been added as a supported tool for RX74x devices. Note that only UART and SWD communication interfaces are supported. In addition, SWD communication is supported only with J-Link.

2.3 Improvements through changes to features

- Support for programming of external flash memory mounted on EK-RA4M2 and EK-RA4M3

EK Board	External Flash Memory
EK-RA4M2	MX25L25645G
EK-RA4M3	

The RFP now supports the erasure and programming of external memory above. This feature is supported only when using the SWD interface. In addition, erasure, programming, and read operations cannot be performed when the target device is in the non-secure state.

- Change to area name

The area names displayed in the GUI and output in the logs of the command-line software rfp-cli have been changed as follows.

Before the Change	After the Change
Code Flash	Code Area
Data Flash	Data Area
User Boot	User Extra*1

Notes: 1. RX74x MCUs only.

- Changes to rfp-cli option name

Applies to: RX74x

The following option names of the command-line software rfp-cli have been changed.

Before the change: userboot-flags

After the change: userextra-flags

- Support for communication speed specification in the -run-user-image command for the rfp-cli

Applies to: RA6W1, RA6W2

The communication speed can now be specified when connecting to the target devices listed above using the -run-user-image command of the rfp-cli command-line software.

- Expanded UART communication speed support

Applies to: DA148xx, RA6W1, and RA6W2

Support has been added for connection at the communication speeds listed below when connecting to the target devices listed above via UART over a serial port.

Speeds: 9600 / 14400 / 19200 / 28800 / 38400 / 57600 bps

- -boundary option for the rfp-cli

In the -boundary option of the command-line software rfp-cli, only <Code Secure> can now be specified as an argument.

- -rfo command for the rfp-cli

The output format of Boundary information generated by the -read-flashoptions (-rfo) command of the command-line software rfp-cli has been changed. Note that there is no change to the output for target devices that support a NSC area.

3. Release Information on the Previous RFP V3 Products

3.1 Release Information on RFP V3.24.00

3.1.1 Additional target devices

Group	Part Number
RH850/U2B6-E	R7F7025Dx
RH850/U2B16-E	R7F7025Fx
RH850/U2C8	R7F702600, R7F702600A
RL78/G21	R7F103G6G, R7F103G6J, R7F103GBG, R7F103GBJ, R7F103GFG, R7F103GFJ, R7F103GGG, R7F103GGJ, R7F103GLG, R7F103GLJ
RL78/G23	R7F104GBG, R7F104GFJ, R7F104GGJ
Battery Management	RAJ242095
RX74M	R5K574M6, R5K574MC
RX74N	R5K574N6, R5K574NC

3.1.2 New features

- -cr command for the rfp-cli

Applies to: RA4E1, RA4M2, RA4M3, RA6E1, RA6M4, RA6M5, RA6T2, RX74x

In the command-line software rfp-cli, manual execution of challenge and response authentication is now supported using the -cr command when connecting to the target devices listed above. When this option is specified, the challenge value is displayed, and authentication is performed by entering a response value provided by the user. Note that when this option is specified, the authentication code specified by the -auth option is ignored.

- -run-user-image command for the rfp-cli

Applies to: RA6W1, RA6W2

In the command-line software rfp-cli, a command has been added to download user-created program data when connecting to the target devices listed above.

- Support for the E2 emulator Lite with RH850 MCUs

Applies to: RH850

The RFP now supports memory programming of RH850 MCUs via the E2 emulator Lite. Note that when using the E2 emulator Lite, only the UART interface is supported.

3.1.3 Improvements through changes to features

- Support for programming of external flash memory mounted on EK-RA6M3, EK-RA6M4 and EK-RA6M5

EK Board	External Flash Memory
EK-RA6M3	MX25L25645G
EK-RA6M4	MX25L25645G MX25LM51245GM
EK-RA6M5	

The RFP now supports the erasure and programming of external memory above. This feature is supported only when using the SWD interface. In addition, erasure, programming, and read operations cannot be performed when the target device is in the non-secure state.

- -writebit and -wite32 commands for the rfp-cli

Previously, when using the -writebit or -write32 command in the command-line software rfp-cli, they could only be executed as standalone operations; however, they can now be specified together with other operations.

- Support for chip erase on RA6W1 and RA6W2 devices

Applies to: RA6W1, RA6W2

Chip erase is now supported for the above target devices.

- Erase operation when the [Erase Chip] option is selected

Applies to: DA

When "Erase Chip" is selected in the GUI erase options, the same operation as "Erase All Blocks" is executed.

- Updating of the USB driver for E2 emulator and E2 emulator Lite

A new version of the USB driver for the E2 emulator and E2 emulator Lite has been released. This driver resolves an issue in which, due to a change in the Windows driver policy in April 2026, the USB driver for our emulator products could not be properly loaded on the host machine, preventing the emulator from being used.

Please install and use the latest versions of the integrated development environment and flash programming software. Older versions may not operate correctly. For details of this issue, please refer to the tool news below.

[Notes]Renesas Emulator and Flash Memory Programmer Products with a USB Interface Notice Regarding Changes to Windows Driver Policy

3.2 Release Information on RFP V3.23.00

3.2.1 Additional target devices

Group	Part Number
RA8D2	R7JA8D2JR, R7JA8D2JS, R7JA8D2KR, R7JA8D2KS
RA8M2	R7JA8M2JR, R7JA8M2JS
RA8P1	R7JA8P1JR, R7JA8P1JS, R7JA8P1KR, R7JA8P1KS
RA8T2	R7JA8T2JR, R7JA8T2JS, R7JA8T2LR, R7JA8T2LS
RH850/U2B12-E	R7F7025Cx
Battery Management	RAJ240091

3.2.2 Improvements through changes to features

- Support for external flash memory on DA148xx devices

Applies to: MX25UM51245G*1, PY25Q64LB

The RFP now supports the erasure and programming of external memory above.

Notes: 1. This external flash memory is not supported for UART connections.

- Support for USB Direct connection for RX devices on Linux and macOS

USB Direct connection for RX devices is now supported on both Linux and macOS.

- Support for UART connections through serial ports on macOS 15

UART connections through serial ports are now supported on macOS 15.

- End of support for macOS 14

macOS 14 has been removed from the set of supported operating systems.

- Support for macOS 26

macOS 26 was added as a supported OS.

- Support for J-Link nickname connection

Connection using J-Link nicknames is now supported. This feature is available only in the command-line software rfp-cli. Nicknames must include at least one non-numeric character. Refer to the SEGGER J-Link user's manual for details.

- Support for OTP programming on DA14531-00 and the RA6W2 Bluetooth LE subsystem

Programming of the OTP areas in DA14531-00 devices and the RA6W2 Bluetooth LE subsystem is now supported. When programming the OTP of the Bluetooth LE subsystem through RA6W2 via UART, select "UART Bridge" as the interface. In this mode, memory operations other than OTP programming of the Bluetooth LE subsystem are not available.

- RA device information during connection via the SWD interface

Applies to: RA2L2, RA4E1, RA4M2, RA4M3, RA6E1, RA6M4, RA6M5, and RA6T2

The device name and unique ID have been added to the device information output during connection via the SWD interface.

- Improvement to UART communication speed settings

Applies to: DA148xx, RA6W1, and RA6W2

An issue where UART communication via serial ports always operated at a fixed rate of 115200 bps in RFP V3.22.00 has been corrected.

- Extension of the [Skip ID Code Verify] option for RH850 Gen1 devices

Applies to: RH850 Gen1 (excluding RH850/P1x-C)

For the target devices above, the [Skip ID Code Verify] option on the [Operation Settings] tab is now always available.

3.3 Release Information on RFP V3.22.00

3.3.1 Additional target devices

Group	Part Number
RH850/U2B24-E	R7F7025Bx
RH850/U2B24-E EVA	R7F70259x

3.3.2 New feature

- -use-ip command for the rfp-cli

A command for making an IP connection with J-Link has been added to the rfp-cli command-line software. When this command is specified, the specification made for <serial> of the -tool command is used as the string for the IP connection. For details on the IP connection, refer to the user's manuals for Segger J-Link.

3.3.3 Improvements through changes to features

- Support for programming of external flash memory mounted on EK-RA8D2 and EK-RA8T2

EK Board	External Flash Memory
EK-RA8D2	IS25LX512M
EK-RA8T2	

The RFP now supports the erasure and programming of external memory above.

- Support for connection through a serial port in DA148xx, RA6W1, and RA6W2 devices

Applies to: DA14850, DA14870, RA6W1, and RA6W2

The RFP now supports UART connection through a serial port of the target devices above.

- Updating of the USB driver for USB Direct of RX devices

A new version of the USB driver for USB Direct of RX devices has been released. This version resolves an issue where the driver could not be loaded when "Memory integrity" in Windows Core isolation was enabled. If a USB-boot device is not recognized by RFP V3.20.00 or an earlier version after this product has been installed, change the USB driver to V1.1.9.0 or an earlier version. For details on the steps for changing the driver, refer to the Renesas Flash Programmer V3.22 User's Manual.

- Support for the new RPD file format

The RFP now supports the new RPD file format generated by e^2 studio and thus supports dual-core devices in the RA8 series.

3.4 Release Information on RFP V3.21.00

3.4.1 Additional target devices

Group	Part Number
RA0E3	R7FA0E303
RA8D2	R7KA8D2AD, R7KA8D2AF, R7KA8D2BD, R7KA8D2BF, R7KA8D2JF, R7KA8D2KF
RA8M2	R7KA8M2AD, R7KA8M2AF, R7KA8M2JF
RH850/U2C2	R7F702608A, R7F702615, R7F702615A
RL78/L23	R7F100LFE, R7F100LFG, R7F100LGE, R7F100LGG, R7F100LJE, R7F100LJG, R7F100LLE, R7F100LLG
RX14T	R5F514T5

3.4.2 Improvements through changes to features

- Support for block-level erasure of the flash memory on DA148xx, RA6W1, and RA6W2 devices

Applies to: DA148xx, RA6W1, RA6W2

Previously, only full-chip erasure of the external flash memory was supported on these devices. With this update, block-level erasure is now available.

Note: Projects created with earlier versions of RFP do not support block-level erasure. To use this feature, create a new project.

- Addition of DA148xx devices as target devices for the [Create and write product/image headers] option

DA148xx devices are now supported by the [Create and write product/image headers] option on the [Operation Settings] tabbed page.

- Support for programming of external flash memory mounted on EK-RA8M2

EK Board	External Flash Memory
EK-RA8M2	MX25LW51245G

The RFP now supports the erasure and programming of external memory above.

3.5 Release Information on RFP V3.20.00

3.5.1 Additional target devices

Group	Part Number
RA0L1	R7FA0L105, R7FA0L107
RA4C1	R7FA4C1BB, R7FA4C1BD
RA6W1*1	R7SA6W1AE, R7SA6W1BE, R7SA6W1CE, RRQ61001
RA6W2*1	R7JA6W2DE, RRQ61051
RA8T2	R7KA8T2AD, R7KA8T2AF, R7KA8T2CD, R7KA8T2CF, R7KA8T2LF
RH850/F1KM	R7F701A61, R7F701A62, R7F701A63
C30	R9A02G0150
DA148xx*2	DA14850, DA14870

Notes: 1. Devices of the RA6W1 and RA6W2 groups support the following types of flash memory: AT25SL641 and AT25SL641C
2. Devices of the DA148xx group support the following types of flash memory: MX25U25643GZ and MX25U6435

3.5.2 New feature

- Technical support

A link to the [Technical Support] page on the Renesas Web site was added to the [Help] menu on the menu bar. If you need a reply from us, you can send your questions from there.

3.5.3 Improvements through changes to features

- Support for programming of external flash memory mounted on EK-RA8P1 and EK-RA8E2

EK Board	External Flash Memory
EK-RA8P1	MX25LW51245G
EK-RA8E2	

The RFP now supports the erasure and programming of external memory above.

- End of support for Ubuntu 20.04 LTS

Ubuntu 20.04 LTS has been removed from the set of supported operating systems.

- Error message when memory in areas that do not support erasure was erased

Previously, when memory was erased only in the Config Area, the erasure processing was skipped. The specification has now been changed so that an error message is output in such cases. In addition, the error message which is output when memory was erased only in MRAM has been improved for clarity.

- Change to the initial value of the offset when a binary file is specified

Previously, when a binary file was specified, the initial value of the offset was “00000000”. The specification has now been changed so that the start address of memory in the target device is displayed.

- Change to the default state of the microcontroller in the [Create New Project] dialog box

Previously, “RA” had been selected as the default state in the [Create New Project] dialog box. The specification has now been changed so that no microcontroller is selected by default.

3.6 Release Information on RFP V3.19.00

3.6.1 Additional target devices

Group	Part Number
RA2L2	R7FA2L207, R7FA2L209
RA8P1	R7KA8P1AD, R7KA8P1AF, R7KA8P1BD, R7KA8P1BF, R7KA8P1JF, R7KA8P1KF
RH850/U2C4	R7F702606, R7F702606A, R7F702613, R7F702613A, R7F702614, R7F702614A, R7F702616A
RH850/U2C8-EVA	R7F702Z32, R7F702Z32A
RL78/L23	R7F100LFJ, R7F100LFL, R7F100LGJ, R7F100LGL, R7F100LJJ, R7F100LJL, R7F100LLJ, R7F100LLL, R7F100LMG, R7F100LMJ, R7F100LML, R7F100LPG, R7F100LPJ, R7F100LPL
DA1453x*	DA14533
DA1459x	DA14594

Note: Write a program to a DA1453x device with a size no greater than that of the RAM in each device. Operation in the case of writing a program with a larger size is not guaranteed.

3.6.2 Improvements through changes to features

- Change to the default state of the [Create and write product/image headers] option

Applies to: DA

The default setting of the [Create and write product/image headers] option on the [Operation Settings] tabbed page has been changed to enabled.

- End of support for macOS 13

macOS 13 has been removed from the set of supported operating systems.

- Support for macOS 15

macOS 15 was added as a supported OS.

- Display of the interface when USB Direct or COM Port is selected as the tool

When “USB Direct” or “COM port” is selected as the tool for the RFP, the selected interface is not indicated except in the case of RL78 devices.

- Controlling reset pins when the RFP is disconnected from the target device during connection with the E2 OB on-board emulator

When the E2 OB on-board emulator is used with RFP V3.18.00, the target device might not operate following its disconnection from the RFP even if [Reset Pin as Hi-Z] has been selected for [Reset signal at Disconnection] in the [Tool Details] dialog box of the RFP. However, this problem has now been corrected.

- Controlling reset pins when the RFP is disconnected from a connected DA device

After a program is written to a DA device, the RFP sets the reset pin to the low level and thus resets the target device when the RFP is disconnected from the target device. This enables normal operation of the device after release of the device from the reset state.

- Reading memory during connection of a DA device

When memory of a DA device was read in RFP V3.18.00, the [External Flash 1] area was not displayed in the [Read Memory Information] dialog box. However, this problem has now been corrected.

3.7 Release Information on RFP V3.18.00

3.7.1 Additional target devices

Group	Part Number
RA0E2	R7FA0E207, R7FA0E209
RA2T1	R7FA2T107
RA4L1	R7FA4L1BB, R7FA4L1BD
RL78/F22	R7F122F7G, R7F122FBG, R7F122FGG

3.7.2 New feature

- Support for programming of external flash memory mounted on EK-RA8M1 and EK-RA8D1

• EK Board	External Flash Memory
EK-RA8M1	S28HL512T
EK-RA8D1	

The RFP now supports the erasure and programming of external memory above. To enable the operation of external flash memory, select [Enable external memory settings] on the [External Memory Settings] tabbed page of the GUI or use the -external-loader command in the rfp-cli. When opening a project created by a previous RFP product, external flash memory operations will not work. To resolve this problem, re-create a new project.

3.7.3 Improvement through changes to a feature

- Changes to the order of programming areas via a serial interface

Applies to: RA2A1, RA2A2, RA2E1, RA2E2, RA2E3, RA2L1, RA4M1, RA4W1, RA6M1, RA6M2, RA6M3, RA6T1

The order of programming areas via a serial interface has now been changed as follows.

Before the change: Code Flash -> Config Area -> Data Flash

After the change: Code Flash -> Data Flash -> Config Area

3.8 Release Information on RFP V3.17.00

3.8.1 Additional target devices

Group	Part Number
RH850/U2B-FCC	R7F702Z23, R7F702Z28
RA8E1	R7FA8E1AF
RA8E2	R7FA8E2AF

3.8.2 Improvement through changes to a feature

- Changes to the order of programming areas via an SWD interface

Applies to: RA0E1, RA2A1, RA2A2, RA2E1, RA2E2, RA2E3, RA2L1, RA4E1, RA4M1, RA4M2, RA4M3, RA4W1, RA6E1, RA6M1, RA6M2, RA6M3, RA6M4, RA6M5, RA6T1, RA6T2

The order of programming areas via an SWD interface has now been changed as follows.

Before the change: Code Flash -> Config Area -> Data Flash

After the change: Code Flash -> Data Flash -> Config Area

3.9 Release Information on RFP V3.16.00

3.9.1 Additional target devices

Group	Part Number
RX260	R5F52606, R5F52607, R5F52608
RX261	R5F52616, R5F52617, R5F52618
RH850/U2B10	R7F70254x
RH850/U2B-FCC	R7F702Z21, R7F702Z26
DA1453x	DA14531, DA14535
RL78/F25	R7F125FGL, R7F125FLL, R7F125FML, R7F125FPL

3.9.2 Improvements through changes to features

- Support for firmware included in the SDK

The software has been updated to use the firmware included in the SDK for flash memory operations on DA devices. Accordingly, the supported external flash memory has been changed.

- External flash memory supported for DA devices

Group	External Flash Memory
DA1469x*1	MX25U3235F, GD25LE32, P25Q32SL
DA1470x*1	MX25U6432, W25Q64JWIM
DA1459x*1	MX25U3235F, W25Q32JWIM, W25Q32JWIQ
DA1453x*2	AT25XE021A, AT25DF021A, P25Q11U, MX25R2035F, W25X10CL, W25X20CL, AT25DF011, AT25DN011, AT25XE011, AT25EU0021A, AT25XE041B, GD25WD20

Notes: 1. DA devices that the external flash memory to be supported has been changed.
2. Write a program to a DA1453x device with a size no greater than that of the RAM in each device. Operation in the case of writing a program with a larger size is not guaranteed.
1., 2. If the program does not operate after it has been written, apply a reset.

- Erasure of the external flash memory in DA devices by rfp-cli

Previously, when the rfp-cli command-line software was used to specify the address range for erasing external flash memory, only erasing a specified range was possible. However, rfp-cli is now usable to erase all areas of external flash memory.

- Writing to RA or DA devices by using rfp-cli

When rfp-cli is used to specify the address range for writing to RA or DA devices via the SWD interface but the specified range violates the requirement for alignment, an address error is now generated.

- Support for Ubuntu 24.04 LTS

Ubuntu 24.04 LTS was added as a supported OS.

- SWD interface signal

The stability of communications of the SWD signal has now been improved for the combination of the E2 emulator and an RA device.

- Reduced startup time for rfp-cli

Startup time for the rfp-cli command-line software has been reduced.

3.10 Release Information on RFP V3.15.00

3.10.1 Additional target devices

Group	Part Number
RL78/G15	R5F12007, R5F12008
DA1470x*	DA14701, DA14705, DA14706, DA14708

Note: Although RFP V3.14.00 did not support some of these devices, this version now supports all devices.

3.10.2 Improvements through changes to features

- Changing the number for the OEM root public key

The number for the OEM root public key flash option has been changed from 1 to 0. This will change the GUI display of the [Flash Options] tabbed page and the following option of the rfp-cli command-line software.

Before the change: -fo oemrootkey1

After the change: -fo oemrootkey0

- Merging files

Simultaneous programming of user key files and all other files has now been possible in RA-family devices.

- End of support for Ubuntu 18.04 LTS

Ubuntu 18.04 LTS has been removed from the set of supported operating systems.

- Support for macOS 14

macOS 14* was added as a supported OS. Note that the GUI (RFPV3.exe) does not run under macOS 14.

*: macOS 14 Sonoma (only supported on machines with Apple silicon)

3.10.3 Removing a restriction

- Installing USB drivers for 32-bit versions of the Windows OS

3.11 Release Information on RFP V3.14.00

3.11.1 Additional target devices

Group	Part Number
RA8T1	R7FA8T1AF, R7FA8T1AH
RA2A2	R7FA2A2AD, R7FA2A2BD
RA0E1	R7FA0E105, R7FA0E107
RH850/U2B6	R7F70255x
RH850/U2B-FCC	R7F702Z22
RH850/F1KM	R7F701A64, R7F701A65, R7F701A66, R7F701A67, R7F701A68, R7F701A69, R7F701A70, R7F701A71, R7F701A72, R7F701A73, R7F701A74, R7F701A75, R7F701A76, R7F701A77, R7F701A78, R7F701A79, R7F701A80, R7F701A81, R7F701A82, R7F701A83, R7F701A84
RISC-V MCU G021	R9A02G021
DA1459x	DA14592
DA1470x*3	DA14701, DA14705, DA14706, DA14708

Notes: 1. DA1459x, DA1470x, and DA1469x devices support the following external flash memory chips.
MX25U3235F, GD25LE32, P25Q32SL, MX25U6432, and W25Q64JWIM
2. Before enabling the “Create and write product/image headers” feature to write a program file to a DA1469x or DA1470x device, set the Quad Enable bit for enabling (= 1) in the status register of the external flash memory.
3. Some devices are still unsupported, and in this case the E3000106 error occurs.
All DA1470x devices will be supported in V3.15.00. (Scheduled to be released on April 22, 2024)

3.11.2 New feature

- Support for macOS

macOS* was added as a supported OS. Note that the GUI (RFPV3.exe) does not run under macOS.

*: macOS 13 Ventura (only supported on machines with Apple silicon)

3.11.3 Improvements through changes to features

- Reduced startup time for rfp-cli and rpe

Startup time for the rfp-cli command-line software and rpe encryption utility program has been reduced.

- Increasing the speed of programming DA devices

Applies to: DA1469x

The speed of programming DA devices has now greatly been improved.

- Changing the names of microcontroller to be displayed in the [Create New Project] dialog box

Applies to: RISC-V MCU

The list name of RISC-V MCUs that are selectable in the [Create New Project] dialog box has been changed.

3.12 Release Information on RFP V3.13.00

3.12.1 Additional target devices

Group	Part Number
RA8M1	R7FA8M1AF, R7FA8M1AH
RA8D1	R7FA8D1AF, R7FA8D1AH, R7FA8D1BF, R7FA8D1BH
RA2E3	R7FA2E305, R7FA2E307
DA1469x*	DA14691, DA14695, DA14697, DA14699

Note: DA1469x devices support the following external flash memory chips.
MX25U3235F, GD25LE32, and W25Q64JWIM

3.12.2 New features

- Reading of HEX files with a specified address offset

A feature for adding an additive offset to the address when reading a HEX file has been added to the [Operation] tabbed page of the GUI.

- Added types of program file

Binary and sfp files have been added to the types of supported program files.

3.12.3 Improvements through changes to a feature

- Merging of features for selecting program files and user key files

The [User Keys] tabbed page of the GUI has been discontinued since user key files can now be selected on the [Operation] tabbed page. This simplifies the addition and removal of user key files and program files.

- Updating the J-Link firmware

A feature for updating the firmware of the J-Link debug probe from SEGGER has been added if the version of the firmware is earlier than that included with this product during connection of the RFP through the J-Link debug probe.

3.13 Release Information on RFP V3.12.00

3.13.1 Additional target device

Group	Part Number
RX26T	R5F526T8, R5F526TA

3.13.2 Improvements through changes to a feature

- Increasing the speed of programming via an SWD interface

Applies to: RA2A1, RA2E1, RA2E2, RA2L1, RA4E1, RA4M1, RA4M2, RA4M3, RA4W1, RA6E1, RA6M1, RA6M2, RA6M3, RA6M4, RA6M5, RA6T1, RA6T2

The speed of programming via an SWD interface has now greatly been improved.

- Merging files

Simultaneous programming of an image file (RPI file) created by the RFP or an encrypted program file (RPE file) and a user key file has now been possible.

- -write-rpi command for the rfp-cli

The result of output by the -write-rpi command for the rfp-cli command-line software has been changed. From this version of the RFP, specification of the address range and the unit for writing to flash memory are applied to the generated RPI files. However, no change has been made to the RPI files generated by the -output-file command.

3.14 Release Information on RFP V3.11.02

3.14.1 Additional target devices

Group	Part Number
RA6T3	R7FA6T3BB
RL78/G16	R5F1211A, R5F1211C, R5F1214A, R5F1214C, R5F1216A, R5F1216C, R5F1217A, R5F1217C, R5F121BA, R5F121BC
RL78/G24	R7F101G6E, R7F101G6G, R7F101G7E, R7F101G7G, R7F101G8E, R7F101G8G, R7F101GAE, R7F101GAG, R7F101GBE, R7F101GBG, R7F101GEE, R7F101GEG, R7F101GFE, R7F101GFG, R7F101GGE, R7F101GGG, R7F101GJE, R7F101GJG, R7F101GLE, R7F101GLG
RX23E-B	R5F523E5B, R5F523E5J, R5F523E5K, R5F523E5L, R5F523E5M, R5F523E5N, R5F523E6B, R5F523E6J, R5F523E6K, R5F523E6L, R5F523E6M, R5F523E6N
RX26T	R5F526T9, R5F526TB, R5F526TF

3.14.2 New features

- -file-offset command for the rfp-cli

A command for appending an offset value for addition during reading of a HEX file has been added to the rfp-cli command-line software.

- -checksum-type command for the rfp-cli

A command for specifying the checksum type has been added to the rfp-cli command-line software.

3.14.3 Improvements through changes to a feature

- Checksum type

Applies to: RL78, except for RL78/G10, G1M, G1N, G15, and G16 devices

A 16-bit additive method has been added as a type of checksum calculation for RL78 devices.

- Increasing the speed of reading via an SWD interface

The speed of reading via an SWD interface through the J-Link debug probe from SEGGER has now greatly been improved. This improves the speed of reading and verifying memory.

- Cancelling the erase command

The problem of an inability to cancel an erase command being executed via an SWD interface in some devices has been fixed.

- -pv command for the rfp-cli

A -pv command which combines the program (-p) and verify (-v) commands has been added to the rfp-cli command-line software.

- End of support for Windows 7 and Windows 8.1

Windows 7 and Windows 8.1 have been removed from the set of supported operating systems.

- Selecting a tool during connection of multiple J-Link debug probes

The facility has been improved to allow the selection of a tool during connection of multiple J-Link debug probes from SEGGER.

3.15 Release Information on RFP V3.11.01

3.15.1 Additional target devices

Group	Part Number
RH850/U2A6	R7F702302
RH850/U2A8	R7F702301B
RH850/U2A16	R7F702300B
RISC-V/VC	R9A06G150
RA4E2	R7FA4E2B9
RA4T1	R7FA4T1B9, R7FA4T1BB
RA6E2	R7FA6E2B9, R7FA6E2BB
RL78/F23	R7F123FBG, R7F123FGG, R7F123FLG, R7F123FMG
RL78/G22	R7F102G4C, R7F102G4E, R7F102G6C, R7F102G6E, R7F102G7C, R7F102G7E, R7F102G8C, R7F102G8E, R7F102GAC, R7F102GAE, R7F102GBC, R7F102GBE, R7F102GCC, R7F102GCE, R7F102GEC, R7F102GEE, R7F102GFC, R7F102GFE, R7F102GGC, R7F102GGE
RX65W-A	R5F565WE

3.15.2 New feature

- Support for Ubuntu 22.04 LTS

Ubuntu 22.04 LTS has been added as a supported OS.

3.15.3 Improvements through changes to a feature

- Increasing the speed of programming via an SWD interface

The speed of programming via an SWD interface through the J-Link debug probe from SEGGER has now greatly been improved.

- Support for programming via an SWD interface

Applies to: RA4E1, RA4M2, RA4M3, RA6E1, RA6M4, RA6M5, RA6T2

The above target devices have now been added to those with support for programming via an SWD interface through the J-Link debug probe from SEGGER, the E2 emulator, or the E2 emulator Lite. Note that those target devices also have facilities which do not allow for programming via an SWD interface. For details, refer to “SWD interface connection”.

- Discontinuation of the Renesas Flash Programmer utility program

The Renesas Flash Programmer utility program, rfp-util.exe, which had been bundled with this product, has been discontinued. Use the Security Key Management Tool as the successor software.

3.16 Release Information on RFP V3.11.00

3.16.1 Additional target devices

Group	Part Number
RL78/G15	R5F12017, R5F12018, R5F12047, R5F12048, R5F12067, R5F12068
Battery Management	RAJ240055, RAJ240057
RISC-V/MC	R9A02G020

3.16.2 New feature

- Giving feedback

A feature for giving feedback has been added to the [Help] menu on the menu bar. You can select this item and then submit your opinions or impressions by using the [Give Feedback] form.

3.16.3 Improvements through changes to a feature

- [Block Settings] tabbed page

The settings for blocks to be erased ([Erase] column) and programmed and verified ([P.V] column) have been integrated into a [Select] column.

- Output for the types of checksum calculation to a log

The log format of the types of calculation used for the output of calculated checksums has been modified.

3.16.4 Removing restrictions

- Writing to the code flash memory of an RL78/F24 for secure boot
- Operation after connection through the SWD interface

3.16.5 Errata for User's Manual

The following OS described in the RFP V3.11.00 User's Manual is not supported. The following OS will be supported from the next version.

“Linux (Ubuntu 22.04 LTS, x64/ARM32/ARM64)”

3.17 Release Information on RFP V3.10.00

3.17.1 Additional target devices

Group	Part Number
RX660	R5F56604, R5F56609

3.17.2 New feature

- Support for programming via an SWD interface

Applies to: RA

The RFP now supports programming by an SWD interface via the J-Link debug probe from SEGGER, the E2 emulator, or the E2 emulator Lite. For the target devices, refer to “List of MCUs supported by Renesas Flash Programmer V3”.

3.17.3 Improvement through changes to a feature

- Connection via a serial interface by J-Link

Applies to: RA

The problem that the RFP did not operate with the J-Link debug probe from SEGGER via a serial interface has been corrected. However, note that the RFP does not operate with some versions of the J-Link hardware and firmware. For more information, refer to the following Web page.
https://www.renesas.com/rfp#system

3.18 Release Information on RFP V3.09.02

3.18.1 Additional target devices

Group	Part Number
RH850/F1KM	R7F701A55, R7F701A56, R7F701A57, R7F701A58, R7F701A59, R7F701A60
RX140	R5F51405, R5F51406

3.18.2 Improvements through changes to a feature

- Change to the default state of the [Skip blank areas] option

The default setting of the [Skip blank areas] option has been changed to enabled in the [Read Memory] dialog box.

- Support for Windows 11

Windows 11 has been added as a supported OS.

3.19 Release Information on RFP V3.09.01

3.19.1 Additional target devices

Group	Part Number
RL78/F24	R7F124FBJ, R7F124FGJ, R7F124FLJ, R7F124FMJ, R7F124FPJ
RL78/G23	R7F100GAH, R7F100GBH, R7F100GCH, R7F100GEH, R7F100GFH, R7F100GGH, R7F100GJH, R7F100GLH, R7F100GMH, R7F100GPH
RH850/F1KM	R7F701760, R7F701762, R7F701764
RH850/U2A8	R7F702301, R7F702301A
RH850/U2A16	R7F702300A
RH850/U2A-EVA	R7F702Z19B
Battery Management	RAJ240310
C30	R9A02G0151

3.19.2 New features

- -key-password and -mac-password commands for the rfp-cli

Applies to: RL78/F2x

Commands for specifying the key and MAC passwords which are required for writing to security data of an RL78/F2x have been added to the rfp-cli command-line software.

- -output-file command for the rfp-cli

A command for merging the specified program data to be output as a file without connecting the target device has been added to the rfp-cli command-line software.

Output file formats:

- HEX files in Motorola S format
- HEX files in Intel HEX format
- RPI files

3.19.3 Improvements through changes to a feature

- Microcontroller types to be displayed during the creation of a new project

Applies to: RL78

The name of the list of RL78 microcontrollers for selection when a new project is created has been changed.

- COM connection of RL78/G10, RL78/G1M and RL78/G1N

Applies to: RL78/G10, RL78/G1M, RL78/G1N

We have changed processing of connection to the COM port.

3.19.4 Removing a restriction

- SVR settings for the RH850/U2A16 group

3.20 Release Information on RFP V3.09.00

3.20.1 Additional target devices

Group	Part Number
RA2E2	R7FA2E2A3, R7FA2E2A5, R7FA2E2A7
RL78/G23	R7F100GFK, R7F100GFL, R7F100GGK, R7F100GGL, R7F100GJK, R7F100GJL, R7F100GLK, R7F100GLL, R7F100GMK, R7F100GML, R7F100GPK, R7F100GPL, R7F100GSK, R7F100GSL
RA6T2	R7FA6T2AB, R7FA6T2AD, R7FA6T2BB, R7FA6T2BD

3.20.2 New features

- Indication by error messages

Applies to: All devices

Description: When an error that is relatively frequent occurs, the log shows the URL for a page that describes the details and the actions to be taken.

- Reading of e^2 studio Renesas Partition Data Files

Applies to: RA

Description: To make the settings of flash option data on boundaries, the RFP now supports the reading of Renesas Partition Data Files output by the e^2 studio.

3.20.3 Improvements through changes to a feature

- Display of recently used projects

Applies to: All devices

Description: The number of recently used project files that are displayed has been increased from four to eight.

- Removal of the function for displaying licenses

Applies to: All devices

Description: Since providing the products on CD-ROM was discontinued, the function for displaying licenses has been removed.

- Connection via the USB serial-conversion IC from FTDI

Applies to: RL78/G10, RL78/G1M, RL78/G1N

Description: The stability of the connection when the USB serial-conversion IC from FTDI is in use has been improved.

- Change of the displayed name of the extended data area

Applies to: RH850 with an extended data area

Description: The displayed name of the extended data area has been changed to Data Flash 2.

- Change to the specifications of the calcresponse command of rfp-util

Applies to: All devices

Description: An algorithm name parameter has been added for the calcresponse command of the rfp-cli command-line software.

- Loading of the J-Link library

Applies to: RA

Description: The problem of frequent failures in loading of the J-Link library during connection of the tool when J-Link software is not installed under Linux has been corrected.

3.21 Release Information on RFP V3.08.03

3.21.1 Additional target devices

Group	Part Number
RA4E1	R7FA4E10B, R7FA4E10D
RA6E1	R7FA6E10D, R7FA6E10F
RL78/G23	R7F100GAJ, R7F100GBJ, R7F100GCJ, R7F100GEJ, R7F100GFJ, R7F100GGJ, R7F100GJJ, R7F100GLJ, R7F100GMJ, R7F100GPJ, R7F100GSJ
RX140	R5F51403
RX671	R5F56719, R5F5671C, R5F5671E

3.22 Release Information on RFP V3.08.02

3.22.1 Additional target devices

Group	Part Number
RL78/G23	R7F100GAF, R7F100GAG, R7F100GBF, R7F100GBG, R7F100GCF, R7F100GCG, R7F100GEF, R7F100GEG, R7F100GFF, R7F100GFG, R7F100GFN, R7F100GGF, R7F100GGG, R7F100GGN, R7F100GJF, R7F100GJG, R7F100GJN, R7F100GLF, R7F100GLG, R7F100GLN, R7F100GMG, R7F100GMN, R7F100GPG, R7F100GPN, R7F100GSN

3.22.2 New feature

- Support for ARM32 and ARM64 Linux

Applies to: All devices

Description: ARM32 and ARM64 have been added to the architectures for which Linux is supported.

3.22.3 Improvement through changes to a feature

- Improvement of error messages when the RFP is connected to a target device

3.23 Release information on RFP V3.08.01

3.23.1 Additional target devices

Group	Part Number
RA2E1	R7FA2E1A5, R7FA2E1A7, R7FA2E1A9
RA4M2	R7FA4M2AB, R7FA4M2AC, R7FA4M2AD
RA4M3	R7FA4M3AD
RA6M5	R7FA6M5AG, R7FA6M5AH, R7FA6M5BF, R7FA6M5BG, R7FA6M5BH
RL78/I1C	R5F10NML, R5F10NPL
RH850/U2A16	R7F702300
RH850/U2A-EVA	R7F702Z19A
RE01B	R7F0E01BD

3.23.2 Removing a restriction

- RPI file

3.24 Release information on RFP V3.08.00

3.24.1 Additional target devices

Group	Part Number
RA2L1	R7FA2L1A8, R7FA2L1A9
RA4M3	R7FA4M3AE, R7FA4M3AF
RA6M4	R7FA6M4AD, R7FA6M4AE, R7FA6M4AF
RA6T1	R7FA6T1AB, R7FA6T1AD
RX23E-A	R5F523E5S, R5F523E6S

3.24.2 New features

- Support for Linux

Applies to: All devices

Description: New rfp-cli software has been added for the RFP command line which supports Ubuntu*. This allows operation from the command line alone and does not require settings by the GUI. Command-line operation is also available under Windows. However, these types of command line operation are not compatible with the simple command line operations of the RFP GUI.

*: 18.04 LTS Desktop, 64-bit and 20.04 LTS Desktop, 64-bit

- Support for the J-Link debug probe from SEGGER

Applies to: RA

Description: The RFP now supports programming by the J-Link debug probe from SEGGER via a serial interface.

- Addition of the support for the security functions of the RA family

Applies to: RA

Description: The RFP now supports the TrustZone and device life-cycle management (DLM) security functions of the RA family.

3.24.3 Change to a feature

- Parameter files for the RA family

Applies to: RA

Description: The format of the parameter files which are automatically generated by the RFP has been changed. If a project file for an RA family device which has been created with a previous version of the product (V3.06.03 or an earlier version) is read with the RFP V3.08.00 or a later version, the following error messages will appear; create a new project.

Error (E3000008): This file is corrupt and cannot be opened (path to the parameter file; line: X).

Error (E0000015): The parameter file is not correct.

3.25 Release information on RFP V3.06.02

3.25.1 Additional target devices

Group	Part Number
RL78/G1M	R5F11W67, R5F11W68
RL78/G1N	R5F11Y67, R5F11Y68
RH850/E2H	R7F702011
RH850/E2UH	R7F702012A
RH850	R7F702Z11A, R7F702Z12
RE01_256KB	R7F0E0108, R7F0E0118

3.26 Release information on RFP V3.06.01

3.26.1 Additional target devices

Group	Part Number
RH850/E2M	R7F702002A
RH850	R7F702Z02C, R7F702Z04C
RL78/F1E	R5F11KLE, R5F11KLF, R5F11KLG, R5F11LLE, R5F11LLF, R5F11LLG
RA2A1	R7FA2A1AB
RA4M1	R7FA4M1AB
RA6M1	R7FA6M1AD
RA6M2	R7FA6M2AD, R7FA6M2AF
RA6M3	R7FA6M3AF, R7FA6M3AH
RL78/G13A	R5F140FK, R5F140FL, R5F140GK, R5F140GL, R5F140LK, R5F140LL, R5F140PK, R5F140PL
RL78/G1P	R5F11Z7A, R5F11ZBA
RL78/I1C	R5F11TLE, R5F11TLG
RA4W1	R7FA4W1AD
RE01_1500KB	R7F0E014D, R7F0E015D, R7F0E016D, R7F0E017D
RX66N	R5F566ND, R5F566NN
RX72N	R5F572ND, R5F572NN
RL78	R5F11VBG, R5F11VLG
RX13T	R5F513T3, R5F513T5

3.27 Release information on RFP V3.06.00

3.27.1 Additional target devices

Group	Part Number
RX23E-A	R5F523E5A, R5F523E6A
RX72M	R5F572MD, R5F572MN
RX23W	R5F523W7, R5F523W8

3.27.2 New features

- Addition of the feature for encrypting program files

Applies to: All devices

Description: A feature for encrypting program files has been added. Executing the encryption utility program from the command line allows the encryption with a password of program files.

- Expansion of command-line options

Applies to: All devices

Description: New commands (bin, read32, write32 and writebit) have been added to those specifiable as command-line options.

- Addition of the feature for standard output from the command line

Applies to: All devices

Description: A feature for displaying a log and the state of progress in standard output from the command line when commands are executed has been added.

3.27.3 Removing a restriction

- Settings of lock bits or OTP of the RH850/C1M-A2 group

3.28 Release information on RFP V3.05.03

3.28.1 Additional target devices

Group	Part Number
RH850/F1KH	R7F701708, R7F701709, R7F701710, R7F701711, R7F701714, R7F701715
RH850/F1KM	R7F701652, R7F701653
RH850	R7F701417, R7F701437
RX66T	R5F566TFA, R5F566TFB, R5F566TFC, R5F566TFE, R5F566TFF, R5F566TFG, R5F566TKA, R5F566TKB, R5F566TKC, R5F566TKE, R5F566TKF, R5F566TKG
RX72T	R5F572TFA, R5F572TFB, R5F572TFC, R5F572TFE, R5F572TFF, R5F572TFG, R5F572TKA, R5F572TKB, R5F572TKC, R5F572TKE, R5F572TKF, R5F572TKG

3.28.2 Removing a restriction

- Enabling of the intelligent cryptographic unit slave E (ICUSE) of the RH850/C1M-A, RH850/F1K, RH850/F1KM-S1, RH850/P1L-C, and RH850/P1M-E groups

---

3.29 Release information on RFP V3.05.01

3.29.1 Additional target devices

Group	Part Number
RX66T	R5F566TA, R5F566TE
RH850	R7F701Z05A, R7F701Z06A, R7F701Z07A, R7F701Z11, R7F701Z12, R7F701Z12A
S5D3	R7FS5D37A
Battery Management	RAJ240047, RAJ240071, RAJ240075
C30	R9J02G012

3.30 Release information on RFP V3.05.00

3.30.1 Additional target devices

Group	Part Number
RX130	R5F51305B, R5F51306B

3.30.2 New features

- Expansion of command-line options

Applies to: All devices

Description: New commands have been added to those specifiable as command-line options. In addition to the existing specification of program files, the command can be executed with the specification of a tool or commands, by which the settings can be replaced with those in the project file.

- Support of relative paths for files

Applies to: All devices

Description: The specification has been changed so that the following files are saved with relative paths when they are placed under the project directory.

• Program file

• Unique code file

- Addition of the feature for displaying projects that have recently been used

Applies to: All devices

Description: A feature for displaying the names of project files that have most recently been used (up to four names) has been added to the [File] menu. A filename can be selected to open the given project.

3.30.3 Improvement through changes to a feature

- Change to the feature for generating RPI files

Applies to: All devices

Description: The specification has been changed so that the following settings are reflected in [Save Image File] from the [File] menu.

• [P.V] on the [Block Setting] tabbed page

• [Fill with 0xFF] on the [Operation Setting] tabbed page

Note: Due to this change, RPI files may not perfectly match those that have been output by V3.04.00 and earlier versions.

3.30.4 Removing a restriction

- Setting lock bits in RX MCUs

3.31 Release information on RFP V3.04.00

3.31.1 Additional target devices

Group	Part Number
RH850/C1M-A	R7F701275
RH850/D1M	R7F701441, R7F701442, R7F701461, R7F701462
RH850/F1H	R7F701511, R7F701512, R7F701526, R7F701528
RH850/F1KM	R7F701644, R7F701645, R7F701646, R7F701647, R7F701648, R7F701649, R7F701650, R7F701651, R7F701652, R7F701653, R7F701684, R7F701685, R7F701686, R7F701687, R7F701688, R7F701689, R7F701690, R7F701691, R7F701692, R7F701693, R7F701694, R7F701695
RL78/G11	R5F1051A, R5F1054A
RL78/H1D	R5F11NGF, R5F11NGG, R5F11NLF, R5F11NLG, R5F11NME, R5F11NMF, R5F11NMG, R5F11RMG
S3A1	R7FS3A17C
S5D5	R7FS5D57C

3.31.2 New features

- Support for the E2 emulator with RX MCUs

Applies to: RX

Description: The RFP now supports programming of flash memory of RX MCUs via the E2 emulator.

- Display of the checksums of files in particular areas of flash memory

Applies to: RH850, RL78, RX

Description: A [File Checksum] feature has been added under the [File] menu. The checksums of program files in particular areas are displayed in the [Log output] panel. For the RL78, the checksums can be calculated within block-selection ranges.

- Release from license authentication

Applies to: All devices

Description: A feature for release from license authentication has been added.

3.32 Release information on RFP V3.03.01

3.32.1 Additional target device

Group	Part Number
Motor control IC	RAJ306000

3.32.2 Removing restrictions

- An error occurring during installation of the USB Driver for USB Boot MCU Type B
- A connection error occurring with the E2 emulator (revision B)

3.33 Release information on RFP V3.03.00

3.33.1 Additional target devices

Group	Part Number
S3A6	R7FS3A677, R7FS3A678
RH850/F1H	R7F701534
RH850/F1K	R7F701542, R7F701543, R7F701546, R7F701547, R7F701557, R7F701560, R7F701561, R7F701562, R7F701563, R7F701566, R7F701567, R7F701577, R7F701580, R7F701582, R7F701586, R7F701597, R7F701602, R7F701603, R7F701610, R7F701611, R7F701612, R7F701613, R7F701620, R7F701621, R7F701622, R7F701623
RH850/P1L-C	R7F701388, R7F701389, R7F701390, R7F701391
RH850/P1M-E	R7F701375, R7F701376, R7F701377, R7F701378, R7F701379, R7F701380, R7F701381, R7F701382, R7F701383, R7F701384, R7F701385, R7F701386
Battery Management	RAJ240045, RAJ240080, RAJ240090, RAJ240100, RAJ240500
RX130	R5F51305, R5F51306, R5F51307, R5F51308
RX651	R5F5651C, R5F5651E
RX65N	R5F565NC, R5F565NE

3.33.2 New features

- Support for the E2 emulator with RL78 MCUs

Applies to: RL78

Description: The RFP now supports programming of flash memory of RL78 MCUs via the E2 emulator.

- Addition to handling of out-of-range errors for the memory of the MCU

Applies to: All devices

Description: Previously, when an attempt at access to data out of the range of memory in the MCU was detected, the RFP output a warning message and continued processing. However, in such cases now, the RFP can be set to generate an error and stop processing with an optional function from V3.03.00.

3.33.3 Improvement through changes to a feature

- Change to filling with 0xFF

Applies to: All devices

Description: For [Fill with 0xFF] in the [Operation Setting] tabbed page, the specification has been changed so that the target area can be selected but the configuration area is not selectable as a target. Since information on the setting for [Fill with 0xFF] is not carried over if a project that was created in V3.02.01 or an earlier version is read, change the setting as required.

3.34 Release information on RFP V3.02.01

3.34.1 Additional target devices

Group	Part Number
S128	R7FS12877, R7FS12878
S3A3	R7FS3A37A
S5D9	R7FS5D96C, R7FS5D96E, R7FS5D97C, R7FS5D97E
RH850/F1H	R7F701530
RH850/P1H-C	R7F701372A
RH850/P1M	R7F701305, R7F701323
RH850/P1M-C	R7F701373A, R7F701374A
RX24T	R5F524TB, R5F524TC, R5F524TE
RX24U	R5F524UB, R5F524UC, R5F524UE

3.34.2 New feature

- Support for the E2 emulator with RH850 MCUs

Applies to: RH850

Description: The RFP now supports programming of flash memory of RH850 MCUs via the E2 emulator.

3.35 Release information on RFP V3.02.00

3.35.1 Additional target devices

Group	Part Number
S124	R7FS12476, R7FS12477
S3A7	R7FS3A77C
S7G2	R7FS7G27G, R7FS7G27H
RH850/E1M-S2	R7F701215, R7F701216
RH850/F1H	R7F701506, R7F701507, R7F701522, R7F701524, R7F701525, R7F701527, R7F701529, R7F701531
RH850/F1K	R7F701581, R7F701583, R7F701587
RH850/F1M	R7F701544, R7F701545, R7F701552, R7F701564, R7F701572
RH850/P1H-C	R7F701371, R7F701372
RH850/P1M-C	R7F701373, R7F701374
RL78/F15	R5F113GK, R5F113LK, R5F113MK, R5F113PG, R5F113PH, R5F113PJ, R5F113PK
RL78/G11	R5F1056A, R5F1057A, R5F1058A
RL78/I1C	R5F10NLE, R5F10NME, R5F10NMJ, R5F10NPG
RL78/L1A	R5F11MMD, R5F11MME, R5F11MMF, R5F11MPE, R5F11MPF, R5F11MPG
RX651	R5F56514, R5F56517, R5F56519
RX65N	R5F565N4, R5F565N7, R5F565N9

3.35.2 New feature

- Support for Renesas Synergy™ microcontrollers

Applies to: Renesas Synergy™

Description: The RFP now supports Renesas Synergy™ microcontrollers. Note that the supported versions may differ according to the microcontroller. For details, refer to "List of MCUs supported by Renesas Flash Programmer V3" on the Renesas Web site.

3.36 Release information on RFP V3.01.00

3.36.1 Additional target devices

Group	Part Number
RH850/C1H	R7F701270
RH850/C1M	R7F701271
RH850/D1L	R7F701402, R7F701403, R7F701422, R7F701423
RH850/D1M	R7F701404, R7F701405, R7F701406, R7F701407, R7F701408, R7F701410, R7F701411, R7F701412, R7F701428, R7F701430, R7F701431, R7F701432
RH850/F1M	R7F701549
RH850/P1M	R7F701304, R7F701313, R7F701315, R7F701320, R7F701321, R7F701322
RX24T	R5F524T8, R5F524TA
RL78/F15	R5F113GL, R5F113LL, R5F113ML, R5F113PL, R5F113TG, R5F113TH, R5F113TJ, R5F113TK, R5F113TL
RL78/G1H	R5F11FLJ, R5F11FLK, R5F11FLL
RL78/I1C	R5F10NLG, R5F10NMG, R5F10NPJ
RL78/L1A	R5F11MMD, R5F11MME, R5F11MMF, R5F11MPE, R5F11MPF, R5F11MPG

3.36.2 New features

- Display of the checksums of files

Applies to: All devices

Description: When a file is selected in the [Program File] area on the [Operation] tabbed page, the checksum of the file as a whole is displayed within the [Program File] area and output in the log output panel.

- Loading multiple program files

Applies to: All devices

Description: The RFP is now capable of loading multiple program files. All of the files selected by the user are combined before being programmed in the flash memory.

- Importing license files

Applies to: All devices

Description: The RFP is now capable of importing license files.

- Programming of unique codes

Applies to: All devices

Description: The RFP now supports programming of a unique code in a designated area of flash memory.

- Generating RPI files

Applies to: All devices

Description: The RFP is now capable of generating RPI files, which contain data from a designated area of code flash or data flash memory, along with the flash option settings.

- Entering user-specified bit-rates for COM connections

Applies to:	All devices
Description:	While the values of [Speed] were only selectable from the pull-down menu on the [Connect Setting] tabbed page in V3.00.00 and earlier versions, V3.01.00 allows the user to enter a desired bit-rate (but only in the case of a COM connection).

3.36.3 Improvement through changes to a feature

- Using a board that includes the UPD78F0730 microcontroller, which supports serial (COM) connection through a virtual USB driver

Applies to:	All devices
Description:	V3.01.00 of the RFP is also capable of programming by using a board that include a UPD78F0730 microcontroller of the 78K0 family, which supports serial (COM) connection through a virtual USB driver. Programming in this way may lead to the following error if V3.00.00 or an earlier version is in use. E4000003: A timeout error occurred. <Example of an applicable board> EZ-0012 evaluation board for DC/DC LED control by the RL78/I1A* *: For other Renesas evaluation boards equipped with the UPD78F0730, check the corresponding manuals.

3.36.4 Removing restrictions

- Errors occurring when commands are executed in the boot mode (USB interface) of MCUs of the RX64M and RX71M groups
- Self-checking of the E1 or E20 emulator leading to errors

3.37 Release history of the RFP

Version	Date of Release
V3.25.00	Oct. 2026
V3.24.00	Jul. 2026
V3.23.00	Apr. 2026
V3.22.00	Jan. 2026
V3.21.00	Oct. 2025
V3.20.00	Jul. 2025
V3.19.00	Apr. 2025
V3.18.00	Jan. 2025
V3.17.00	Oct. 2024
V3.16.00	Jul. 2024
V3.15.00	Apr. 2024
V3.14.00	Jan. 2024
V3.13.00	Oct. 2023
V3.12.00	Jul. 2023
V3.11.02	Apr. 2023
V3.11.01	Jan. 2023
V3.11.00	Oct. 2022
V3.10.00	Jul. 2022
V3.09.02	Apr. 2022
V3.09.01	Jan. 2022
V3.09.00	Oct. 2021
V3.08.03	Jul. 2021
V3.08.02	Apr. 2021
V3.08.01	Jan. 2021
V3.08.00	Oct. 2020
V3.06.02	Jul. 2020
V3.06.01	Oct. 2019
V3.06.00	Aug. 2019
V3.05.03	Apr. 2019
V3.05.01	Nov. 2018
V3.05.00	Jul. 2018
V3.04.00	Jan. 2018
V3.03.01	Nov. 2017
V3.03.00	Jul. 2017
V3.02.01	Jan. 2017
V3.02.00	Oct. 2016
V3.01.00	May 2016
V3.00.00	Dec. 2015

4. Restrictions

4.1 List of restrictions

No.	Restriction	Target	Corresponding Version	Corrected Version
1	Errors occurring when commands are executed in the boot mode (USB interface) of MCUs of the RX64M and RX71M groups	RX64M RX71M	V3.00.00	V3.01.00
2	Self-checking of the E1 or E20 emulator leading to errors	All	V3.00.00	V3.01.00
3	An error occurring during installation of the USB Driver for USB Boot MCU Type B	Renesas Synergy™ RX651 RX65N	V3.02.00 to V3.03.00	V3.03.01
4	A connection error occurring with the E2 emulator (revision B)	RH850 RL78	V3.02.01 to V3.03.00	V3.03.01
5	Setting lock bits in RX MCUs	RX21x, RX22x, RX610, RX62x, RX63x, RX64M, RX71M	V3.00.00 to V3.04.00	V3.05.00
6	Enabling of the intelligent cryptographic unit slave E (ICUSE) of the RH850/C1M-A, RH850/F1K, RH850/F1KM-S1, RH850/P1L-C, and RH850/P1M-E groups	RH850/C1M-A RH850/F1K RH850/F1KM-S1 RH850/P1L-C RH850/P1M-E	V3.00.00 to V3.05.02	V3.05.03
7	Settings of lock bits or OTP of the RH850/C1M-A2 group	RH850/C1M-A2 (R7F701275)	V3.05.00 to V3.05.03	V3.06.00
8	RPI file	RL78 family (excluding RL78/G10, RL78/G1M, and RL78/G1N) Battery Management Renesas USB Power Delivery family (C30 group) Motor Driver/ Actuator Driver ICs (motor control ICs)	V3.08.00	V3.08.01
9	SVR settings for the RH850/U2A16 group	RH850/U2A16	V.3.09.00	V3.09.01
10	Writing to the code flash memory of an RL78/F24 for secure boot	RL78/F24	V3.09.01 to V3.10.00	V3.11.00

11	Operation after connection through the SWD interface	RA2A1, RA2E1, RA2E2, RA2L1, RA4M1, RA4W1, RA6M1, RA6M2, RA6M3, RA6T1	V3.10.00	V3.11.00
12	SWD interface connection	RA4E1, RA4M2, RA4M3, RA6E1, RA6M4, RA6M5, RA6T2	V3.11.01 and later versions	—
13	Installing USB drivers for 32-bit versions of the Windows OS	—	V3.12.00 to V3.14.00	V3.15.00

4.2 Details of restrictions

No. 1 Errors occurring when commands are executed in the boot mode (USB interface) of MCUs of the RX64M and RX71M groups

Applies to: RX64M and RX71M groups

Description: The following error will occur if commands such as for writing are executed while a target device is connected and is in boot mode (for the USB interface).

E100000D: A flow error occurred in the device. (Response 34:C3)

Corrected version: V3.01.00

No. 2 Self-checking of the E1 or E20 emulator leading to errors

Applies to: All devices

Description: Executing the self-checking program for an E1 or E20 emulator that has been connected with V3.00.00 of the Renesas Flash Programmer leads to errors.

The following are the log entries relating to errors in the self-checking program.

[Result of TEST1] FAIL (Error 1103)

[Error Message] The E1/E20 self-check has failed.

[Error Detail] Internal module check has failed.

Facilities other than self-checking (flash programming and debugging) will operate correctly.

Supplementary Note:

Connecting the V3.00.00 Renesas Flash Programmer to an E1 or E20 emulator leads to overwriting of the firmware in the emulator. This leads to errors when the self-checking program for the emulator is executed.

Corrected version: V3.01.00

No. 3 An error occurring during installation of the USB Driver for USB Boot MCU Type B

Applies to: Renesas Synergy™, RX651 and RX65N group

Description: When using the applicable products shown in section 3.1 (No. 3), the following error may occur during installation of the USB Driver for USB Boot MCU Type B V1.00.00 (for Renesas Synergy™ microcontrollers and RX651 and RX65N groups in the RX family), and installation may not succeed. If the error does not occur, installation was successful.

E0140021: Some installations have failed. The installations of the specified tools are not completed

Corrected version: V3.03.01

No. 4 A connection error occurring with the E2 emulator (revision B)

Applies to: RH850, RL78

Description: When using the applicable products shown in section 3.1 (No. 4) and connecting the Renesas Flash Programmer to the MCU via the E2 emulator (revision B), the following error occurs, and connection is not established.

E30002FE: This tool is not supported

Note: E2 emulator revision B can be confirmed by the label on the back of the main unit.

- The Ⓑ mark is attached.



- The end of the serial No. is other than “A”.



Corrected version: V3.03.01

No. 5 Setting lock bits in RX MCUs

Applies to: RX21x, RX22x, RX610, RX62x, RX63x, RX64M, RX71M

Description: For details on this problem, refer to the following Tool News.

https://www.renesas.com/document/tnn/notes-renesas-flash-programmer

-RENESAS TOOL NEWS, Jul. 16, 2018 Document No. R20TS0330JJ0100

[Notes] Renesas Flash Programmer

Corrected version: V3.05.00

No. 6 Enabling of the intelligent cryptographic unit slave E (ICUSE) of the RH850/C1M-A, RH850/F1K, RH850/F1KM-S1, RH850/P1L-C, and RH850/P1M-E groups

Applies to: RH850/C1M-A, RH850/F1K, RH850/F1KM-S1, RH850/P1L-C, RH850/P1M-E

Description: For details on this problem, refer to the following Tool News.

https://www.renesas.com/document/tnn/notes-pg-fp6pg-fp5-flash-memory-programmer-renesas-flash-programmer

-RENESAS TOOL NEWS, Feb. 01, 2019 Document No. R20TS0399EJ0100

[Notes] PG-FP6/PG-FP5 Flash Memory Programmer, Renesas Flash Programmer

Corrected version: V3.05.03

No. 7 Settings of lock bits or OTP of the RH850/C1M-A2 group

Applies to: RH850/C1M-A2 (R7F701275)

Description: For the settings of lock bits or OTP, when blocks 69 and 70 which straddle code flash memory 1 and code flash memory 2 are successively set, the settings for all blocks above block 70 in code flash memory 2 are not reflected (only the settings of all blocks in code flash memory 1, that is, up to block 69 are reflected).

Corrected version: V3.06.00

No. 8 RPI file

Applies to: RL78 family (excluding RL78/G10, RL78/G1M, and RL78/G1N)

Battery Management

Renesas USB Power Delivery family (C30 group)

Motor Driver/Actuator Driver ICs (motor control ICs)

Description: If you execute the [Program] or [Verify Flash Options] command using an RPI file on which no flash option is set, the command does not end normally and returns the following error:

"Error (E3000108): There is no data in the operation range."

Corrected version: V3.08.01

No. 9 SVR settings for the RH850/U2A16 group

Applies to:

Group	Part Number
RH850/U2A16	R7F702300
RH850/U2A-EVA	R7F702Z19A

Description: If both conditions 1 and 2 listed below are satisfied during the creation of a new project, the error listed below the conditions that matches the type of communications in use occurs and prevents creation of the project.

Condition 1: The DC/DC converter is connected to VDD by the SVR function of the target system.

Condition 2: The SVR function is disabled (SVRENABLE = 0) in the SVR option byte (OPBT16) and this becomes the initial state of the device.

Errors:

With CSI communications in use:

“Error (E300010C): Data received from the device are corrupted.”

With 2-wire UART communications in use:

“Error (E4000003): A timeout error occurred. (BFW: 0358)”

Corrected version: V3.09.01

No. 10 Writing to the code flash memory of an RL78/F24 for secure boot

Applies to:

Group	Part Number
RL78/F24	R7F124FBJ, R7F124FGJ, R7F124FLJ, R7F124FMJ, R7F124FPJ

Description: Writing to the code flash memory of an RL78/F2x for secure boot with specification of the key and MAC passwords may not proceed correctly. In such cases, no error will occur but undefined data will be written.

Corrected version: V3.11.00

No. 11 Operation after connection through the SWD interface

Applies to: RA2A1, RA2E1, RA2E2, RA2L1, RA4M1, RA4W1, RA6M1, RA6M2, RA6M3, RA6T1

Description: After the RFP has been connected to the MCU via the SWD interface, if the connected MCU is not turned on again, it will be incapable of operating in single-chip or SCI boot mode. When “2 wire UART” is selected as [Interface] for the RFP, the SCI boot mode of the MCU will be used.

Corrected version: V3.11.00

No. 12 SWD interface connection

Applies to: RA4E1, RA4M2, RA4M3, RA6E1, RA6M4, RA6M5, RA6T2

Description: The following functions cannot be used with an SWD interface connection. If options for these functions are specified with rfp-cli, the option settings will be ignored or an error will occur. This also applies in cases where the options are specified in an RPI file. Use these functions through UART or USB communications.

- Programming, verifying, or reading flash options
- Writing or verifying user keys
- Checksums (including file checksums)
- Settings or acquisition in relation to TrustZone
- Initializing devices
- Connecting the RFP while the target device is in non-secure state

No. 13 Installing USB drivers for 32-bit versions of the Windows OS

Description: The RFP V3.12.00 to V3.14.00 installers for 32-bit versions of the Windows OS do not include the following USB drivers.

- USB driver for the E1 or E20 emulator
- USB driver for USB-boot MCU Type A
  USB driver for the Renesas Flash Programmer for USB-boot MCU Type A, which supports devices of the RX family except those of the RX65x, RX66x, RX67x, and RX72x groups.

Corrected version: V3.15.00

General Precautions in the Handling of Microprocessing Unit and Microcontroller Unit Products

The following usage notes are applicable to all Microprocessing unit and Microcontroller unit products from Renesas. For detailed usage notes on the products covered by this document, refer to the relevant sections of the document as well as any technical updates that have been issued for the products.

1. Precaution against Electrostatic Discharge (ESD)

   A strong electrical field, when exposed to a CMOS device, can cause destruction of the gate oxide and ultimately degrade the device operation. Steps must be taken to stop the generation of static electricity as much as possible, and quickly dissipate it when it occurs. Environmental control must be adequate. When it is dry, a humidifier should be used. This is recommended to avoid using insulators that can easily build up static electricity. Semiconductor devices must be stored and transported in an anti-static container, static shielding bag or conductive material. All test and measurement tools including work benches and floors must be grounded. The operator must also be grounded using a wrist strap. Semiconductor devices must not be touched with bare hands. Similar precautions must be taken for printed circuit boards with mounted semiconductor devices.
2. Processing at power-on

   The state of the product is undefined at the time when power is supplied. The states of internal circuits in the LSI are indeterminate and the states of register settings and pins are undefined at the time when power is supplied. In a finished product where the reset signal is applied to the external reset pin, the states of pins are not guaranteed from the time when power is supplied until the reset process is completed. In a similar way, the states of pins in a product that is reset by an on-chip power-on reset function are not guaranteed from the time when power is supplied until the power reaches the level at which resetting is specified.
3. Input of signal during power-off state

   Do not input signals or an I/O pull-up power supply while the device is powered off. The current injection that results from input of such a signal or I/O pull-up power supply may cause malfunction and the abnormal current that passes in the device at this time may cause degradation of internal elements. Follow the guideline for input signal during power-off state as described in your product documentation.
4. Handling of unused pins

   Handle unused pins in accordance with the directions given under handling of unused pins in the manual. The input pins of CMOS products are generally in the high-impedance state. In operation with an unused pin in the open-circuit state, extra electromagnetic noise is induced in the vicinity of the LSI, an associated shoot-through current flows internally, and malfunctions occur due to the false recognition of the pin state as an input signal become possible.
5. Clock signals

   After applying a reset, only release the reset line after the operating clock signal becomes stable. When switching the clock signal during program execution, wait until the target clock signal is stabilized. When the clock signal is generated with an external resonator or from an external oscillator during a reset, ensure that the reset line is only released after full stabilization of the clock signal. Additionally, when switching to a clock signal produced with an external resonator or by an external oscillator while program execution is in progress, wait until the target clock signal is stable.
6. Voltage application waveform at input pin

   Waveform distortion due to input noise or a reflected wave may cause malfunction. If the input of the CMOS device stays in the area between V_{IL} (Max.) and V_{IH} (Min.) due to noise, for example, the device may malfunction. Take care to prevent chattering noise from entering the device when the input level is fixed, and also in the transition period when the input level passes through the area between V_{IL} (Max.) and V_{IH} (Min.).
7. Prohibition of access to reserved addresses

   Access to reserved addresses is prohibited. The reserved addresses are provided for possible future expansion of functions. Do not access these addresses as the correct operation of the LSI is not guaranteed.
8. Differences between products

   Before changing from one product to another, for example to a product with a different part number, confirm that the change will not lead to problems. The characteristics of a microprocessing unit or microcontroller unit products in the same group but having a different part number might differ in terms of internal memory capacity, layout pattern, and other factors, which can affect the ranges of electrical characteristics, such as characteristic values, operating margins, immunity to noise, and amount of radiated noise. When changing to a product with a different part number, implement a system-evaluation test for the given product.

Notice

1. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation or any other use of the circuits, software, and information in the design of your product or system. Renesas Electronics disclaims any and all liability for any losses and damages incurred by you or third parties arising from the use of these circuits, software, or information.
2. Renesas Electronics hereby expressly disclaims any warranties against and liability for infringement or any other claims involving patents, copyrights, or other intellectual property rights of third parties, by or arising from the use of Renesas Electronics products or technical information described in this document, including but not limited to, the product data, drawings, charts, programs, algorithms, and application examples.
3. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
4. You shall be responsible for determining what licenses are required from any third parties, and obtaining such licenses for the lawful import, export, manufacture, sales, utilization, distribution or other disposal of any products incorporating Renesas Electronics products, if required.
5. You shall not alter, modify, copy, or reverse engineer any Renesas Electronics product, whether in whole or in part. Renesas Electronics disclaims any and all liability for any losses or damages incurred by you or third parties arising from such alteration, modification, copying or reverse engineering.
6. Renesas Electronics products are classified according to the following two quality grades: “Standard” and “High Quality”. The intended applications for each Renesas Electronics product depends on the product’s quality grade, as indicated below.
   "Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; industrial robots; etc.
   "High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control (traffic lights); large-scale communication equipment; key financial terminal systems; safety control equipment; etc.

   Unless expressly designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not intended or authorized for use in products or systems that may pose a direct threat to human life or bodily injury (artificial life support devices or systems; surgical implantations; etc.), or may cause serious property damage (space system; undersea repeaters; nuclear power control systems; aircraft control systems; key plant systems; military equipment; etc.). Renesas Electronics disclaims any and all liability for any damages or losses incurred by you or any third parties arising from the use of any Renesas Electronics product that is inconsistent with any Renesas Electronics data sheet, user’s manual or other Renesas Electronics document.
7. No semiconductor product is absolutely secure. Notwithstanding any security measures or features that may be implemented in Renesas Electronics hardware or software products, Renesas Electronics shall have absolutely no liability arising out of any vulnerability or security breach, including but not limited to any unauthorized access to or use of a Renesas Electronics product or a system that uses a Renesas Electronics product. RENESAS ELECTRONICS DOES NOT WARRANT OR GUARANTEE THAT RENESAS ELECTRONICS PRODUCTS, OR ANY SYSTEMS CREATED USING RENESAS ELECTRONICS PRODUCTS WILL BE INVULNERABLE OR FREE FROM CORRUPTION, ATTACK, VIRUSES, INTERFERENCE, HACKING, DATA LOSS OR THEFT, OR OTHER SECURITY INTRUSION (“Vulnerability Issues”). RENESAS ELECTRONICS DISCLAIMS ANY AND ALL RESPONSIBILITY OR LIABILITY ARISING FROM OR RELATED TO ANY VULNERABILITY ISSUES. FURTHERMORE, TO THE EXTENT PERMITTED BY APPLICABLE LAW, RENESAS ELECTRONICS DISCLAIMS ANY AND ALL WARRANTIES, EXPRESS OR IMPLIED, WITH RESPECT TO THIS DOCUMENT AND ANY RELATED OR ACCOMPANYING SOFTWARE OR HARDWARE, INCLUDING BUT NOT LIMITED TO THE IMPLIED WARRANTIES OF MERCHANTABILITY, OR FITNESS FOR A PARTICULAR PURPOSE.
8. When using Renesas Electronics products, refer to the latest product information (data sheets, user’s manuals, application notes, “General Notes for Handling and Using Semiconductor Devices” in the reliability handbook, etc.), and ensure that usage conditions are within the ranges specified by Renesas Electronics with respect to maximum ratings, operating power supply voltage range, heat dissipation characteristics, installation, etc. Renesas Electronics disclaims any and all liability for any malfunctions, failure or accident arising out of the use of Renesas Electronics products outside of such specified ranges.
9. Although Renesas Electronics endeavors to improve the quality and reliability of Renesas Electronics products, semiconductor products have specific characteristics, such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Unless designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not subject to radiation resistance design. You are responsible for implementing safety measures to guard against the possibility of bodily injury, injury or damage caused by fire, and/or danger to the public in the event of a failure or malfunction of Renesas Electronics products, such as safety design for hardware and software, including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult and impractical, you are responsible for evaluating the safety of the final products or systems manufactured by you.
10. Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. You are responsible for carefully and sufficiently investigating applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive, and using Renesas Electronics products in compliance with all these applicable laws and regulations. Renesas Electronics disclaims any and all liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
11. Renesas Electronics products and technologies shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations. You shall comply with any applicable export control laws and regulations promulgated and administered by the governments of any countries asserting jurisdiction over the parties or transactions.
12. It is the responsibility of the buyer or distributor of Renesas Electronics products, or any other party who distributes, disposes of, or otherwise sells or transfers the product to a third party, to notify such third party in advance of the contents and conditions set forth in this document.
13. This document shall not be reprinted, reproduced or duplicated in any form, in whole or in part, without prior written consent of Renesas Electronics.
14. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products.

(Note1) “Renesas Electronics” as used in this document means Renesas Electronics Corporation and also includes its directly or indirectly controlled subsidiaries.
(Note2) “Renesas Electronics product(s)” means any product developed or manufactured by or for Renesas Electronics.

(Rev.5.0-1 October 2020)

Corporate Headquarters

TOYOSU FORESIA, 3-2-24 Toyosu,
Koto-ku, Tokyo 135-0061, Japan
www.renesas.com

Trademarks

Renesas and the Renesas logo are trademarks of Renesas Electronics Corporation. All trademarks and registered trademarks are the property of their respective owners.

Contact information

For further information on a product, technology, the most up-to-date version of a document, or your nearest sales office, please visit:
www.renesas.com/contact/.

© 2026 Renesas Electronics Corporation. All rights reserved.