

CUSTOMER NOTIFICATION

SUD-DT-04-0180

March 30, 2004

Yoshiro Harada, Senior System Integrator
Microcomputer Group
2nd Solutions Division
Solutions Operations Unit
NEC Electronics Corporation

CP(K), O

Device File for 78K0 Series

DF780148 (V2.00)

User's Manual

[Supported machines/OS]

PC-9800 Series (Windows™ Based)

IBM PC/AT™ Compatibles (Windows Based)

Be sure to read this document before using the product.

CONTENTS

1. OUTLINE	3
2. CONTENTS OF PACKAGE	3
3. USER ENVIRONMENT.....	3
4. CORRESPONDING VERSIONS OF DEVELOPMENT TOOLS	4
5. INSTALLATION	5
6. USAGE	5
7. RELATED DOCUMENTS	5
8. REVISION HISTORY	6

1. OUTLINE

A device file is a binary file that contains device-dependent information and is prepared for each device model or for each product in the same series.

Device files are commonly used with development tools (such as assembler, compiler, and debugger). Employing device files enables generation and debugging of device-unique codes. In addition, when developing applications, device files enable the SFR names unique to the device being used to can be used for programming.

The DF780148 contains device files necessary for developing applications using the 78K0/KF1 or 78K0/KF1+ microcontrollers in the 78K0 Series.

2. CONTENTS OF PACKAGE

The device files included in this product and the corresponding devices are as follows.

Table 2-1. Contents of Package

Types	Device File Name	Corresponding Device Name	Device Specification Name	Version
Device file	D0143.78K	μ PD780143	0143	V2.00
	D0144.78K	μ PD780144	0144	V2.00
	D0146.78K	μ PD780146	0146	V2.00
	D0148.78K	μ PD780148	0148	V2.00
	DF0148.78K	μ PD78F0148	F0148	V2.00
	DF0148H.78K	μ PD78F0148H μ PD78F0148HD	F0148H	V2.00
Database file	S014X.78K, S0146.78K, S0148.78K			

The Device Specification Name is the character string specified as “-c *device specification name*” (device type specification option), “#pragma pc(*device specification name*)” in C source in the CC78K0 (C compiler), and “\$PROCESSOR(*device specification name*)” in assembler source in the RA78K0 (assembler).

The database file is required when using the system simulator SM78K0. This file is also included in the SM78K0. Installation of the database file can be selected when installing the device file and the SM78K0.

It is recommended to use the latest version of the database file. If this file already exists when the database file is being installed using a device file installer, you are asked if you want to overwrite the file. At this time, confirm the time stamp and make sure that the file being installed is the latest version (note, however, that this file is always overwritten when installing the SM78K0).

The file is not necessary when using the integrated debugger ID78K0-NS or ID78K0-QB. Therefore, you don't have to install this file.

3. USER ENVIRONMENT

Like development tools, device files are available for Windows.

User environment for device files is as follows.

Machine	Operating System
PC-9800 series, IBM PC/AT compatible machines	Windows NT 4.0
	Windows 98
	Windows 2000
	Windows Me
	Windows XP

4. CORRESPONDING VERSIONS OF DEVELOPMENT TOOLS

The corresponding versions of the DF780148 and 78K0 Series development tools made by NEC Electronics are shown below. Use these tools in the following combinations.

Tool Used	Version of Corresponding Tool
C compiler package CC78K0	V3.50 or later
Assembler package RA78K0	V3.60 or later
Integrated debugger ID78K0-NS	V2.52 or later
Integrated debugger ID78K0-QB	V2.81 or later
System simulator SM78K0	V2.52 or later

Caution The μ PD78F0148H and μ PD78F0148HD do not support the system simulator SM78K0.

Windows and Windows NT are either registered trademarks or trademarks of Microsoft Corporation in the United States and/or other countries.

PC/AT is a trademark of International Business Machines Corporation.

5. INSTALLATION

Device files are included on one floppy disk. Use the device file installer (DFINST) included in the NEC Electronics development tools to install the device file.

Note A self-extraction file (an execution file) is downloaded along with device files with ODS (online delivery service). If this file is executed, a disk image is created. Copy this to hard disk or to a floppy disk and then begin the installation process.

The installation procedure is explained below.

- (1) Start Windows.
- (2) Start the device file installer (DFINST). If the NEC Electronics development tool has been installed in the standard directory, the device file installer will be in *installed drive\Nectools32\bin*.
- (3) If installing from the floppy disk, insert the floppy disk in the floppy disk drive.
- (4) Click the **Install** button.
- (5) If installing from the floppy disk, use the **FD Browse** button to display the path where the disk image (icon) is located. Use the **Browse** button to do this if installing from hard disk.
- (6) Necsetup.ini file and _csetup.ini file are displayed in the file list of the dialog box that appears after step (5). Select _csetup.ini to install the English version and Necsetup.ini to install the Japanese version.
- (7) Follow the installation wizard to continue installation.

6. USAGE

Refer to the user's manual of each tool listed in **7. RELATED DOCUMENTS** for details of how to use the device file.

7. RELATED DOCUMENTS

The documents related to the DF780148 are listed below.

User's Manuals
78K0/KF1 Hardware
78K0/KF1+ Hardware
78K/0 Series Instruction
CC78K0 C Compiler Package Operation
CC78K0 C Compiler Package Language
RA78K0 Assembler Package Operation
RA78K0 Assembler Package Assembly Language
RA78K0 Assembler Package Structured Assembly Language
ID78K0-NS Integrated Debugger Operation
ID78K0-QB Integrated Debugger Operation
SM78K0 System Simulator Operation

8. REVISION HISTORY

1. V1.00

- (1) First edition

2. V1.20

- (1) Modification of the following SFR functions

Change of ASICL6 access attribute from REEEEEEE to RERRRREE [bits 7 to 0]

Removal of TXS0 redraw prohibition

Modification of protect information of PCC

Modification of protect information of IF1

Modification of protect information of MK1

Modification of protect information of PR1

- (2) Addition of function to the following SFR

- SBRT6

- (3) Modification of the program area (μ PD780146, μ PD780148, and μ PD78F0148 only)

- (4) Correction of illegal trace data and illegal display of SFR data.

- (5) Addition of the following device

μ PD78F0148H

3. V2.00

- (1) Modification of the following SFR functions

Modification of protect information of LVIS

- (2) Addition of information for IECUBE (QB-78K0KX1H) and MINICUBE (QB-78K0MINI)

- (3) Addition of the following device

μ PD78F0148HD

Remark "Protect information" is information that is used to check the accessible data patterns.