

# RENESAS TECHNICAL UPDATE

TOYOSU FORESIA, 3-2-24, Toyosu, Koto-ku, Tokyo 135-0061, Japan  
Renesas Electronics Corporation

Product Category	MPU/MCU		Document No.	TN-SY*-A0086A/E	Rev.	1.00
Title	Note about the interruption during the transition to low power modes		Information Category	Technical Notification		
Applicable Product	S7G2, S5D9, S5D5, S5D3, S3A7, S3A6, S3A3, S3A1, S124, S128, S1JA Group	Lot No.	Reference Document	Refer table at the end of this document		
		All				

Corrections are made to the figures and tables in the user's manual hardware as shown in 1 and 2 below.

If the software meets the applicable condition listed in 4 below, you may not be able to enter the intended low power mode and transit to unintended states described in 4 below.

If the unintended states described in the following 4 notes cannot be tolerated, use the following 5 workaround.

## Contents

1. Correction of the Figure "Mode transitions".....	2
2. Correction of the table "Operating conditions of each low power mode".....	5
3. Notes about the Sleep-on-exit function.....	6
4. Applicable condition and notes .....	6
5. Workaround .....	7

### 1. Correction of the Figure “Mode transitions”

#### 1) Figure 11.1 of S7G2, S5D9, S5D5, and S5D3 groups

##### Before correction




Figure 11.1 Mode transitions

##### After correction




Figure 11.1 Mode transitions

2) Figure 10.1 of S3A6, S128, and S124 groups

Before correction




Figure 10.1 Mode transitions

After correction




Figure 10.1 Mode transitions

5) Figure 11.1 of S3A7, S3A3, S3A1, and S1JA groups

Before correction




Figure 11.1 Mode transitions

After correction




Figure 11.1 Mode transitions

2. Correction of the table “Operating conditions of each low power mode”

1) Tables 11.2 for S7G2, S5D9, S5D5, S5D3 groups

Before correction

Parameter	Sleep mode	Software Standby mode	Snooze mode	Deep Software Standby mode
Transition condition	WFI instruction while SBYCR.SSBY = 0	WFI instruction while SBYCR.SSBY = 1 and DPSBYCR.DPSBY = 0	Snooze request trigger in Software Standby mode. SNZCR.SNZE = 1	WFI instruction while SBYCR.SSBY = 1 and DPSBYCR.DPSBY = 1
State after cancellation by an interrupt	Program execution state (interrupt processing)	Program execution state (interrupt processing)	Program execution state (interrupt processing)	Reset state

After correction

Parameter	Sleep mode	Software Standby mode	Snooze mode	Deep Software Standby mode
Transition condition	When [Condition 1] or [Condition 2] while SBYCR.SSBY=0 [Condition 1] · WFI instruction · A valid interrupt request(*1) cannot be accepted to CPU. (including a transition from the time WFI instruction is executed to the time the transition to Sleep mode is completed) [Condition 2] · SCR.SLEEPONEXIT=1 · Complete execution of all exception handlers · A valid interrupt request(*1) cannot be accepted to CPU. (including a transition from the time WFI instruction is executed to the time the transition to Sleep mode is completed)	When [Condition 1] or [Condition 2] while SBYCR.SSBY=1 and DPSBYCR.DPSBY=0 [Condition 1] · WFI instruction · A valid interrupt request(*1) cannot be accepted to CPU. (including a transition from the time WFI instruction is executed to the time the transition to sleep Software Standby mode is completed) [Condition 2] · SCR.SLEEPONEXIT=1 · Complete execution of all exception handlers · A valid interrupt request(*1) cannot be accepted to CPU. (including a transition from the time WFI instruction is executed to the time the transition to Software Standby mode is completed)	Snooze request trigger in Software Standby mode. SNZCR.SNZE = 1	When [Condition 1] or [Condition 2] while SBYCR.SSBY=1 and DPSBYCR.DPSBY=1 [Condition 1] · WFI instruction · A valid interrupt request(*1) cannot be accepted to CPU. (including a transition from the time WFI instruction is executed to the time the transition to Software Standby mode is completed) [Condition 2] · SCR.SLEEPONEXIT=1 · Complete execution of all exception handlers · A valid interrupt request(*1) cannot be accepted to CPU. (including a transition from the time WFI instruction is executed to the time the transition to Software Standby mode is completed)
State after cancellation by an interrupt	Program execution state	Program execution state	Program execution state	Reset state

(\*1) Valid interrupt requests are any interrupt/exception that are not masked by the priority level of current exception and the priority level set by BASEPRI. In addition, if the interrupt request is based on IELSRn, the interrupt must be enabled by NVIC\_ISERn.

2) Table 11.2 for S3A7, S3A3, S3A1, S1JA groups, and table 10.2 for S3A6, S128, S124 groups

Before correction

Parameter	Sleep mode	Software Standby mode	Snooze mode
Transition condition	WFI instruction while SBYCR.SSBY = 0	WFI instruction while SBYCR.SSBY = 1	Snooze request trigger in Software Standby mode. SNZCR.SNZE = 1
State after cancellation by an interrupt	Program execution state (interrupt processing)	Program execution state (interrupt processing)	Program execution state (interrupt processing)

After correction

Parameter	Sleep mode	Software Standby mode	Snooze mode
Transition condition	When [Condition 1] or [Condition 2] while SBYCR.SSBY=0 [Condition 1] · WFI instruction · A valid interrupt request(*1) cannot be accepted to CPU. (including a transition from the time WFI instruction is executed to the time the transition to Sleep mode is completed) [Condition 2] · SCR.SLEEPONEXIT=1 · Complete execution of all exception handlers · A valid interrupt request(*1) cannot be accepted to CPU. (including a transition from the time WFI instruction is executed to the time the transition to Sleep mode is completed)	When [Condition 1] or [Condition 2] while SBYCR.SSBY=1 and DPSBYCR.DPSBY=0 [Condition 1] · WFI instruction · A valid interrupt request(*1) cannot be accepted to CPU. (including a transition from the time WFI instruction is executed to the time the transition to Software Standby mode is completed) [Condition 2] · SCR.SLEEPONEXIT=1 · Complete execution of all exception handlers · A valid interrupt request(*1) cannot be accepted to CPU. (including a transition from the time WFI instruction is executed to the time the transition to Software Standby mode is completed)	Snooze request trigger in Software Standby mode. SNZCR.SNZE = 1
State after cancellation by an interrupt	Program execution state	Program execution state	Program execution state

(\*1) Valid interrupt requests are any interrupt/exception that are not masked by the priority level of current exception and the priority level set by BASEPRI. In addition, if the interrupt request is based on IELSRn, the interrupt must be enabled by NVIC\_ISERN.

3. Notes about the Sleep-on-exit function

There are 2 ways to transition to low power modes. One is WFI instruction and the other is Sleep-on-exit. When Sleep-on-exit is used for transition to low power modes, WFI instruction comments written in User’s Manual Hardware is applicable to Sleep-on-exit.

4. Applicable condition and notes

[Applicable condition]

Transition to Software Standby mode is started by a trigger (WFI instruction or SLEEPONEXIT) with SBYCR.SSBY=1 set to use Software Standby, Snooze, or Deep Software Standby mode.

During the specified interval (ICLK 2cycle) of transitioning to Software Standby mode, one of the following interrupt requests that is not an interrupt source to return from Software Standby mode is accepted by CPU.

1) SysTick interrupt (all of the following are applicable)

- Exception number 15 of Interrupt vector table .
- Interrupt requests are not masked by Base Priority Mask Register (BASEPRI)  
(BASEPRI=0 or BASEPRI > SHPR3.PRI\_15)

2) Maskable interrupt requests that are not interrupt source to return from Software Standby mode (all of the following are applicable)

- By WUPEN in exception numbers 16 to 111 in the interrupt vector table

those not permitted to return from Software Standby mode

- Interrupt requests are enabled by Interrupt Set-Enable Register (NVIC\_ISErN).
- Interrupt requests are not masked by Base Priority Mask Register (BASEPRI)  
(BASEPRI=0 or BASEPRI > NVIC\_IPRn.PRI\_N)

3) Non-maskable interrupt request triggered by the following sources

- SRAM parity error
- SRAM ECC failure
- MPU bus master error
- MPU bus slave error
- TrustZone filtering error

[Notes]

If the above conditions are met, the MCU will transit to following unintended states.

These unintended states can be resolved by a reset or returning to Normal mode with an interrupt request of an interrupt source to return from Software Standby mode.

Adapt a workaround if these unintended states are not acceptable.

1) When transitioning to Software Standby mode (SBYCR.SSBY=1, DPSBYCR.DPSBY=0, SNZCR.SNZE=0)

Only CPU clock is stopped, and the remaining clocks continue to operate as they were prior to transitioning Software Standby mode.

- As before the transition to Software Standby mode is started, depending on the setting, timer or other peripherals continue to operate, and an interrupt request related to the peripheral is generated.
- Because the IWDT and WDT clock-stop function is disabled, a reset or an interrupt for the IWDT and WDT is generated depending on the settings before starting the transition to Software Standby mode.
- Interrupt requests are held in IR flag (IELSRn, DELSRn).

2) When transitioning to Snooze mode (SBYCR.SSBY=1, DPSBYCR.DPSBY=0, SNZCR.SNZE=1)

The transition to Snooze mode is not possible, and the states shown in “1) When transitioning to Software Standby mode” is continued.

To return to Normal mode by an interrupt source (SELSR0) from Snooze mode depends on whether the interrupt request (SELSR0) to returning from Snooze mode can be generated while DTC operation is disabled.

If DTC operation is disabled (SNZCR.SNZDTCEN=0) in Snooze mode, Normal mode can be returned because an interrupt source for the interrupt source (SELSR0) to return from Snooze mode can be generated.

If DTC operation is enabled (SNZCR.SNZDTCEN=1) in Snooze mode, the Normal mode cannot be returned because an interrupt request for the interrupt source (SELSR0) to return from Snooze mode cannot be generated.

3) When transitioning to Deep Software Standby mode (SBYCR.SSBY=1, DPSBYCR.DPSBY=1)

The transition to Deep Software Standby mode is not possible, and the state shown in “1) When transitioning to Software Standby mode” is continued.

As for the interrupt source (DPSIERn) settings to returning from Deep Software Standby mode, these interrupt requests can return to Normal mode only when the interrupt source (WUPEN) to return from Software Standby mode is set.

## 5. Workaround

[Workaround]

To avoid the unintended states described above, apply the following before the terms for transition to Software

Standby mode, Snooze mode, or Deep Software Standby mode are met: (For the setting procedure, see "Setting Procedure for Transition to Software Standby, Snooze, or Deep Software Standby Mode")

1) Disable SysTick interrupt requests.

Exception number 15 of Interrupt vector table

2) Disable maskable interrupt requests that are not interrupt sources to return from Software Standby mode.

Exception number 16~111 of Interrupt vector table that WUPEN does not allow to return from Software Standby mode

3) Stop access from the bus master other than the CPU so that the non-maskable interrupt is not triggered by the following sources.

SRAM parity error

SRAM ECC failure

SRAM DED failure

MPU bus master error

MPU bus slave error

**Setting Procedure for Transition to Software Standby, Snooze, or Deep Software Standby Mode**

This section describes procedures for avoiding unintended states.

The handling of interrupt requests after returning from Software Standby or Snooze mode varies depending on the method used to disable the maskable interrupt request. Either one or the other should be applied.

Procedure A) Disable maskable interrupt request acceptance.

Any interrupt request that occurs while interrupt request acceptance is disabled is discarded.

Before transitioning to Software Standby, Snooze, or Deep Software Standby mode

Step1: Stop the bus access from the bus master other than CPU. (\*1)

Step2: Disable the SysTick interrupt request. (\*2)

Step3: Clear IELSRn in ICU to disable acceptance of maskable interrupt requests that are not interrupt sources to return from Software Standby mode.

Step4: Read IELSRn in ICU to confirm that IELSRn in ICU has been cleared.

Step5: Transition to Software Standby mode (WFI instruction, SLEEPONEXIT)

After returning from Software Standby mode or Snooze mode

Step6: Enable the SysTick interrupt request.

Step7: Set IELSRn in ICU to enable acceptance of maskable interrupt requests that are not interrupt sources to return from Software Standby mode.

Step8: Enable bus access from bus masters other than CPU.

Step B) Disable the maskable interrupt request

The interrupt request generated while the interrupt request is disabled is retained in IELSRn.IR flag.

Therefore, after returning from Software Standby or Snooze mode and enabling the maskable interrupt, it is

possible to process the interrupt.

Before transitioning to Software Standby, Snooze, or Deep Software Standby mode

- Step1: Stop the bus access from the bus master other than CPU. (\*1)
- Step2: Disable the SysTick interrupt request. (\*2)
- Step3: Write 1 to the corresponding bit in NVIC\_ICERn in CPU to disable maskable interrupt requests that are not interrupt sources to return from Software Standby mode.
- Step4: Execute Data Synchronization Barrier (DSB) instruction.
- Step5: Transition Software Standby mode (WFI instruction, SLEEPONEXIT)

After returning from Software Standby or Snooze mode

- Step6: Enable the SysTick interrupt request.
- Step7: Write 1 to the corresponding bit in NVIC\_IUSERn in CPU to enable maskable interrupt requests that are not interrupt sources to return from Software Standby mode.
- Step8: Enable bus access from bus masters other than CPU.

\*1: SRAM parity error interrupt, SRAM ECC error interrupt, MPU bus master error interrupt, MPU bus slave error interrupt, or TrustZone filter error interrupt is enabled as a non-maskable interrupt.

\*2: Disabling a SysTick interrupt request may cause SysTick interrupt request to be delayed by one cycle of SysTick timer without generating the latest SysTick interrupt request.

Reference for each product table number, register name, mode, error name.

1. Interrupt vector table is as follows.

Table 14.3 shows the interrupt vector table for S7G2, S5D9, S5D5, S5D3, S3A7, S3A3, and S3A1 groups.

Table 13.3 shows the interrupt vector table for S3A6, and S1JA groups.

Table 12.3 shows the interrupt vector table for S128, and S124 groups.

2. Deep Software Standby mode existence is as follows.

S3A7, S3A6, S3A3, S3A1, S128, S124, and S1JA groups do not have Deep Software Standby mode.

3. The maximum exception number in the interrupt vector table is as follows:

47 for S3S6, S3A3, S124, S128, and S1JA groups.

79 for S3A7, and S3A1 groups.

111 for S7G2, S5D9, S5D5, and S5D3 groups.

4. DELSRn and BASEPRI register existence is as follows:

S128, S124, and S1JA groups do not have DELSRn and BASEPRI register.

5. SRAM ECC error and SRAM DED error existence is as follows:

Only S7G2 has SRAM DED error. S5D9, S5D5, S5D3, S3A7, S3A6, S3A3, S3A1, S128, S124, S1JA groups do not have SRAM DED error.

S7G2 and S124 groups does not have SRAM ECC Error.

**Related Documentation**

Product	Document Name
S7G2 Group	Renesas S7G2 Group User's Manual: Hardware Rev. 1.40
S5D9 Group	Renesas S5D9 Group User's Manual: Hardware Rev. 1.40
S5D5 Group	Renesas S5D5 Group User's Manual: Hardware Rev. 1.40
S5D3 Group	Renesas S5D3 Group User's Manual: Hardware Rev. 1.20
S3A7 Group	Renesas S3A7 Group User's Manual: Hardware Rev. 1.50
S3A6 Group	Renesas S3A6 Group User's Manual: Hardware Rev. 1.30
S3A3 Group	Renesas S3A3 Group User's Manual: Hardware Rev. 1.20
S3A1 Group	Renesas S3A1 Group User's Manual: Hardware Rev. 1.30
S128 Group	Renesas S128 Group User's Manual: Hardware Rev. 1.20
S124 Group	Renesas S124 Group User's Manual: Hardware Rev.1.40
S1JA Group	Renesas S1JA Group User's Manual: Hardware Rev.1.60