

To our customers,

Old Company Name in Catalogs and Other Documents

On April 1st, 2010, NEC Electronics Corporation merged with Renesas Technology Corporation, and Renesas Electronics Corporation took over all the business of both companies. Therefore, although the old company name remains in this document, it is a valid Renesas Electronics document. We appreciate your understanding.

Renesas Electronics website: <http://www.renesas.com>

April 1st, 2010
Renesas Electronics Corporation

Issued by: Renesas Electronics Corporation (<http://www.renesas.com>)

Send any inquiries to <http://www.renesas.com/inquiry>.

RENESAS TECHNICAL UPDATE

Nippon Bldg., 2-6-2, Ohte-machi, Chiyoda-ku, Tokyo 100-0004, Japan
Renesas Technology Corp.

Product Category	MPU&MCU	Document No.	TN-SH7-A723A/E	Rev.	1.00
Title	Note on Use of SH7763 SIOF Slave Mode Receiver	Information Category	Technical Notification		
Applicable Product	SH7763 Group	Lot No.	Reference Document	SH7763 Hardware Manual Rev.2.00 (REJ09B0256-0200)	
		All lots			

The SIOF of the SH7763 has the following note when using slave mode receiver.

[Summary]

When using the receiver of the SIOF in slave mode, if specifying no bit delay (SIMDR.SYNCDL=0), the receive data is sampled at the rising edge of the SIOF_SCK, then the hold time of the receive data may not be ensured.




Figure. SIOF Receive Data Sampling Timing in Slave Mode

[Workaround]

Specify one bit delay (SIMDR.SYNCDL=1) for receiver like for transceiver in slave mode. Then the receive data is sampled at the falling edge of the SIOF_SCK.

- End of Text -