

Customer Notification

78K4TM Series

CCWIN-CDR-78K4

Operating Precautions

**Embedded Workbench 78K4
Integrated Development Environment**

DISCLAIMER

The related documents in this customer notification may include preliminary versions. However, preliminary versions may not have been marked as such.

The information in this customer notification is current as of its date of publication. The information is subject to change without notice. For actual design-in, refer to the latest publications of NEC's data sheets or data books, etc., for the most up-to-date specifications of NEC PRODUCT(S). Not all PRODUCT(S) and/or types are available in every country. Please check with an NEC sales representative for availability and additional information.

No part of this customer notification may be copied or reproduced in any form or by any means without prior written consent of NEC. NEC assumes no responsibility for any errors that may appear in this customer notification. NEC does not assume any liability for infringement of patents, copyrights or other intellectual property rights of third parties by or arising from the use of NEC PRODUCT(S) listed in this customer notification or any other liability arising from the use of such PRODUCT(S).

No license, express, implied or otherwise, is granted under any patents, copyrights or other intellectual property rights of NEC or others. Descriptions of circuits, software and other related information in this customer notification are provided for illustrative purposes of PRODUCT(S) operation and/or application examples only. The incorporation of these circuits, software and information in the design of customer's equipment shall be done under the full responsibility of customer. NEC assumes no responsibility for any losses incurred by customers or third parties arising from the use of these circuits, software and information.

While wherever feasible, NEC endeavors to enhance the quality, reliability and safe operation of PRODUCT(S) the customer agree and acknowledge that the possibility of defects and/or erroneous thereof cannot be eliminated entirely. To minimize risks of damage to property or injury (including death) to persons arising from defects and/or errors in PRODUCT(S) the customer must incorporate sufficient safety measures in their design, such as redundancy, fire-containment and anti-failure features.

The customer agrees to indemnify NEC against and hold NEC harmless from any and all consequences of any and all claims, suits, actions or demands asserted against NEC made by a third party for damages caused by one or more of the items listed in the enclosed table of content of this customer notification for PRODUCT(S) supplied after the date of publication.

Applicable Law:

The law of the Federal Republic of Germany applies to all information provided by NEC to the Customer under this Operating Precaution document without the possibility of recourse to the Conflicts Law or the law of 5th July 1989 relating to the UN Convention on Contracts for the International Sale of Goods (the Vienna CISG agreement).

Düsseldorf is the court of jurisdiction for all legal disputes arising directly or indirectly from this information. NEC is also entitled to make a claim against the Customer at his general court of jurisdiction.

If the supplied goods/information are subject to German, European and/or North American export controls, the Customer shall comply with the relevant export control regulations in the event that the goods are exported and/or re-exported. If deliveries are exported without payment of duty at the request of the Customer, the Customer accepts liability for any subsequent customs administration claims with respect to NEC.

Notes: (1) "**NEC**" as used in this statement means NEC Corporation and also includes its direct or indirect owned or controlled subsidiaries.

(2) "**PRODUCT(S)**" means 'NEC semiconductor products' (*NEC semiconductor products* means any semiconductor product developed or manufactured by or for NEC) and/or 'TOOLS' (*TOOLS* means 'hardware and/or software development tools' for NEC semiconductor products' developed, manufactured and supplied by 'NEC' and/or 'hardware and/or software development tools' supplied by NEC but developed and/or manufactured by independent 3rd Party vendors worldwide as their own product or on contract from NEC)

Table of Contents

(A)	Table of Operating Precautions (IDE)	4
(B)	Table of Operating Precautions (Assembler).....	4
(C)	Table of Operating Precautions (C-Compiler).....	5
(D)	Table of Operating Precautions (Linker)	5
(E)	Description of Operating Precautions (IDE).....	6
(F)	Table of Operating Precautions (Assembler).....	7
(G)	Description of Operating Precautions (C Compiler)	8
(H)	Description of Operating Precautions (Linker).....	10
(I)	Valid Specification	11
(J)	Revision History.....	11

(A) Table of Operating Precautions (IDE)

No.	Outline	EW78400				
		Version	2.31e			
A1	Temporary File isn't deleted		X			
A2	Assembler Error Message isn't displayed		X			

- ✓ : Not applicable
- X : applicable
- : Not checked

(B) Table of Operating Precautions (Assembler)

No.	Outline	A78400				
		Version	1.33A			
B1	Backslash as last character in a comment		X			
B2	Project using only absolute segments		X			

- X : Applicable
- ✓ : Not applicable
- : Not checked

(C) Table of Operating Precautions (C-Compiler)

No.	Outline	Version	ICC78400			
			1.33A	1.33B		
C1	Stack area location exceeding 64K boundary		X	X		
C2	Missing external variable entry, if a global variable is only used in Inline-Assembler		X	X		
C3	For some C assignments no source code is generated		X	✓		

- X : Applicable
- ✓ : Not applicable
- : Not checked

(D) Table of Operating Precautions (Linker)

No.	Outline	Version	XLINK			
			4.53I			
D1	Unused Segments in multi-segment-definition line causes unnecessary error message		X			

- X : Applicable
- ✓ : Not applicable
- : Not checked

(E) Description of Operating Precautions (IDE)

No. A1	Temporary File isn't deleted
<p><u>Details</u> The Embedded Workbench generated under special conditions a temporary file (0001.tmp) in the project directory, which isn't deleted after exiting the Workbench. The problem occurs only if the used operating system is Windows 98 and at the first generation of a new project.</p> <p><u>Workaround(s)</u></p> <p>a) Update the operating system to Windows 98 SE b) Delete the temporary file manually.</p>	

No. A2	Assembler Error Message isn't displayed
<p><u>Details</u> If the total character size of filename, path and error message exceeds a certain limit and an assembler list file is generated an assembler error message may be not displayed. As the size of the message depends on the line number, kind of error etc. the maximum length of path and file name is not easily predictable. Keeping the path and file name within 80 characters should work.</p> <p><u>IAR Bug-ID</u> EW13168</p> <p><u>Workaround(s)</u></p> <p>Don't enable the generation of an assembler list file.</p>	

(F) Table of Operating Precautions (Assembler)

No. B1	Backslash as last character in a comment
<p><u>Details</u></p> <p>If the last character in a comment is a backslash the pre-processor looks upon the next source line as a comment too. So the assembler code in the following line is not used.</p> <p><u>Workaround</u></p> <p>Don't use the backslash as the last character in a comment</p>	

No. B2	Project using only absolute segments
<p><u>Details</u></p> <p>If a project uses only absolute segments, the linker generates a correct output file in XCOFF78K-format. But the NEC debugger (or simulator) before version 2.30 can't read the file (Error message; c0003(A): Failed in reading file).</p> <p><u>Workaround</u></p> <p>Use relative segments and do the segment definition in the XCL file.</p>	

(G) Description of Operating Precautions (C Compiler)

No. C1	Stack area location exceeding 64K boundary
<p><u>Details</u></p> <p>Please take care of locating the stack area. If the stack area exceeds a 64K boundary, the consequence is a wrong stack access, because the access is done only with a 16-Bit pointer.</p> <p>Example:</p> <pre>void test (int index) { unsigned char array [10], *p; p=&array[index]; }</pre> <p>The list-file shows the 16 Bit access, which produces wrong results if a 64K boundary is exceeded:</p> <pre>P=&array[index] MOVG RG7,SP ADDW RP7,RP0 ; 16 Bit access!!</pre> <p><u>Workaround</u></p> <p>Do not place the stack area, which exceeds a 64K boundary.</p>	

No. C2	Missing external variable entry, if a global variable is only used in Inline-Assembler
<p><u>Details</u></p> <p>The global variable "var2" does not have an external entry! The result will be an unresolved external error during linking.</p> <p>Example:</p> <pre>extern char var1; extern char var2; void func1(void) { var1 = 2; _ASM("MOV R0,#var1"); _ASM("MOV R0,#var2"); }</pre> <p><u>Workaround</u></p> <p>Use the global variable in a C statement, too</p>	

No. C3	For some C assignments no source code is generated
	<p><u>Details</u></p> <p>The error occurs when assigning one saddr variable with another. If only one of them is a saddr variable, the error will not occur.</p> <p>.</p> <p>Example:</p> <pre>saddr char i1,i2; char i3,i4; void test1(void) { i2 = 0; i1 = i2; } void test2(void) { i2 = 0; i2 = i1; // -> no code generated }</pre> <p><u>Workaround</u></p> <p>Install the update patch V1.33b.</p>

(H) Description of Operating Precautions (Linker)

No. D1	Unused Segments in multi-segment-definition line causes unnecessary error message
	<p><u>Details</u></p> <p>If an unused segment is defined in a multi-segment-definition-line and there are no more bytes available the linker generates an unnecessary error message telling that the unused segment can not be located:</p> <p style="text-align: center;"><i>Error[e16]: Segment NO_INIT (size: 0 align: 0) is too long for segment definition. At least 0 more bytes needed.</i></p> <p>Example:</p> <pre>-Z (DATA) CSTACK+20,NO_INIT, IDATA2, UDATA2, ECSTR, TEMP=FE00-FE1F</pre> <p>The segment CSTACK uses the complete address area, but even if the following segments are not used the linker generates the error message and stops the link process.</p> <p><u>Workaround</u></p> <p>Change the segment order: Unused segments should be defined before the last used segment:</p> <pre>-Z (DATA) NO_INIT, IDATA2, UDATA2, ECSTR, TEMP, CSTACK+20=FE00-FE1F</pre>

(I) Valid Specification

Item	Date published	Document No.	Document Title
1	December 1997	ICC78400C-2	78400 C Compiler Programming Guide
2	December 1997	A78400C-2	78400 Assembler, Linker and Librarian Programming Guide
3	December 1997	EW78400-1	78400 Windows Workbench Interface Guide
4	October 2001	XLINK-453E	XLINK Linker™ and XLIB Librarian™ Reference Guide
5	September 2000	IARCLIB-1	C Library Functions Reference Guide
6	December 2001	ILG-2	Installation and Licensing Guide for Embedded Workbench™

(J) Revision History

Item	Date published	Document No.	Comment
1	11-04-2002	DTOP0004V10	First release.
2	18-04-2002	DTOP0004V11	Correction: Item A2 deleted
3	08-05-2002	DTOP0004V12	Item D1 added
4	05-08-2002	DTOP0004V13	Item C3 added
5	05-12-2002	DTOP0004V14	Item A2 added