

RENESAS TECHNICAL UPDATE

TOYOSU FORESIA, 3-2-24, Toyosu, Koto-ku, Tokyo 135-0061, Japan
Renesas Electronics Corporation

Product Category	MPU/MCU		Document No.	TN-R8C-A061A/E	Rev.	1.00
Title	Caution on using wait mode		Information Category	Technical Notification		
Applicable Product	R8C/36T-A, R8C/38T-A	Lot No.	Reference Document	Latest user's Manual: Hardware of applicable products		
		-				

This document described caution on using wait mode for above mentioned applicable products.

1. Description

The Compare match timer mode of Timer RE2 interrupt is not used to exit wait mode.

“Table. Interrupts Used to Exit Wait Mode and Usage Conditions” in User's Manual: Hardware is shown below.

● Interrupts Used to Exit Wait Mode and Usage Conditions

Correct:

Table. Interrupts Used to Exit Wait Mode and Usage Conditions

Interrupt	When CM02 = 0	When CM02 = 1
Serial interface interrupt	Usable with an internal clock or external clock supplied.	Usable with an external clock supplied.
Synchronous serial communication unit/I ² C bus interface	Usable in all modes.	- (Do not use.)
Key input interrupt	Usable	Usable
A/D interrupt	- (Do not use.)	- (Do not use.)
Timer RJ interrupt	Usable in all modes.	Usable without a filter in event counter mode. Usable when fOCO, fC1, or fC32 is selected as the count source.
Timer RB2 interrupt	Usable in all modes.	- (Do not use.)
Timer RC interrupt	Usable in all modes.	Usable when fHOCO or fHOCO-F is selected as the count source.
Timer RE2 interrupt	Usable when fC1 is selected as the count source.	Usable when fC1 is selected as the count source.
INT interrupt	Usable	Usable (usable when INT0 to INT4 are used without a filter.)
Voltage monitor 1 interrupt	Usable	Usable
Voltage monitor 2 interrupt	Usable	Usable
Oscillation stop detection interrupt	Usable	- (Do not use.)

Incorrect:

Table. Interrupts Used to Exit Wait Mode and Usage Conditions

Interrupt	When CM02 = 0	When CM02 = 1
Serial interface interrupt	Usable with an internal clock or external clock supplied.	Usable with an external clock supplied.
Synchronous serial communication unit/I ² C bus interface	Usable in all modes.	- (Do not use.)
Key input interrupt	Usable	Usable
A/D interrupt	- (Do not use.)	- (Do not use.)
Timer RJ interrupt	Usable in all modes.	Usable without a filter in event counter mode. Usable when fOCO, fC1, or fC32 is selected as the count source.
Timer RB2 interrupt	Usable in all modes.	- (Do not use.)
Timer RC interrupt	Usable in all modes.	Usable when fHOCO or fHOCO-F is selected as the count source.
Timer RE2 interrupt	Usable in all modes.	Usable when fC1 is selected as the count source.
INT interrupt	Usable	Usable (usable when INT0 to INT4 are used without a filter.)
Voltage monitor 1 interrupt	Usable	Usable
Voltage monitor 2 interrupt	Usable	Usable
Oscillation stop detection interrupt	Usable	- (Do not use.)