

RTKA271084DE0000BU

7-channel Automotive PMIC Evaluation Board and GUI

Description

The RTKA271084DE0000BU evaluates the performance of the RAA271084 Automotive PMIC with a high voltage primary buck/boost controller, a low voltage synchronous buck controller, and five low-dropout liner regulators (LDO), two of which can be used as trackers. The evaluation board is intended for providing MCU power in automotive applications.

In addition to four output voltages, the evaluation board also contains an SPI interface.

The RAA271084 is offered in a 7mm×7mm 48-lead Step Cut QFN (SCQFN) package or 9mm×9mm 48-lead thin QFP (LQFP) with an exposed pad. The RAA271084 is qualified to AEC-Q100, Grade1.

Features

- $V_{IN}$  operating range from 2.7 to 42V including cold crank
- Start range 4.5 to 42V
- Two DC/DC controllers with integrated drivers
  - Buck-Boost DCDC1 5.7V at 2.2A
  - Buck DCDC2 resistor programmable (5V at 1.2A, 3.3V at 1.8A, 1.09V at 4.2A)
- Five linear regulators
  - LDO0 (VCC), 5V (always on)
  - LDO1-4, programmable 3.3V/5V (LDO1-2 at 350mA, LDO3-4 at 200mA)
  - LDO3-4, configurable as trackers with short-to-battery/short-to-ground and reverse current protection
- Configurable Frequency 440kHz/2.2MHz
- Over-temperature, overcurrent, overvoltage, and negative overcurrent protection





Figure 1. Block Diagram

## Contents

<b>1. Functional Description</b>	<b>3</b>
1.1 Manual Output Control using WAKE1 and WAKE2	3
1.2 Testing the Outputs	4
<b>2. GUI Operation</b>	<b>4</b>
2.1 Changing Programming Options	8
2.2 Feature Set Tab	9
2.3 Misc Tab	11
2.4 Table View Tab	12
2.5 Reg Map link	13
2.6 Log Tab	13
<b>3. Board Design</b>	<b>14</b>
3.1 Schematic Diagrams	15
3.2 Bill of Materials	17
3.3 Board Layout	20
<b>4. Ordering Information</b>	<b>21</b>
<b>5. Revision History</b>	<b>21</b>

# 1. Functional Description

The evaluation board with connections, headers, and test points is shown in [Figure 2](#).



**Figure 2. RAA271084 Evaluation Board: Connections, Headers, and Test Points**

- To start the board, apply the input voltage ( $2.7V < V_{IN} < 42$ ) to the VIN supply terminals J1(+) and J2(-) (see [Figure 2](#)).
- For EN control, use WAKE1 and WAKE2 at J25 and J26 (see [Figure 2](#)).
- For VDDIO voltage supply, use the VDDIO voltage jumpers to select the supply source (see [Figure 2](#)).
- For tracker reference input, use the VTR3/4 Input jumpers to select the supply source (see [Figure 2](#)).

## 1.1 Manual Output Control using WAKE1 and WAKE2

For manual control of EN, ensure that the J25 and J26 jumpers are not installed. WAKE1/WAKE2 enables the IC (see [Figure 2](#)).

The following are the states of WAKE1/WAKE2:

- WAKE1/WAKE2 < 0.4V
  - The IC is off and in its lowest power state.
- WAKE1 or WAKE2 > 1.4V
  - The IC is enabled.

The status of the regulators depends on the PMIC STATE and settings. Refer to the *RAA271084 Datasheet*, section *Operation of the PMIC*.

## 1.2 Testing the Outputs

When the WAKE1 or WAKE2 inputs are configured, the outputs can be loaded to perform tests such as load regulation, startup and shutdown, and load transients.

### 1.2.1 Input and Output Connections and Test Points

The input and output connections are shown in [Figure 1](#) and [Table 1](#).

**Table 1. Connections and Test Points**

Connection	(+) Test Point	GND Test Point	Default Value (V)
VBAT (input)	TP1	TP61	12 (2.7V to 42V, 4.5V to start)
Vout1	TP6	TP10	5.7
Vout2	TP5	TP10	5.0 or 3.3 or 1.09
LDO0 (VCC)	J5 (VCC)	TP62	5.0
LDO1	TP21	TP45	5.0 or 3.3
LDO2	TP22	TP45	5.0 or 3.3
LDO3/TRACKER3	TP23	TP45	5.0 or 3.3
LDO4/TRACKER4	TP24	TP45	5.0 or 3.3

The following are more test points (see [Figure 1](#)):

- RSTB and INTB test points, located on the upper-side of J4.
- WAKE1 and WAKE2 test points, located on the middle of J4.

## 2. GUI Operation

The RAA271084 GUI can be used to configure feature sets by creating an OTP file, which generates customer samples. For initial samples of the RAA271084, the Renesas Application Engineering Team provides a short-form questionnaire for customer inputs on major options. (The customer can also review the datasheet and specify additional configuration options as required.)


The RAA271084 OTP Initial Configuration:

- Input voltage range
- DCDC1 (Buck/Boost) and DCDC2 (Buck) switching frequency
- DCDC1 (Buck/Boost) output current
- DCDC2 (Buck) output voltage and current
- Output voltage and current for LDO1-4
- Output rails startup and shutdown timing and sequencing requirements
- LDO3/LDO4 usage (LDO or tracker)

The following are requirements before starting the GUI software:


- A USB interface cable must be connected between the host computer and the EVB.
- The VDDIO supply to the EVB must be 3.3V minimum.

[Figure 3](#) shows the list of the GUI files to be downloaded. Double-click the **RAA271084.exe** file to start the GUI software.



**Figure 3. GUI Files**

When powered up, the GUI appears as shown in [Figure 4](#).



\*Note: When the GUI opens, it displays the last tab used.

Figure 4. State/Status Tab with Labels

The GUI functions are grouped into rows or columns. [Figure 4](#) displays the **State/Status** tab, which is detailed in this section along with other tabs such as the **Feature Set**, **Fault Management**, **Misc**, and **Table View**.

In the center of [Figure 4](#), the **Status Information** label points to data that is grouped into rows.

*Note:* These rows are shown for the **State/Status** tab, and other tabs show different options. The rows are explained as follows:

- **Tab Select** – This row contains buttons for the different tabs in the GUI. Each tab controls a set of functions. When the tab is selected, the GUI displays the dropdowns and options associated with that tab.
- **Connection Status** – This row shows the Connection Status with the GUI tool and EVB. Green signals a correct connection. Yellow signals no connection. Red signals an incorrect connection.
- **Manual register Read / Write** – This row contains the Bus interface, ChipSelect Pin, Reg. Address, Send Data, Read Data, and Advanced Mode column. A bus interface can be used to select RAA271084\_ISL\_SPI or RAA271084\_SAM3U\_SPI. Select to suit for the EVB and GUI connection. (If the EVB and PC are connected directly, select RAA271084\_ISL\_SPI. For a register read/write, input the register address and use Send Data to write or Read Data to read. To control the Frequency, Dev Num, CLK Mode, Write Flag, Dummy Bytes, and CRC Flag, check the **Advanced Mode** box.
- **Register Polling Enable / Disable** – This row contains the register polling function. Set the button to enable or disable the register polling function.
- **File IO** – This row contains file related functions. The GUI can export or import the OTP setting from a CSV or TXT file.

Complete the following steps to create an OTP file:

1. Make the selections for these tabs: **Feature Set**, **Fault Management**, and **Misc**.
2. Review the selections using the **Table View** tab.
3. Start the OTP programming widget located in the **Tools** dropdown menu (Figure 5).

From the main menu, select **Tools > RAA271084 OTP Programmer** to start the OTP Programmer Widget.




Figure 5. OTP Programming Sequence

4. In the OTP programmer screen, click **Load From Registers** (Figure 6).

Click **Load from Registers** to update changes made to the default settings.




Figure 6. Import OTP Changes from Default Configuration

5. Save the configuration using the .ini format (Figure 7).




Figure 7. Save the OTP Configuration as .ini File

- **Load defaults** – Use this button to update the register values to default.
- **Info** window – This row describes information (see Figure 4).
- **Status** menu tabs – These tabs are the **Console** tab, used for scripts, and the **Log** tab, used to view activity logs.
- **Status** information – This indicates the register settings. The value can be changed by clicking.
- **Chip ID** – Reads the device ID and silicon revision.

When powered up, the GUI should initially appear as in Figure 4. When the IC is enabled and connected with a USB, the GUI automatically detects the EVB.

## 2.1 Changing Programming Options

Complete the following steps to make changes in the options on this tab such as Output Voltage and  $V_{OUT}$  OV Threshold:

1. Input the VBAT and WAKE1 or WAKE2 to place the IC in enabled. All the options on the **State/Status** tab can be changed only when the device is Enabled.
2. Select the options by clicking the relevant menu button.

*Note:* There are options not shown on this **State/Status** tab. These other options are located on the **Feature Set, Misc, and Table View** tabs. Changes on that tab can be made by moving to that tab and selecting the required options.

3. Changes are applied immediately when the button is clicked.

*Note:* While options can be selected, the accuracy of the selected options can be slightly outside the datasheet specifications. Datasheet accuracy limits are assured only for the factory-programmed settings. As an example, if LDO1 is selected to the default value of 5.0V, the output value is finely adjusted at the factory for LDO1 set to 5.0V. If  $V_{OUT1}$  is later changed to a different voltage setting, the new  $V_{OUT1}$  voltage might be slightly less accurate than the default setting. However, the change in accuracy is minor and should not significantly affect system or board level testing. After the required options are chosen, the device can be ordered and factory-adjusted with those specific options to provide the best accuracy available.

*Note:* If any option is set to a value other than the factory-programmed value and OPT\_SPI\_CRC is enabled, this creates a CRC Recheck fault. This CRC Recheck error is ignored if the OPT\_SPI\_CRC is disabled.

## 2.2 Feature Set Tab

View the **Feature Set** information by clicking the **Feature Set** button in the tab row.

The screenshot displays the 'Feature Set' tab in the RTKA271084 software. The interface is organized into several functional sections, each with a title and a list of control parameters:

- Rail Timing:** Includes parameters for OPT\_SEQ\_CTRL, OPT\_SLOT\_TIME, OPT\_SLOT\_DCDC, OPT\_SLOT\_LDO, OPT\_HP, OPT\_DS, OPT\_TOFF\_TIME, and OPT\_SLOT\_LDO.
- Regulator Control:** Includes parameters for DCDC\_CTRL, LDO\_CTRL, and various start/stop controls for DCDC and LDO regulators.
- Monitor:** Includes parameters for OPT\_ERRB\_CTRL1, OPT\_VMONB\_CTRL1, AMUX\_SEL, ERRB\_CTRL2, VMONB\_CTRL2, and VMONB\_PER\_USED.
- System Self Test:** Includes parameters for WAKE\_PIN\_CTRL, PWR\_PIN\_CTRL, INTB\_PIN\_CTRL, VMONOUT\_PIN\_CTRL, ERRB\_PIN\_CTRL, RSTB\_PIN\_CTRL, SSIPB\_PIN\_CTRL, WDENB\_PIN\_CTRL, and PWR\_MODE\_CTRL.
- EOT:** Includes parameters for EOT\_CTRL1, EOT\_CTRL2, EOT\_CTRL3, EOT\_P00, EOT\_P01, EOT\_WU0, EOT\_WU1, EOT\_WU2, EOT\_TMR0, EOT\_TMR1, EOT\_TMR2, EOT\_CD, EOT\_PDD0B, EOT\_WUDB0, and EOT\_WUDB1.
- WDT:** Includes parameters for WDT\_CTRL1, WDT\_CTRL2, OPT\_WDT\_CONFIG1, WDT\_CONFIG2, WDT\_CONFIG3, WDT\_SST, WDT\_KICK\_REG, WDT\_LFSR, WDT\_ACC\_THRESH, WDT\_TOACC\_CLEAR, WDT\_TICK, WDT\_LLCONT, and WDT\_TOTICK.

Arrows on the right side of the image point to these sections: Rail Timing, Regulator Control, Monitor, System Self Test, EOT, and WDT.

Figure 8. Feature Set Tab

The **Feature Set** tab information is arranged in columns as follows: Rail Timing, Regulator Control, Monitor, System Self Test, EOT, and WDT. The first column on top, Rail Timing lists OPT settings related to sequence timings, such as SLOT selection and delay time of each regulators and signals. For details on the sequence timing, refer to the *RAA271084 Datasheet*, section *Timing Summary*.

The remaining columns are described as follows:

- The Regulator Control column lists the start and stop settings of each regulator.
- The Monitor column lists monitoring function settings: such as the ERRB, VMONB, and AMUX monitoring mode settings.
- The System Self Test column lists the IC pin settings, such as WAKE1, WAKE2, PSTBYB, PWRCTRLB, INTB, VMONOUT, ERRB, RSTB, SSPB, and WDENB.

### 2.2.1 Fault Management

To view any detected faults, use the **Fault Management** tab. Any detected faults highlight with a green background such as in **Figure 9** where the detected faults are the Overvoltage on LDO1 and LDO2.




Figure 9. Fault Management (LDO1 and LDO2 Severe OV Detected)

**Note:** If a fault is detected, the fault status bit for that fault is set to logic 1 and stays at logic 1 until the bit is cleared.

To clear a fault, go to the **Fault Management** dropdown and click the relevant button. This button changes to **no fault detected**, and the button background now appears white.

## 2.3 Misc Tab

The **Misc** tab is selected by clicking the **Misc** button in the tab row (see Figure 10). This tab controls miscellaneous options that are not contained in the **Feature Set** tab and **Fault Management** tab. The control method is the same as the other tabs.




Figure 10. Misc Tab

## 2.4 Table View Tab

The **Table View** tab is selected by clicking the **Table View** button in the tab row (see Figure 11). This tab contains all the registers that are shown in other tabs.

The screenshot shows the 'Table View' tab selected in the software interface. On the left, a list of registers is shown with their addresses and current values. On the right, a detailed bit-level configuration table is displayed, showing the settings for each bit (Bit 7 to Bit 0) for various registers. Annotations indicate that the 'Register Value' is shown in the 'Data' column and the 'Register Address: Register Name' is shown in the first column of the register list.

Register Address	Register Name	Data
0x0000	DEV_ID_LO_BYTE	0x84
0x0001	DEV_ID_HI_BYTE	0x10
0x0002	DEV_REV_LO_BYTE	0x01
0x0003	DEV_REV_HI_BYTE	0x0C
0x0004	SEQ_STATUS	0x00
0x0005	PG_STATUS	0x00
0x0008	DCDC_STATE	0x00
0x0009	LDO_STATE	0x00
0x000A	CONTROLLER_STATE	0x00
0x000B	FUSA_STATE	0x00
0x0010	OPT_SEQ_CTRL	0x00
0x0011	OPT_SLOT_TIME	0x00
0x0012	OPT_SLOT_DCDC	0x00
0x0013	OPT_SLOT_LDO	0x00
0x0014	OPT_HP	0x00
0x0015	OPT_DS	0x00
0x0016	OPT_TOFF_TIME	0x00
0x0020	DCDC_CTRL	0x00
0x0021	LDO_CTRL	0x00
0x0030	OPT_ERRB_CTRL1	0x00
0x0031	OPT_VMONB_CTRL1	0x00
0x0032	AMUX_SEL	0x00
0x0034	ERRB_CTRL2	0x00
0x0035	VMONB_CTRL2	0x00
0x0040	WAKE_PIN_CTRL	0x00
0x0041	PWR_PIN_CTRL	0x00
0x0042	INTB_PIN_CTRL	0x00
0x0043	VMONOUT_PIN_CTRL	0x00
0x0044	ERRB_PIN_CTRL	0x00

Figure 11. Table View

On the left side, the register address, name, and its value are described; on the right side, the settings for each bit are described. By clicking a bit, the value can be changed.

## 2.5 Reg Map link

The Reg Map (register map) link is selected by clicking **Help** from the main menu (see Figure 12). The GUI can show the register map in an HTML file by clicking the link.




Figure 12. Reg Map link

## 2.6 Log Tab

The **Log** tab is selected by clicking the **Log** tab in the tab row (see Figure 13). This tab maintains a log of read/write operations completed between the GUI and the RAA271084, which is useful for analyzing and understanding the register read/write operations used to configure the device options. For example, clicking **Read All** at any time initiates a read of many registers, and this series of register reads is displayed in the Log window. This Log feature can be useful when tracking the relationship between selecting device options and the registers associated with those options.

The **Log** tab also contains a **Clear Log** button that clears away all previous read/write information. This is helpful in tracking individual register operations.




Figure 13. Log Tab

### 3. Board Design




Figure 14. RTKA271084DE0000BU Evaluation Board (Top)




Figure 15. RTKA271084DE0000BU Evaluation Board (Bottom)

### 3.1 Schematic Diagrams







Figure 16. RTKA271084DE0000BU Schematic (1 of 2)

GND Test Points




Option 1 is a voltage divider fed from 5v.  
Option 2 is a voltage fed directly from the DAC8 of the MCU

Voltages to be measured from the PMIC (place on back of board)




IO Voltage Selection



Option 1 is LDOV01, IO voltage is based on LDOV01  
Option 2 is LDOV02, IO voltage is based on LDOV02  
Option 3 is LDOV03, IO voltage is based on LDOV03  
Option 4 is LDOV04, IO voltage is based on LDOV04  
Option 5 is external, IO voltage is based on an External Voltage


Tracker Voltage Selection



Option 1 is LDOV01, Tracker Target voltage is based on LDOV01  
Option 2 is LDOV02, Tracker Target voltage is based on LDOV02  
Option 3 is LDOV03, Tracker Target voltage is based on LDOV03  
Option 4 is LDOV04, Tracker Target voltage is based on LDOV04  
Option 5 is external, Tracker Target voltage is based on an External Voltage


Output Headers

LDO, Monitor, and other analog measurements



40-pin ribbon cable connector for GPIO/ADC measurements

DDC1 and DDC2 Measurements



Static ID Measurements, connected directly to PMIC pins



ISLUSB Adaptor




Figure 17. RTKA271084DE0000BU Schematic (2 of 2)

### 3.2 Bill of Materials

Qty	Reference Designator	Description	Manufacturer Part Number
1	PCB	PWB-PCB, RTKA271084DE0000BU, REVD, ROHS	RTKA271084DE0000BURVDP
1	C46	CAP, SMD, 0603, 10pF, 25V, 10%, C0G/NP0, ROHS	CGA3E2C0G2A100D080AA-T
2	C1, C72	CAP-AEC-Q200, SMD, 0603, 2.2μF, 10V, 10%, X7S, ROHS	CGA3E3X7S1A225K080AE-T
2	C12, C13	CAP-AEC-Q200, SMD, 2220, 4.7μF, 100V, 10%, X7R, ROHS	CGA9N2X7R2A475K230KA-T
1	C54	CAP-AEC-Q200, SMD, 0603, 4.7nF, 100V, 10%, X7R, ROHS	GCM188R72A472KA37D-T
1	C21	CAP-AEC-Q200, SMD, 0603, 10nF, 100V, 10%, X7R, ROHS	GCM188R72A103KA37D-T
1	C45	CAP-AEC-Q200, SMD, 0603, 10000pF, 50V, X7R, ROHS	CGA3E2X7R1H103K080AA
2	C22, C42	CAP-AEC-Q200, SMD, 0603, 0.047μF, 50V, 10%, X8R, ROHS	GCM188R91H473KA37D-T
2	C56, C58	CAP-AEC-Q200, SMD, 0805, 1.0μF, 16V, 10%, X7R, ROHS	GCM219R71C105KA37D-T
6	C57, C59, C60, C62, C64, C66	CAP-AEC-Q200, SMD, 0805, 4.7μF, 25V, 10%, X7S, ROHS	GCM21BC71E475KE36L-T
9	C31, C32, C33, C34, C35, C36, C47, C48, C49	CAP-AEC-Q200, SMD, 1210, 22μF, 16V, 10%, X7R, ROHS	GCM32ER71C226KE19L-T
2	C40, C41	CAP-AEC-Q200, SMD, 0805, 4.7μF, 16V, 10%, X7R, ROHS	GCM21BR71C475KA73K-T
3	C2, C7, C74	CAP-AEC-Q200, SMD, 0603, 0.1μF, 25V, 10%, X7R, ROHS	CGA3E2X7R1E104K080AA-T
0	a) C3, C4, C5, C6, C23, C24, C25, C29, C30,	CAP, SMD, 0603, DNP-PLACE HOLDER, ROHS	H1045-DNP
0	b) C43, C44, C55, C61, C71	CAP, SMD, 0603, DNP-PLACE HOLDER, ROHS	H1045-DNP
0	C63, C68	CAP, SMD, 0805, DNP-PLACE HOLDER, ROHS	H1046-DNP
0	C37, C38, C50, C51, C52, C65, C67	CAP, SMD, 1210, DNP-PLACE HOLDER, ROHS	H1082-DNP
2	C39, C69	CAP-AEC-Q200, SMD, 0603, 1.0μF, 25V, 10%, X7R, ROHS	TMK107AB7105KAHT-T
2	C17, C73	CAP, SMD, 0603, 1.0μF, 50V, 10%, X7R, ROHS	UMK107AB7105KA-T
1	C53	CAP-AEC-Q200, SMD, 0805, 1.0μF, 50V, 10%, X7R, ROHS	UMK212B7105KGHT-T
1	C15	CAP-AEC-Q200, SMD, 10.3mm, 120μF, 50V, 20%, 28mΩ, ROHS	EEH-ZC1H121P-T
3	C8, C9, C75	CAP, SMD, 0603, 4.7μF, 25V, 10%, X5R, ROHS	GRT188R61E475KE13D-T
1	L1	COIL-PWR CHOKE, SMD, 7.3*6.8*3, 0.68μH	VCMT063T-R68MN5TM-T
1	L2	COIL-PWR INDUCTOR, SMD, 4.5*4.3*2.1, 0.68μH	VCHA042A-R68MS62M-T
4	J1, J9, J11, J14	CONN-GEN, BIND.POST, INSUL-RED, THMBNUT-GND	111-0702-001
3	J2, J10, J12	CONN-GEN, BIND.POST, INSUL-BLK, THMBNUT-GND	111-0703-001
4	TP10, TP45, TP61, TP62	CONN-TURRET, TERMINAL POST, TH, ROHS	1514-2
1	J7	CONN-RECEPTACLE, TH, 9.6x8.4, 5-CONTACT, MINI B, ROHS	UX60-MB-5S8

Qty	Reference Designator	Description	Manufacturer Part Number
28	TP1, TP2, TP3, TP5, TP6, TP7, TP8, TP9, TP11, TP12, TP13, TP15, TP17, TP18, TP19, TP20, TP21, TP22, TP23, TP24, TP25, TP26, TP27, TP28, TP30, TP31, TP32, TP63	CONN-MINI TEST POINT, VERTICAL, WHITE, ROHS	5002
3	J4, J5, J6	CONN-HEADER, 2x20, BRKAWY-2x36, 2.54mm, ROHS	67996-272HLF-2X20
28	J3, J35, J36, J38, J40, J42, J44, J65, J66, J72, J73, J74, J75, J76, J77, J78, J79, J80, J81, J82, J83, J84, J85, J90, J94, J95, J96, J97	CONN-HEADER, 1x2, BRKAWY 1x36, 2.54mm, ROHS	68000-236HLF-1X2
10	J8, J25, J26, J27, J30, J33, J34, J91, J92, J93	CONN-HEADER, 1x3, BREAKAWY 1x36, 2.54mm, ROHS	68000-236HLF-1X3
4	R5, R32, R67, R115 *SOLDER SHORT PADS	CONN-JUMPER, SOLDER SHORT	ASSEMBLY-SOLDER JUMPER
1	D3	DIODE-SCHOTTKY, AEC-Q101, SMD, 3P, TO-277, 45V, 15A, ROHS	PMEG045V150EPDZ-T
2	D1, D2	DIODE-SCHOTTKY, SMD, SOT-323, 70V, 200mA, ROHS	SMMBD770T1G-T
1	U1	IC-PMIC, AUTOMOTIVE GRADE, 48P, SCQFN, ROHS	RAA271084A4HNP#AA0
1	U2	IC-USB uCONTROLLER, 32P, LQFP, HID-REV2.4 PROGRAM, ROHS	C8051F320-GQ/HID-REV2.4
1	U3	IC-SINGLE USB PORT TVS, SMD, 6P, SOT-23-6, ROHS	SN65220DBVR-T
3	Q1, Q2, Q3	TRANSISTOR-MOS, N-CHANNEL, SMD, LFPK-33-8, 40V, 40A, 9.5mΩ, ROHS	BUK9M9R5-40HX-T
2	Q5, Q6	TRANSISTOR-MOS, N-CHANL, SMD, 8P, PowerDI3333-8, 30V, 14A, ROHS	DMG7430LFGQ-7-T
1	Q8	TRANSISTOR, N-CHANNEL, 3LD, SOT-23, 60V, 115mA, ROHS	2N7002-7-F-T
1	R64	RES, SMD, 0603, 2K, 1/10W, 1%, TF, ROHS	AC0603JR-072KL
1	R71	RES-AEC-Q200, SMD, 0603, 2.2Ω, 1/10W, 1%, TF, ROHS	ERJ-3RQF2R2V-T
1	R20	RES-AEC-Q200, SMD, 0603, 10Ω, 1/10W, 1%, ROHS	ERJ-3EKF10R0V-T
9	R3, R4, R12, R13, R100, R101, R102, R103, R116	RES-AEC-Q200, SMD, 0402, 0Ω, 1/10W, ROHS	ERJ-2GE0R00X-T
1	R129	RES-AEC-Q200, SMD, 0603, 10K, 1/10W, 1%, TF, ROHS	ERJ-3EKF1002V-T
19	R21, R23, R26, R29, R31, R36, R46, R50, R51, R52, R53, R60, R62, R66, R73, R79, R98, R99, R130	RES-AEC-Q200, SMD, 0603, 0Ω, 1/10W, TF, ROHS	ERJ-3GEY0R00V-T
1	R1	RES-AEC-Q200, SMD, 0603, 2.2Ω, 1/10W, 1%, TF, ROHS	ERJ-3RQF2R2V-T
2	R134, R135	RES, SMD 0603, 300Ω	RK73B1JTDD301J-T
1	LED1	LED, SMD, 1206, RED, 2.0V, 6mcd, 635nm, 20mA, ROHS	SML-LX1206IW-TR-T
1	LED2	LED, SMD, 1206, GREEN, 2.2V, 10mcd, 565nm, 20mA, ROHS	SML-LX1206GW-TR-T

Qty	Reference Designator	Description	Manufacturer Part Number
0	R2, R8, R9, R10, R11, R15, R16, R47, R54, R80, R81, R82, R83, R84, R85, R86, R87, R88, R89, R90, R91, R92, R93, R94, R104, R105, R106, R107, R108, R109, R110, R111, R112, R113, R118, R119, R120, R121, R122, R127, R128	RES, SMD, 0402, DNP, DNP, DNP, TF, ROHS	-
0	R6, R7, R25, R27, R34, R58, R59, R68, R70	RES, SMD, 0603, DNP-PLACE HOLDER, ROHS	-
0	R38, R39, R56, R57	RES, SMD, 0805, DNP-PLACE HOLDER, ROHS	-
1	R55	RES, SMD, 0402, 100K, 1/16W, 1%, TF, ROHS	RC0402FR-07100KL-T
4	R95, R96, R97, R117	RES-AEC-Q200, SMD, 0402, 10K, 1/16W, 1%, TF, ROHS	RMCF0402FT10K0-T
3	R75, R77, R126	RES-AEC-Q200, SMD, 0603, 100K, 1/10W, 1%, TF, ROHS	RMCF0603FT100K-T
2	R74, R76 (ALT:RN73R1JTTD3612F50)	RES, SMD, 0603, 36.5K, 1/10W, 0.5%, 50ppm, THINFILM, ROHS	RT0603DRE0736K5L-T
1	R69	RES-AEC-Q200, SMD, 1206, 0.005Ω, 1W, 1%, METAL, CURR.SENSE, ROHS	TLR2BWDTD5L00F75-T
1	R28	RES-CURR.SENSE, SMD, 1206, 0.01Ω, 1W, 1%, 75ppm, ROHS	WSP1206R0100FEA-T
5	Four corners top PCB + near J11	SCREW, 4-40X1/4in, PHILLIPS, PANHEAD, STAINLESS, ROHS	4-40X1/4-SCREW-SS
5	Four corners bottom PCB + near J11	STANDOFF, 4-40X3/4in, F/F, HEX, ALUMINUM, 0.25 OD, ROHS	4-40X3/4-STANDOFF-METAL
1	Place assy in bag	BAG, STATIC, 6X8, ZIPLOC, ROHS	6X8-STATIC-BAG
0	C10, C11, C16	Do not populate or purchase	DNP
0	Q9	Do not populate or purchase	DNP
2	D1, D2	DIODE-SCHOTTKY, SMD, SOT-323, 70V, 200mA, ROHS	SMMBD770T1G-T
1	Affix To Back Of PCB	LABEL-DATE CODE = LINE 1:YRWK-REV#, LINE 2:BOM NAME	LABEL-DATE CODE
10	J26.1&2, J27.1&2, J30.1&2, J25.1&2, J33.1&2, J34.1&2, J92.1&2, J77, J85, J93.1&2	CONN SHUNT 2POS 100 CLOSED TOP	880584-4
1	Bag & ship w/board	CABLE-USB 2.0, A MALE TO MINI B MALE, 1.8M, WHITE, ROHS	887328800

### 3.3 Board Layout




Figure 18. Top Layer




Figure 19. Layer 2




Figure 20. Layer 3




Figure 21. Layer 4




Figure 22. Layer 5




Figure 23. Bottom Layer



## Notice

1. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation or any other use of the circuits, software, and information in the design of your product or system. Renesas Electronics disclaims any and all liability for any losses and damages incurred by you or third parties arising from the use of these circuits, software, or information.
2. Renesas Electronics hereby expressly disclaims any warranties against and liability for infringement or any other claims involving patents, copyrights, or other intellectual property rights of third parties, by or arising from the use of Renesas Electronics products or technical information described in this document, including but not limited to, the product data, drawings, charts, programs, algorithms, and application examples.
3. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
4. You shall be responsible for determining what licenses are required from any third parties, and obtaining such licenses for the lawful import, export, manufacture, sales, utilization, distribution or other disposal of any products incorporating Renesas Electronics products, if required.
5. You shall not alter, modify, copy, or reverse engineer any Renesas Electronics product, whether in whole or in part. Renesas Electronics disclaims any and all liability for any losses or damages incurred by you or third parties arising from such alteration, modification, copying or reverse engineering.
6. Renesas Electronics products are classified according to the following two quality grades: "Standard" and "High Quality". The intended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below.
  - "Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; industrial robots; etc.
  - "High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control (traffic lights); large-scale communication equipment; key financial terminal systems; safety control equipment; etc.Unless expressly designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not intended or authorized for use in products or systems that may pose a direct threat to human life or bodily injury (artificial life support devices or systems; surgical implantations; etc.), or may cause serious property damage (space system; undersea repeaters; nuclear power control systems; aircraft control systems; key plant systems; military equipment; etc.). Renesas Electronics disclaims any and all liability for any damages or losses incurred by you or any third parties arising from the use of any Renesas Electronics product that is inconsistent with any Renesas Electronics data sheet, user's manual or other Renesas Electronics document.
7. No semiconductor product is absolutely secure. Notwithstanding any security measures or features that may be implemented in Renesas Electronics hardware or software products, Renesas Electronics shall have absolutely no liability arising out of any vulnerability or security breach, including but not limited to any unauthorized access to or use of a Renesas Electronics product or a system that uses a Renesas Electronics product. RENESAS ELECTRONICS DOES NOT WARRANT OR GUARANTEE THAT RENESAS ELECTRONICS PRODUCTS, OR ANY SYSTEMS CREATED USING RENESAS ELECTRONICS PRODUCTS WILL BE INVULNERABLE OR FREE FROM CORRUPTION, ATTACK, VIRUSES, INTERFERENCE, HACKING, DATA LOSS OR THEFT, OR OTHER SECURITY INTRUSION ("Vulnerability Issues"). RENESAS ELECTRONICS DISCLAIMS ANY AND ALL RESPONSIBILITY OR LIABILITY ARISING FROM OR RELATED TO ANY VULNERABILITY ISSUES. FURTHERMORE, TO THE EXTENT PERMITTED BY APPLICABLE LAW, RENESAS ELECTRONICS DISCLAIMS ANY AND ALL WARRANTIES, EXPRESS OR IMPLIED, WITH RESPECT TO THIS DOCUMENT AND ANY RELATED OR ACCOMPANYING SOFTWARE OR HARDWARE, INCLUDING BUT NOT LIMITED TO THE IMPLIED WARRANTIES OF MERCHANTABILITY, OR FITNESS FOR A PARTICULAR PURPOSE.
8. When using Renesas Electronics products, refer to the latest product information (data sheets, user's manuals, application notes, "General Notes for Handling and Using Semiconductor Devices" in the reliability handbook, etc.), and ensure that usage conditions are within the ranges specified by Renesas Electronics with respect to maximum ratings, operating power supply voltage range, heat dissipation characteristics, installation, etc. Renesas Electronics disclaims any and all liability for any malfunctions, failure or accident arising out of the use of Renesas Electronics products outside of such specified ranges.
9. Although Renesas Electronics endeavors to improve the quality and reliability of Renesas Electronics products, semiconductor products have specific characteristics, such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Unless designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not subject to radiation resistance design. You are responsible for implementing safety measures to guard against the possibility of bodily injury, injury or damage caused by fire, and/or danger to the public in the event of a failure or malfunction of Renesas Electronics products, such as safety design for hardware and software, including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult and impractical, you are responsible for evaluating the safety of the final products or systems manufactured by you.
10. Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. You are responsible for carefully and sufficiently investigating applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive, and using Renesas Electronics products in compliance with all these applicable laws and regulations. Renesas Electronics disclaims any and all liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
11. Renesas Electronics products and technologies shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations. You shall comply with any applicable export control laws and regulations promulgated and administered by the governments of any countries asserting jurisdiction over the parties or transactions.
12. It is the responsibility of the buyer or distributor of Renesas Electronics products, or any other party who distributes, disposes of, or otherwise sells or transfers the product to a third party, to notify such third party in advance of the contents and conditions set forth in this document.
13. This document shall not be reprinted, reproduced or duplicated in any form, in whole or in part, without prior written consent of Renesas Electronics.
14. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products.

(Note1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its directly or indirectly controlled subsidiaries.

(Note2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.

(Disclaimer Rev.5.0-1 October 2020)

## Corporate Headquarters

TOYOSU FORESIA, 3-2-24 Toyosu,  
Koto-ku, Tokyo 135-0061, Japan  
[www.renesas.com](http://www.renesas.com)

## Trademarks

Renesas and the Renesas logo are trademarks of Renesas Electronics Corporation. All trademarks and registered trademarks are the property of their respective owners.

## Contact Information

For further information on a product, technology, the most up-to-date version of a document, or your nearest sales office, please visit:  
[www.renesas.com/contact/](http://www.renesas.com/contact/)