

RENESAS SEMICONDUCTOR RELIABILITY REPORT

GROUP : RX71M
DEVICE : R5F571MXXX
APPLICATION : Consumer / Industry

Quality Assurance Div.
Renesas Electronics Corporation

Notice

1. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation or any other use of the circuits, software, and information in the design of your product or system. Renesas Electronics disclaims any and all liability for any losses and damages incurred by you or third parties arising from the use of these circuits, software, or information.
 2. Renesas Electronics hereby expressly disclaims any warranties against and liability for infringement or any other claims involving patents, copyrights, or other intellectual property rights of third parties, by or arising from the use of Renesas Electronics products or technical information described in this document, including but not limited to, the product data, drawings, charts, programs, algorithms, and application examples.
 3. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
 4. You shall be responsible for determining what licenses are required from any third parties, and obtaining such licenses for the lawful import, export, manufacture, sales, utilization, distribution or other disposal of any products incorporating Renesas Electronics products, if required.
 5. You shall not alter, modify, copy, or reverse engineer any Renesas Electronics product, whether in whole or in part. Renesas Electronics disclaims any and all liability for any losses or damages incurred by you or third parties arising from such alteration, modification, copying or reverse engineering.
 6. Renesas Electronics products are classified according to the following two quality grades: "Standard" and "High Quality". The intended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below.
"Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; industrial robots; etc.
"High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control (traffic lights); large-scale communication equipment; key financial terminal systems; safety control equipment; etc.
Unless expressly designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not intended or authorized for use in products or systems that may pose a direct threat to human life or bodily injury (artificial life support devices or systems; surgical implantations; etc.), or may cause serious property damage (space system; undersea repeaters; nuclear power control systems; aircraft control systems; key plant systems; military equipment; etc.). Renesas Electronics disclaims any and all liability for any damages or losses incurred by you or any third parties arising from the use of any Renesas Electronics product that is inconsistent with any Renesas Electronics data sheet, user's manual or other Renesas Electronics document.
 7. No semiconductor product is absolutely secure. Notwithstanding any security measures or features that may be implemented in Renesas Electronics hardware or software products, Renesas Electronics shall have absolutely no liability arising out of any vulnerability or security breach, including but not limited to any unauthorized access to or use of a Renesas Electronics product or a system that uses a Renesas Electronics product. RENESAS ELECTRONICS DOES NOT WARRANT OR GUARANTEE THAT RENESAS ELECTRONICS PRODUCTS, OR ANY SYSTEMS CREATED USING RENESAS ELECTRONICS PRODUCTS WILL BE INVULNERABLE OR FREE FROM CORRUPTION, ATTACK, VIRUSES, INTERFERENCE, HACKING, DATA LOSS OR THEFT, OR OTHER SECURITY INTRUSION ("Vulnerability Issues"). RENESAS ELECTRONICS DISCLAIMS ANY AND ALL RESPONSIBILITY OR LIABILITY ARISING FROM OR RELATED TO ANY VULNERABILITY ISSUES. FURTHERMORE, TO THE EXTENT PERMITTED BY APPLICABLE LAW, RENESAS ELECTRONICS DISCLAIMS ANY AND ALL WARRANTIES, EXPRESS OR IMPLIED, WITH RESPECT TO THIS DOCUMENT AND ANY RELATED OR ACCOMPANYING SOFTWARE OR HARDWARE, INCLUDING BUT NOT LIMITED TO THE IMPLIED WARRANTIES OF MERCHANTABILITY, OR FITNESS FOR A PARTICULAR PURPOSE.
 8. When using Renesas Electronics products, refer to the latest product information (data sheets, user's manuals, application notes, "General Notes for Handling and Using Semiconductor Devices" in the reliability handbook, etc.), and ensure that usage conditions are within the ranges specified by Renesas Electronics with respect to maximum ratings, operating power supply voltage range, heat dissipation characteristics, installation, etc. Renesas Electronics disclaims any and all liability for any malfunctions, failure or accident arising out of the use of Renesas Electronics products outside of such specified ranges.
 9. Although Renesas Electronics endeavors to improve the quality and reliability of Renesas Electronics products, semiconductor products have specific characteristics, such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Unless designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not subject to radiation resistance design. You are responsible for implementing safety measures to guard against the possibility of bodily injury, injury or damage caused by fire, and/or danger to the public in the event of a failure or malfunction of Renesas Electronics products, such as safety design for hardware and software, including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult and impractical, you are responsible for evaluating the safety of the final products or systems manufactured by you.
 10. Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. You are responsible for carefully and sufficiently investigating applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive, and using Renesas Electronics products in compliance with all these applicable laws and regulations. Renesas Electronics disclaims any and all liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
 11. Renesas Electronics products and technologies shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations. You shall comply with any applicable export control laws and regulations promulgated and administered by the governments of any countries asserting jurisdiction over the parties or transactions.
 12. It is the responsibility of the buyer or distributor of Renesas Electronics products, or any other party who distributes, disposes of, or otherwise sells or transfers the product to a third party, to notify such third party in advance of the contents and conditions set forth in this document.
 13. This document shall not be reproduced or duplicated in any form or disclosed to any third party, in whole or in part, without prior written consent of Renesas Electronics.
 14. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products.
- (Note 1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its directly or indirectly controlled subsidiaries.
- (Note 2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.

(Rev.5.0-2 October 2020)

Table. Reliability test results (QFP)

Test Items	Reference	Test Conditions	Results Failure/Size	Comment
High Temperature Operating Life (HTOL)	JESD22-A108	Ta=125 °C, Vccmax, 1000 hrs	0/22	
High Temperature Storage Life (HTSL)	JESD22-A103	Ta=150 °C, 1000 hrs	0/22	
Temperature Humidity bias (THB) (*1)	JESD22-A101	Ta=85 °C, RH=85 %, Vccmax, 1000 hrs	0/22	
Temperature Cycling (TC) (*1)	JESD22-A104	Ta=-65 °C to 150 °C , 300 cycles	0/22	
Latch-Up (LU)	JESD78	Pulse Current Injection, I=+/-150 mA	0/3	
Electrostatic discharge (ESD-HBM)	JS-001	1.5 kΩ, 100 pF, +/-2000 V, 1 time	0/3	Class: 2
Electrostatic discharge (ESD-CDM)	JEITA ED-4701/302	+/-1000V,1time	0/3	Class: Equivalent to C2b
Solderability (SD)	J-STD-002	245 °C, 5 s, Solder coverage ≥95 %	0/5	
Resistance to Soldering Heat (PC)	JESD22-A113, J-STD-020	MSL3(Moisture Sensitivity Level 3)	0/22	

*1) With preconditioning per JESD22-A113, MSL 3

•It is tested to confirm that all the samples are satisfied with an individual product specification.

Note :

Basically qualification tests were performed using a representative product with the same wafer process and the same package structure .

Table. Reliability test results (BGA)

Test Items	Reference	Test Conditions	Results Failure/Size	Comment
High Temperature Operating Life (HTOL)	JESD22-A108	Ta=125 °C, Vccmax, 1000 hrs	0/22	
High Temperature Storage Life (HTSL)	JESD22-A103	Ta=150 °C, 1000 hrs	0/22	
Temperature Humidity bias (THB) (*1)	JESD22-A101	Ta=85 °C, RH=85 %, Vccmax, 1000 hrs	0/22	
Temperature Cycling (TC) (*1)	JESD22-A104	Ta=-55 °C to 125 °C , 500 cycles	0/22	
Latch-Up (LU)	JESD78	Pulse Current Injection, I=+/-150 mA	0/3	
Electrostatic discharge (ESD-HBM)	JS-001	1.5 kΩ, 100 pF, +/-2000 V, 1 time	0/3	Class: 2
Electrostatic discharge (ESD-CDM)	JEITA ED-4701/302	+/-1000V,1time	0/3	Class: Equivalent to C2b
Resistance to Soldering Heat (PC)	JESD22-A113, J-STD-020	MSL3(Moisture Sensitivity Level 3)	0/22	

*1) With preconditioning per JESD22-A113, MSL 3

•It is tested to confirm that all the samples are satisfied with an individual product specification.

Note :

Basically qualification tests were performed using a representative product with the same wafer process and the same package structure .

Table. Reliability test results (LGA)

Test Items	Reference	Test Conditions	Results Failure/Size	Comment
High Temperature Operating Life (HTOL)	JESD22-A108	Ta=125 °C, Vccmax, 1000 hrs	0/22	
High Temperature Storage Life (HTSL)	JESD22-A103	Ta=150 °C, 1000 hrs	0/22	
Temperature Humidity bias (THB) (*1)	JESD22-A101	Ta=85 °C, RH=85 %, Vccmax, 1000 hrs	0/22	
Temperature Cycling (TC) (*1)	JESD22-A104	Ta=-55 °C to 125 °C , 500 cycles	0/22	
Latch-Up (LU)	JESD78	Pulse Current Injection, I=+/-150 mA	0/3	
Electrostatic discharge (ESD-HBM)	JS-001	1.5 kΩ, 100 pF, +/-2000 V, 1 time	0/3	Class: 2
Electrostatic discharge (ESD-CDM)	JEITA ED-4701/302	+/-1000V,1time	0/3	Class: Equivalent to C2b
Resistance to Soldering Heat (PC)	JESD22-A113, J-STD-020	MSL3(Moisture Sensitivity Level 3)	0/22	

*1) With preconditioning per JESD22-A113, MSL 3

•It is tested to confirm that all the samples are satisfied with an individual product specification.

Note :

Basically qualification tests were performed using a representative product with the same wafer process and the same package structure .

The failure rate of the device in an actual use condition can be estimated by the below procedure.

•Equation for the failure rate estimation (λ)

$$\lambda = \lambda_b \times \pi T \text{ (FIT)}$$

①Unique failure rate (λ_b)

$$\lambda_b = 0.04 \text{ FIT}$$

Unique failure rate at $T_a=55^\circ\text{C}$ using 60 % confidence level.

②Temperature term (πT)

$$\pi T = \exp\{11600 \times E_a \times (1/(273+55) - 1/(273+T_a))\}$$

E_a : Activation energy (eV)

T_a : Ambient temperature ($^\circ\text{C}$)

πT simplified chart as $E_a=0.7 \text{ eV}$

T_a ($^\circ\text{C}$)	40	50	55	60	65	70	75	80	85	90	100	110
πT	0.31	0.68	1	1.45	2.08	2.95	4.15	5.77	7.96	10.88	19.82	34.99

•MTTF (Mean Time To Failure)

$$MTTF = 1/\lambda$$

Reference about Renesas package code

Package type		Package code *1
Lead type plastic package	QFP	PxQP
Non-lead type plastic package	QFN	PxQN
Grid array type plastic package	BGA	PxBG
	LGA	PxLG

*1. First four digit

Table. Product list

No	Group	Product part number	Package code	No	Group	Product part number	Package code
1	RX71M	R5F571MFCDBG	PLBG0176G*	51	RX71M	R5F571MFDDFC	PLQP0176K*
2	RX71M	R5F571MFDDBG	PLBG0176G*	52	RX71M	R5F571MFDGFC	PLQP0176K*
3	RX71M	R5F571MFGDBG	PLBG0176G*	53	RX71M	R5F571MFGDFC	PLQP0176K*
4	RX71M	R5F571MFHDBG	PLBG0176G*	54	RX71M	R5F571MFGGFC	PLQP0176K*
5	RX71M	R5F571MGCDBG	PLBG0176G*	55	RX71M	R5F571MFHDFC	PLQP0176K*
6	RX71M	R5F571MGDDBG	PLBG0176G*	56	RX71M	R5F571MFHGFC	PLQP0176K*
7	RX71M	R5F571MGGDBG	PLBG0176G*	57	RX71M	R5F571MGCDFC	PLQP0176K*
8	RX71M	R5F571MGHDBG	PLBG0176G*	58	RX71M	R5F571MGCDFC	PLQP0176K*
9	RX71M	R5F571MJCDBG	PLBG0176G*	59	RX71M	R5F571MGDDFC	PLQP0176K*
10	RX71M	R5F571MJDDBG	PLBG0176G*	60	RX71M	R5F571MGDGFC	PLQP0176K*
11	RX71M	R5F571MJGDBG	PLBG0176G*	61	RX71M	R5F571MGGDFC	PLQP0176K*
12	RX71M	R5F571MJHDBG	PLBG0176G*	62	RX71M	R5F571MGGGFC	PLQP0176K*
13	RX71M	R5F571MLCDBG	PLBG0176G*	63	RX71M	R5F571MGHDFC	PLQP0176K*
14	RX71M	R5F571MLDDBG	PLBG0176G*	64	RX71M	R5F571MGHGFC	PLQP0176K*
15	RX71M	R5F571MLGDBG	PLBG0176G*	65	RX71M	R5F571MJCDFC	PLQP0176K*
16	RX71M	R5F571MLHDBG	PLBG0176G*	66	RX71M	R5F571MJCGFC	PLQP0176K*
17	RX71M	R5F571MFCDFB	PLQP0144K*	67	RX71M	R5F571MJDDFC	PLQP0176K*
18	RX71M	R5F571MFCGFB	PLQP0144K*	68	RX71M	R5F571MJDGFC	PLQP0176K*
19	RX71M	R5F571MFDDFB	PLQP0144K*	69	RX71M	R5F571MJGDFC	PLQP0176K*
20	RX71M	R5F571MFDGFB	PLQP0144K*	70	RX71M	R5F571MJGGFC	PLQP0176K*
21	RX71M	R5F571MFGDFB	PLQP0144K*	71	RX71M	R5F571MJHDFC	PLQP0176K*
22	RX71M	R5F571MFGGFB	PLQP0144K*	72	RX71M	R5F571MJHGFC	PLQP0176K*
23	RX71M	R5F571MFHDFB	PLQP0144K*	73	RX71M	R5F571MLCDFC	PLQP0176K*
24	RX71M	R5F571MFHGFB	PLQP0144K*	74	RX71M	R5F571MLCGFC	PLQP0176K*
25	RX71M	R5F571MGCDFB	PLQP0144K*	75	RX71M	R5F571MLDDFC	PLQP0176K*
26	RX71M	R5F571MGCDFB	PLQP0144K*	76	RX71M	R5F571MLDGFC	PLQP0176K*
27	RX71M	R5F571MGDDFB	PLQP0144K*	77	RX71M	R5F571MLGDFC	PLQP0176K*
28	RX71M	R5F571MGDGFB	PLQP0144K*	78	RX71M	R5F571MLGGFC	PLQP0176K*
29	RX71M	R5F571MGGDFB	PLQP0144K*	79	RX71M	R5F571MLHDFC	PLQP0176K*
30	RX71M	R5F571MGGGFB	PLQP0144K*	80	RX71M	R5F571MLHGFC	PLQP0176K*
31	RX71M	R5F571MGHDFB	PLQP0144K*	81	RX71M	R5F571MFCDFP	PLQP0100K*
32	RX71M	R5F571MGHGFB	PLQP0144K*	82	RX71M	R5F571MFCGFP	PLQP0100K*
33	RX71M	R5F571MJCDFB	PLQP0144K*	83	RX71M	R5F571MFDDFP	PLQP0100K*
34	RX71M	R5F571MJCGFB	PLQP0144K*	84	RX71M	R5F571MFDGFP	PLQP0100K*
35	RX71M	R5F571MJDDFB	PLQP0144K*	85	RX71M	R5F571MFGDFP	PLQP0100K*
36	RX71M	R5F571MJDGFB	PLQP0144K*	86	RX71M	R5F571MFGGFP	PLQP0100K*
37	RX71M	R5F571MJGDFB	PLQP0144K*	87	RX71M	R5F571MFHDFP	PLQP0100K*
38	RX71M	R5F571MJGGFB	PLQP0144K*	88	RX71M	R5F571MFHGFP	PLQP0100K*
39	RX71M	R5F571MJHDFB	PLQP0144K*	89	RX71M	R5F571MGCDFP	PLQP0100K*
40	RX71M	R5F571MJHGFB	PLQP0144K*	90	RX71M	R5F571MGCDFP	PLQP0100K*
41	RX71M	R5F571MLCDFB	PLQP0144K*	91	RX71M	R5F571MGDDFP	PLQP0100K*
42	RX71M	R5F571MLCGFB	PLQP0144K*	92	RX71M	R5F571MGDGFP	PLQP0100K*
43	RX71M	R5F571MLDDFB	PLQP0144K*	93	RX71M	R5F571MGGDFP	PLQP0100K*
44	RX71M	R5F571MLDGFB	PLQP0144K*	94	RX71M	R5F571MGGGFP	PLQP0100K*
45	RX71M	R5F571MLGDFB	PLQP0144K*	95	RX71M	R5F571MGHDFP	PLQP0100K*
46	RX71M	R5F571MLGGFB	PLQP0144K*	96	RX71M	R5F571MGHGFP	PLQP0100K*
47	RX71M	R5F571MLHDFB	PLQP0144K*	97	RX71M	R5F571MJCDFP	PLQP0100K*
48	RX71M	R5F571MLHGFB	PLQP0144K*	98	RX71M	R5F571MJCGFP	PLQP0100K*
49	RX71M	R5F571MFCDFC	PLQP0176K*	99	RX71M	R5F571MJDDFP	PLQP0100K*
50	RX71M	R5F571MFCGFC	PLQP0176K*	100	RX71M	R5F571MJDGFP	PLQP0100K*

Table. Product list

MCR-22-0321

No	Group	Product part number	Package code	No	Group	Product part number	Package code
101	RX71M	R5F571MJGDFP	PLQP0100K*	161			
102	RX71M	R5F571MJGGFP	PLQP0100K*	162			
103	RX71M	R5F571MJHDFP	PLQP0100K*	163			
104	RX71M	R5F571MJHGFP	PLQP0100K*	164			
105	RX71M	R5F571MLCDFP	PLQP0100K*	165			
106	RX71M	R5F571MLCGFP	PLQP0100K*	166			
107	RX71M	R5F571MLDDFP	PLQP0100K*	167			
108	RX71M	R5F571MLDGFP	PLQP0100K*	168			
109	RX71M	R5F571MLGDFP	PLQP0100K*	169			
110	RX71M	R5F571MLGGFP	PLQP0100K*	170			
111	RX71M	R5F571MLHDFP	PLQP0100K*	171			
112	RX71M	R5F571MLHGFP	PLQP0100K*	172			
113	RX71M	R5F571MFCDL	PTLG0177K*	173			
114	RX71M	R5F571MFDDL	PTLG0177K*	174			
115	RX71M	R5F571MFGDL	PTLG0177K*	175			
116	RX71M	R5F571MFHDL	PTLG0177K*	176			
117	RX71M	R5F571MGCDL	PTLG0177K*	177			
118	RX71M	R5F571MGDDL	PTLG0177K*	178			
119	RX71M	R5F571MGDDL	PTLG0177K*	179			
120	RX71M	R5F571MGHDL	PTLG0177K*	180			
121	RX71M	R5F571MJCDL	PTLG0177K*	181			
122	RX71M	R5F571MJDDL	PTLG0177K*	182			
123	RX71M	R5F571MJGDL	PTLG0177K*	183			
124	RX71M	R5F571MJHDL	PTLG0177K*	184			
125	RX71M	R5F571MLCDL	PTLG0177K*	185			
126	RX71M	R5F571MLDDL	PTLG0177K*	186			
127	RX71M	R5F571MLGDL	PTLG0177K*	187			
128	RX71M	R5F571MLHDL	PTLG0177K*	188			
129	RX71M	R5F571MFCDLJ	PTLG0100J*	189			
130	RX71M	R5F571MFDDLJ	PTLG0100J*	190			
131	RX71M	R5F571MFGDLJ	PTLG0100J*	191			
132	RX71M	R5F571MFHDLJ	PTLG0100J*	192			
133	RX71M	R5F571MGCDLJ	PTLG0100J*	193			
134	RX71M	R5F571MGDDLJ	PTLG0100J*	194			
135	RX71M	R5F571MGDDLJ	PTLG0100J*	195			
136	RX71M	R5F571MGHDLJ	PTLG0100J*	196			
137	RX71M	R5F571MJCDLJ	PTLG0100J*	197			
138	RX71M	R5F571MJDDLJ	PTLG0100J*	198			
139	RX71M	R5F571MJGDLJ	PTLG0100J*	199			
140	RX71M	R5F571MJHDLJ	PTLG0100J*	200			
141	RX71M	R5F571MLCDLJ	PTLG0100J*	201			
142	RX71M	R5F571MLDDLJ	PTLG0100J*	202			
143	RX71M	R5F571MLGDLJ	PTLG0100J*	203			
144	RX71M	R5F571MLHDLJ	PTLG0100J*	204			
145	RX71M	R5F571MFCDLK	PTLG0145K*	205			
146	RX71M	R5F571MFDDLK	PTLG0145K*	206			
147	RX71M	R5F571MFGDLK	PTLG0145K*	207			
148	RX71M	R5F571MFHDLK	PTLG0145K*	208			
149	RX71M	R5F571MGCDLK	PTLG0145K*	209			
150	RX71M	R5F571MGDDLK	PTLG0145K*	210			
151	RX71M	R5F571MGDDLK	PTLG0145K*	211			
152	RX71M	R5F571MGHDLK	PTLG0145K*	212			
153	RX71M	R5F571MJCDLK	PTLG0145K*	213			
154	RX71M	R5F571MJDDLK	PTLG0145K*	214			
155	RX71M	R5F571MJGDLK	PTLG0145K*	215			
156	RX71M	R5F571MJHDLK	PTLG0145K*	216			
157	RX71M	R5F571MLCDLK	PTLG0145K*	217			
158	RX71M	R5F571MLDDLK	PTLG0145K*	218			
159	RX71M	R5F571MLGDLK	PTLG0145K*	219			
160	RX71M	R5F571MLHDLK	PTLG0145K*	220			