Old Company Name in Catalogs and Other Documents

On April 1st, 2010, NEC Electronics Corporation merged with Renesas Technology Corporation, and Renesas Electronics Corporation took over all the business of both companies. Therefore, although the old company name remains in this document, it is a valid Renesas Electronics document. We appreciate your understanding.

Renesas Electronics website: http://www.renesas.com

April 1st, 2010 Renesas Electronics Corporation

Issued by: Renesas Electronics Corporation (http://www.renesas.com)

Send any inquiries to http://www.renesas.com/inquiry.



HITACHI MICROCOMPUTER TECHNICAL UPDATE

DATE	27 September 2001	No.	Т	N-SH7-359A/E
ТНЕМЕ	SH3-DSP usage notice on DMAC Indirect address transfer mode			
CLASSIFICATION	☐ Spec change ☐ Limitation on Use ☐ Supplement of Documents			
PRODUCTNAME	HD6417729, HD6417729R, HD6417727			Lot No.etc.
REFERENCE	HD6417729 Hardware Manual, HD6417729R Hardware	e Rev	v.	EffectiveDate
DOCUMENTS	Manual, HD6417727 Hardware Manual	<u> </u>		From
SH3-DSP series HD6417729, HD6417729R, and HD6417727 have following usage notice.				
1. Phenomenon				
When you use data	transfer from XY memory by DMAC, if all the	followin	ng con	nditions are satisfied,
it will be accessed	by the big endian.			
Condition:				
(1) Data transfer fro	om XY memory			
(2) Indirect address	s transfer mode.			
(3) Byte size (8 bits	s) data.			
(4) Little endian.				
2. Work Around				
When you use data	transfer from XY memory by DMAC, please us	se one o	of fol	lowing methods.
(1) Please use direct address transfer mode.				
(2) Please use longword size (32 bits) or word size (16 bits).				
(3) Please use the big endian.				
· I				