

Outline

When using the License Manager, note the following point.

1. License authentication of License Manager

1. License Authentication of License Manager

1.1 Applicable Products

(1) License Manager

- License Manager V2.02.00

(Packaged in the e² studio integrated development environment V7.0.0 and CS+ integrated development environment V7.00.00)

(2) Any of the following compilers

- CC-RL V1.00.00 to V1.03.00
- CC-RX V2.00.00 to V2.05.00
- CC-RH V1.00.00 to V1.04.00

(3) Any of the following licenses

- Compiler Standard V1 for RL78 (CC-RL) node locked license (permanent)
- Compiler Standard V2 for RX (CC-RX) node locked license (permanent)
- Compiler Standard V1 for RH850 (CC-RH) node locked license (permanent)
- Compiler Upgrade (edition) Professional V1 for RL78 (CC-RL) node locked license (permanent)
- Compiler Upgrade (edition) Professional V2 for RX (CC-RX) node locked license (permanent)
- Compiler Upgrade (edition) Professional V1 for RH850 (CC-RH) node locked license (permanent)

1.2 Details

A license of the compiler is disabled when registered in the License Manager of the applicable products. Once the license is disabled, the compiler will operate as an evaluation edition and when you run a build, one of the following warning or error messages will be output.

- E0511178: The xx option has no effect in this license.
- W0561016: The evaluation version is valid for the remaining xx days.
- W0561017: The evaluation period has expired.
- W0511179: The evaluation version is valid for the remaining xx days.
- W0511180: The evaluation period has expired.

1.3 Conditions

A warning or error will occur if a build is run with a combination of the License Manager, compiler and license of the versions listed in 1.1 Applicable Products.

1.4 Workaround

Install the License Manager V2.01.00 and re-register the license key by following the steps below.

Note, however, that the following licenses that are newly supported in the License Manager V2.02.00 will no longer be available.

- Compiler Upgrade (version) Standard V2 for RH850 (CC-RH) node locked license (permanent)
- Compiler Upgrade (version) Professional V2 for RH850 (CC-RH) node locked license (permanent)

(1) Uninstalling License Manager V2.02.00

(1-1) For Windows 10

Open [Settings] in the start menu → [Apps], then select [Renesas Electronics MCU Tools License Manager] to uninstall the program.

(1-2) For Windows 8.1

Open [Control Panel] in the start screen → [Uninstall a program] or [Programs and Features], then select [Renesas Electronics MCU Tools License Manager] to uninstall the program

(1-3) For Windows 7

Open [Control Panel] in the start menu → [Uninstall a program] or [Programs and Features], then select [Renesas Electronics MCU Tools License Manager] to uninstall the program.

(2) Installing License Manager V2.01.00

Download the installer for the License Manager V2.01.00 from the following URL and install the License Manager.

Download page for License Manager V2.01.00

<https://www.renesas.com/software/D4000398.html>

(3) Re-registering the license key

(3-1) For Windows 10

Select [All Apps] in the start menu → [Renesas Electronics Utilities] → [Renesas License Manager] to start the License Manager, delete the license key, then add it back to re-register.

(3-2) For Windows 8.1

Select [Renesas License Manager] in the start screen to start the License Manager, delete the license key, then add it back to re-register.

(3-3) For Windows 7

Select [All Programs] in the start menu → [Renesas Electronics Utilities] → [Renesas License Manager] to start the License Manager, delete the license key, then add it back to re-register.

1.5 Schedule for Fixing the Problem

This problem will be fixed in the License Manager V2.02.01. The revision update will be available on September 20, 2018.

Revision History

Rev.	Date	Description	
		Page	Summary
1.00	Sep. 01, 2018	-	First edition issued

TOYOSU FORESIA, 3-2-24 Toyosu, Koto-ku, Tokyo 135-0061 Japan
 Renesas Electronics Corporation

■Inquiry

<https://www.renesas.com/contact/>

Renesas Electronics has used reasonable care in preparing the information included in this document, but Renesas Electronics does not warrant that such information is error free. Renesas Electronics assumes no liability whatsoever for any damages incurred by you resulting from errors in or omissions from the information included herein.

The past news contents have been based on information at the time of publication. Now changed or invalid information may be included.

The URLs in the Tool News also may be subject to change or become invalid without prior notice.

All trademarks and registered trademarks are the property of their respective owners.