

Customer Notification

QB-78K0KX1H

In-Circuit Emulator

Operating Precautions

Target Devices

78K0/Kx1 Series

78K0/Kx1+ Series

DISCLAIMER

The related documents in this customer notification may include preliminary versions. However, preliminary versions may not have been marked as such.

The information in this customer notification is current as of its date of publication. The information is subject to change without notice. For actual design-in, refer to the latest publications of NEC's data sheets or data books, etc., for the most up-to-date specifications of NEC PRODUCT(S). Not all PRODUCT(S) and/or types are available in every country. Please check with an NEC sales representative for availability and additional information.

No part of this customer notification may be copied or reproduced in any form or by any means without prior written consent of NEC. NEC assumes no responsibility for any errors that may appear in this customer notification. NEC does not assume any liability for infringement of patents, copyrights or other intellectual property rights of third parties by or arising from the use of NEC PRODUCT(S) listed in this customer notification or any other liability arising from the use of such PRODUCT(S).

No license, express, implied or otherwise, is granted under any patents, copyrights or other intellectual property rights of NEC or others. Descriptions of circuits, software and other related information in this customer notification are provided for illustrative purposes of PRODUCT(S) operation and/or application examples only. The incorporation of these circuits, software and information in the design of customer's equipment shall be done under the full responsibility of customer. NEC assumes no responsibility for any losses incurred by customers or third parties arising from the use of these circuits, software and information.

While wherever feasible, NEC endeavors to enhance the quality, reliability and safe operation of PRODUCT(S) the customer agree and acknowledge that the possibility of defects and/or erroneous thereof cannot be eliminated entirely. To minimize risks of damage to property or injury (including death) to persons arising from defects and/or errors in PRODUCT(S) the customer must incorporate sufficient safety measures in their design, such as redundancy, fire-containment and anti-failure features.

The customer agrees to indemnify NEC against and hold NEC harmless from any and all consequences of any and all claims, suits, actions or demands asserted against NEC made by a third party for damages caused by one or more of the items listed in the enclosed table of content of this customer notification for PRODUCT(S) supplied after the date of publication.

Applicable Law:

The law of the Federal Republic of Germany applies to all information provided by NEC to the Customer under this Operating Precaution document without the possibility of recourse to the Conflicts Law or the law of 5th July 1989 relating to the UN Convention on Contracts for the International Sale of Goods (the Vienna CISG agreement).

Düsseldorf is the court of jurisdiction for all legal disputes arising directly or indirectly from this information. NEC is also entitled to make a claim against the Customer at his general court of jurisdiction.

If the supplied goods/information are subject to German, European and/or North American export controls, the Customer shall comply with the relevant export control regulations in the event that the goods are exported and/or re-exported. If deliveries are exported without payment of duty at the request of the Customer, the Customer accepts liability for any subsequent customs administration claims with respect to NEC.

Notes: (1) "**NEC**" as used in this statement means NEC Corporation and also includes its direct or indirect owned or controlled subsidiaries.

(2) "**PRODUCT(S)**" means 'NEC semiconductor products' (*NEC semiconductor products* means any semiconductor product developed or manufactured by or for NEC) and/or 'TOOLS' (*TOOLS* means 'hardware and/or software development tools' for NEC semiconductor products' developed, manufactured and supplied by 'NEC' and/or 'hardware and/or software development tools' supplied by NEC but developed and/or manufactured by independent 3rd Party vendors worldwide as their own product or on contract from NEC)

Table of Contents

(A)	Table of Operating Precautions	4
(B)	Description of Operating Precautions.....	5
(C)	Valid Specification.....	7
(D)	Revision History	8

QB-78K0KX1H

(A) Table of Operating Precautions

No.	Outline	Control Code ^{Note}	QB-78K0KX1H			
			C	D	E	G
1	Internal high-speed osc. operation during HALT (Technical Limitation)		X	✓	✓	✓
2	Caution on option byte (Specification change)		X	X	X	X
3	External memory access (Technical Limitation)		X	✓	✓	✓
4	Simultaneous occurrence of a software breakpoint and an interrupt (Technical Limitation)		X	X	✓	✓
5	Peripheral operation, when a special function register generates a wait during access and a break occurs simultaneously (Technical Limitation)		X	X	✓	✓
6	Illegal program execution, when an instruction is re-executed after a software breakpoint (Technical Limitation)		X	X	✓	✓
7	Internal ROM area is overwritten during program execution (Technical Limitation)		X	X	X	✓
8	Support of emulation for bootstrap function (Technical Limitation)		X	X	X	✓

✓ : Not applicable
 X : Applicable

Notes:

1. The “control code” is the second digit from the left in the 10-digit serial number in the warranty supplied with the product you purchased (if it has not been upgraded). If the product has been upgraded, a label indicating the new version is attached to the product and the x in V-UP LEVEL x on this label indicates the control code.
2. The Operating Precautions for products with control codes A, B are not content of this customer notification because these parts were not released here in EUROPE.
3. The control code “F” is not part of this operating precaution because it was not released in Europe.

(B) Description of Operating Precautions

No. 1	Internal high-speed osc. operation during HALT (Technical Limitation)
	<p><u>Details</u> As long as the operation clock for the watchdog timer is not stopped, the watchdog timer does not stop operation when the HALT instruction is executed. This happens even if the mask option “Internal high-speed osc. can be stopped by software” is set. As a result the reset signal is generated.</p>
No. 2	Caution on option byte function (Specification change)
	<p><u>Details</u> When using a microcontroller with on chip flash memory and option byte function, the function set by the option byte at address 0080H cannot be emulated. To set the option byte function pls. use the Mask Option dialog box of the debugger instead of the option byte</p>
No. 3	External memory access (Technical Limitation)
	<p><u>Details</u> When using the external memory (“Target” is selected in the memory Mapping area in the Configuration dialog box), data in the external memory cannot be displayed nor can data be written to the external memory using the Memory window or the Memory command. Accessing the external memory via the user program is performed normally.</p>
No. 4	Simultaneous occurrence of a software breakpoint and an interrupt (Technical Limitation)
	<p><u>Details</u> When a software breakpoint and an interrupt occurs simultaneously during program execution the content of the program counter becomes illegal.</p> <p><u>Workaround</u> Please use hardware breakpoints.</p>
No. 5	Peripheral operation, when an special function register generates a wait during access and a break occurs simultaneously (Technical Limitation)
	<p><u>Details</u> When a special function register generates a wait during access, a break occurs simultaneously and the peripheral break function is enabled, the peripheral continues operation, instead to stop operation.</p> <p>Example: Each time, when the watch window or SFR window are refreshed, waits will be generated. The count value of the timer SFR will be counted up.</p>

Operating Precautions for QB-78K0KX1H™

No. 6	Illegal program execution, when an instruction is re-executed after a software breakpoint (Technical Limitation)
	<p><u>Detail</u> If a software breakpoint is set to a 2-byte instruction and the 2nd byte of this instruction is C0H, the values in the stack area become illegal after the break execution. As a result, the program counter may become illegal after re-execution of the instruction.</p> <p><u>Detail</u> Please use hardware breakpoints.</p>
No. 7	Internal ROM area is overwritten during program execution (Technical Limitation)
	<p><u>Details</u> Data in the internal ROM area may be overwritten if the Source window or Assemble window is open during program execution. As a result, an unexpected fail-safe break (such as Write Protect Break or Non Map Break) may occur.</p>
No. 8	Support of emulation for bootswap function (Technical Limitation)
	<p><u>Details</u> Emulation for the boot swap function is now supported. When using this function, use the tools in the following combinations.</p> <ul style="list-style-type: none">• ID78K0-QB: V3.00 or later• QB-78K0KX1H: Control code G or later

(C) Valid Specification

Item	Date published	Document No.	Document Title
1	April 2004 or later	U17081E	QB-78K0KX1H In-Circuit Emulator User's Manual

(D) Revision History

Item	Date published	Document No.	Comment
1	August, 2004	TPS-LE-OP-TQBKX1H-1	1 st Release
2	February, 2005	TPS-LE-OP-TQBKX1H-2	1 st Update, Level D added
3	November, 2005	TPS-LE-OP-TQBKX1H-3	2 nd Update, Items 4, 5 and 6 added due to addition of control code "E"
4	December 2007	TPS-LE-OP-TQBKX1H-4	3 rd Update Items 7 and 8 added due to addition of control code "G"