



Renesas Microcomputer

SuperH RISC engine Family Selection Guide

SH7750 Series

Application	Device			Memory				CPU			DMA		External Bus Interface		Clock	ADC	DAC	Timer				Watchdog timer	Serial Interface		Fbus	SSU/ Special I/O	CAN		Ethernet	USB HOST	USB Function	LCD	I/O Port		External Interrupt Pins	On-Chip Debug Function	Other Functions	Operating Frequency/ Supply Voltage	Operating Ambient Temperature (°C)	Package Code					
	Series	Group	Part No.	ROM (bytes)	RAM (bytes)	ROM Type*	Data flash/ E2Data flash	Cache Memory	Basic Instructions	Minimum Instruction Execution Time (ns)	FPU	MMU	DMAC (channels)	DTC/DMACII				Bus State Controller	Bus structure	Real Time Clock	Resolution x Channels		Resolution x Channels	8-bit			16-bit	32-bit					2-Phase Encoder Input	3-Phase Inverter Control							Clock Sync./ Clock Async.	Clock Sync. Only	Channels	Channels	Input Only (Numbers)
General-purpose	SH7760		HD6417760BL200AD	-	-				2.5 (@200MHz)			8/4 of them are available externally		SRAM/ SDRAM/ MPX/ Burst ROM/ Byte control SRAM/ PCMCIA		-	10-bit x 4			4(CMT)	3(TMU)			3	-	2		2		1(Full speed)		Yes	69 (Max.)		HAC x 2, SSI x 2, MultiMedia card interface (*Some pins for each module are multiplexed)	200MHz/1.5V, 3.3V(I/O)	-40 to 85	BP-256B							
			HD6417760BL200A						2.1 (@240MHz)																																				
	SH7751R			HD6417751RBG240						2.5 (@200MHz)			8/2 of them are available externally		Separate bus(8/16/32-bit)/ Multiplexed bus(32-bit)																			39 (Max.)			240MHz/1.5V, 3.3V(I/O)	-40 to 85	PRBG0292GA-A						
				HD6417751RBP200						2.1 (@240MHz)																																			
				HD6417751RBP240							2.5 (@200MHz)																																		
				HD6417751RBP240							2.1 (@240MHz)																																		
				HD6417751RFP240								2.5 (@200MHz)																																	
				HD6417751RFP200								2.1 (@240MHz)																																	
				HD6417751RFP200								2.5 (@200MHz)																																	
				HD6417751RFP200								2.1 (@240MHz)																																	
				HD6417751RFP240								2.5 (@200MHz)																																	
				HD6417751RFP240								2.1 (@240MHz)																																	
	SH7750R			HD6417750RBP200			L			2.5 (@200MHz)	Yes	Yes			SRAM/ DRAM/ SDRAM/ MPX/ Burst ROM/ Byte control SRAM/ PCMCIA																														
				HD6417750RBP240						2.1 (@240MHz)																																			
				HD6417750RBP200							2.5 (@200MHz)																																		
				HD6417750RBP240							2.1 (@240MHz)																																		
				HD6417750RFP240								2.5 (@200MHz)																																	
				HD6417750RFP240							2.1 (@240MHz)																																		
				HD6417750RFP200								2.5 (@200MHz)																																	
				HD6417750RFP200								2.1 (@240MHz)																																	
				HD6417750RFP240								2.5 (@200MHz)																																	
				HD6417750RFP240								2.1 (@240MHz)																																	
	SH7750S			HD6417750SP200W						2.5 (@200MHz)					Separate bus(8/16/32/64-bit)/ Multiplexed bus(32/64-bit)																														
				HD6417750SF1671						3 (@ 167MHz)																																			
				HD6417750SF200W							2.5 (@200MHz)																																		
				HD6417750SF167D							3 (@ 167MHz)																																		
				HD6417750SF167								2.5 (@200MHz)																																	
				HD6417750SF200								2.5 (@200MHz)																																	
				HD6417750S/BT133								3.8 (@ 133MHz)																																	
				HD6417750S/VF133																																									

★ : New product ★★ : Under development
 *F : Flash memory version, L : ROM-less version, M : Mask ROM version, O : One-time PROM version, Qz : QzROM version

SH7200 Series

Application	Device			Memory				CPU				DMA		External Bus Interface		Clock	ADC	DAC	Timer					Watchdog timer	Serial Interface		F-Cbus	SSU/Special Serial I/O	CAN Channels	Ethernet	USB HOST	USB Function	LCD	I/O Port		External Interrupt Pins	On-Chip Debug Function	Other Functions	Operating Frequency/Supply Voltage	Operating Ambient Temperature (°C)	Package Code	
	Series	Group	Part No.	ROM (bytes)	RAM (bytes)	ROM Type*	Data flash/E2Data flash	Cache Memory	CPU	Basic Instructions	Minimum Instruction Execution Time (ns)	FPU	MMU	DMAC (channels)	DTC/DMACII				Bus State Controller	Bus structure	Real Time Clock	Resolution x Channels	Resolution x Channels		8-bit	16-bit								32-bit	2-Phase Encoder Input							3-Phase Inverter Control
Industrial field	SH7200	SH7203	R5S72030W200FP	-	64K (high-speed) +16K (retention)	L	-	16K	SH2A-FPU core	112	-	-	8/4 of them are available externally)	-	Yes	-	Yes	-	-	-	5(MTU), 2(CMT)	-	-	-	-	1	4	4	8(SSUx 2, SSIx 4)	2	-	1(High-Speed)	High-Speed	Yes	16	82	17(NMI, IRQx 8, PINTx 8)	Yes	FLCTL, TFF-support, LCDC	200MHz/1.1 to 1.3V, 3.0 to 3.6V	-20 to 85	PRQP0240KC-A
		SH7206	R5S72060W200FPV	-	128K	-	-	16K, 4-wayset-associative	SH-2A core	91	5(@200MHz)	-	-	8/4 of them are available externally)	-	-	-	-	-	-	-	11(MTU2 x 6, MTU2S x 3, CMT x 2)	-	-	2(shared with MTU2, MTU2S)	1	4	1	-	-	-	-	-	8	71	9	-	200MHz/1.15 to 1.35V, 3.0 to 3.6V (bus)	-20 to 85	PLQP0176KD-A		
		SH7205	R5S72050W200BG	-	96K (high-speed) +16K (retention)	-	-	16K	SH2A-FPU core	112	-	Yes	-	8/4 of them are available externally)	14	Yes	-	Yes	-	-	-	9(MTU x 5, CMT x 4)	1(MTU2)	2(shared with MTU2)	1(shared with MTU2)	2	6	4	8(SSUx 2, SSIx 6)	2	-	2(High-Speed)	High-Speed	-	11	96	17(NMI, IRQx 8, PINTx 8)	-	FLCTL, ATAPI, 2DG	200MHz/1.1 to 1.3V, 3.0 to 3.6V	-20 to 85	PRBG0272GA-A
		SH7201	R5S72011RB120FP R5S72011RW100FP	-	32K	-	-	16K, 4-wayset-associative	SH-2A core	112	8.33(@120MHz) 10(@100MHz)	-	-	8/4 of them are available externally)	-	-	SRAM/SDRAM	Separate bus (8/16/32-bit)	Yes	-	-	2(TMR)	8(MTU2)	-	-	1	8	3	2(SSIx 2)	2	-	-	-	14	104	17	-	120MHz/3.0 to 3.6V 100MHz/3.0 to 3.6V	-20 to 70 -20 to 85	PLQP0176KB-A		

★ : New product ★★ : Under development

*F : Flash memory version, L : ROM-less version, M : Mask ROM version, O : One-time PROM version, Qz : QzROM version

SH7260 Series

Application		Device			Memory				CPU				DMA		External Bus Interface		Clock	ADC	DAC	Timer				Serial Interface			I/O Port		On-Chip Debug Function	Other Functions	Operating Frequency/Supply Voltage	Operating Ambient Temperature (°C)	Package Code										
	Series	Group	Part No.	ROM (bytes)	RAM (bytes)	ROM Type*	Data flash/E2Data flash	Cache Memory	CPU	Basic Instructions	Minimum Instruction Execution Time (ns)	FPU	MMU	DMAC (channels)	DTC/DMACII	Bus State Controller	Bus structure	Real Time Clock	Resolution x Channels	Resolution x Channels	8-bit	16-bit	32-bit	2-Phase Encoder Input	3-Phase Inverter Control	Watchdog timer	Clock Sync./Clock Async.	Clock Sync. Only	F2Bus	SSU/Special I/O				CAN Channels	Ethernet	USB HOST	USB Function	LCD	Input Only (Numbers)	CMOS I/O (Numbers)	External Interrupt Pins	On-Chip Debug	Others
Automotive, Industrial field	SH7260	SH7264	R5S7264MP144FPU	-	640K (SRAM) + 64K (high-speed)	L	-	16K	SH2A-FPU core	112	6.94 (@ 144MHz)	Yes	-	16	-	Yes	Separate bus (8/16-bit)	Yes	10-bit x 8	-	-	-	2(shared with MTU2)	1(shared with MTU2)	1	8	-	3	6(RSPIx 2, SSIx 4)	-	-	1(High-Speed)	High-Speed	-	8	115	17(NMI, IRQ x 8, PINT x 8)	Yes	Video in, Display cntl., CDROM Decoder, SRC, FLCTL	144MHz/1.1 to 1.3V (internal), 3.0 to 3.6V (peripheral)	-20 to 85	PLQP0208KB-A	
			2																											-20 to 85													
			-																											-20 to 85													
			-																											-20 to 85													
			2																											-20 to 85													
			-																											-20 to 85													
			2																											-20 to 85													
			-																											-20 to 85													
		SH7262	SH7262	R5S72624W144FPU	-	640K (SRAM) + 64K (high-speed)	L	-	16K	SH2A-FPU core	112	6.94 (@ 144MHz)	Yes	-	16	-	Yes	Separate bus (8/16-bit)	Yes	10-bit x 4	-	-	-	2(shared with MTU2)	1(shared with MTU2)	1	8	-	3	6(RSPIx 2, SSIx 4)	-	-	1(High-Speed)	High-Speed	-	4	89	17(NMI, IRQ x 8, PINT x 8)	Yes	Video in, Display cntl., CDROM Decoder, SRC, FLCTL	144MHz/1.1 to 1.3V (internal), 3.0 to 3.6V (peripheral)	-20 to 85	PLQP0176KB-A
				2																											-20 to 85												
				-																											-20 to 85												
				-																											-20 to 85												
				2																											-20 to 85												
				-																											-20 to 85												
				2																											-20 to 85												
				-																											-20 to 85												

★ : New product ★★ : Under development
 *F : Flash memory version, L : ROM-less version, M : Mask ROM version, O : One-time PROM version, Qz : QzROM version

SH7260 Series

Application	Device			Memory				CPU			DMA		External Bus Interface		Clock	ADC	DAC	Timer				Serial Interface			F-Cbus	SSU/ Special Serial I/O	CAN	Ethernet	USB HOST	USB Function	LCD	I/O Port		External Interrupt Pins	On-Chip Debug Function	Other Functions	Operating Frequency/ Supply Voltage	Operating Ambient Temperature (°C)	Package Code		
	Series	Group	Part No.	ROM (bytes)	RAM (bytes)	ROM Type*	Data flash/ E2Data flash	Cache Memory	CPU	Basic Instructions	Minimum Instruction Execution Time (ns)	FPU	MMU	DMAC (channels)				DTC/DMACII	Bus State Controller	Bus structure	Real Time Clock	Resolution x Channels	Resolution x Channels	8-bit								16-bit	32-bit							2-Phase Encoder Input	3-Phase Inverter Control
Automotive, Industrial fields	SH7263		R6S72630P200FP	-	64K (high-speed) +16K (retention)	L	-	16K	SH2A-FPU core	5 (@200MHz)	Yes	-	8/4 of them are available externally)	-	Yes	-	10-bit x 8	8-bit x 2	-	5 (MTU), 2 (CMT)	-	-	-	1	4	4	6 (SSU x 2, SSI x 4)	2	-	1 (High-Speed)	-	High-Speed	-	16	82	17 (NMI, IRQx 8, PINTx 8)	Yes	CDROM, SRC, FLCTL, TFF-support LCD	200MHz/ 1.1 to 1.3V, 3.0 to 3.6V	-40 to 85	PRQP0240KC-A
			R6S72631P200FP																																						
			R6S72632P200FP																																						
			R6S72633P200FP																																						
	SH7265			R6S72650P200BG	-	96K (high-speed) +16K (retention)	L	-	16K	SH-2A core	112	Yes	-	14	-	Yes	10-bit x 8	8-bit x 2	-	9 (MTU x 5, CMT x 4)	1 (MTU2)	-	-	2	6	-	8 (SSU x 2, SSI x 6)	2	-	2 (High-Speed)	-	11	96	-	Yes	FLCTL, ATAPI, 2DG, AAC encoder	200MHz/ 1.1 to 1.3V, 3.0 to 3.6V	-40 to 85	PRBG0272GA-A		
				R6S72651P200BG																																					
				R6S72652P200BG																																					
				R6S72653P200BG																																					
	SH7261			R6S72611RB120FP	-	32K	L	-	16K, 4-wayset-associative	SH-2A core	8.33 (@120MHz)	-	-	8/4 of them are available externally)	SRAM/SDRAM	Separate bus (8/16/32-bit)	-	2 (TMR)	6 (MTU2)	-	2 (shared with MTU2)	1 (shared with MTU2)	1	8	3	2 (SSI x 2)	3 (SSI x 2, IEbus)	2	-	-	-	14	104	17	-	Yes	120MHz/ 3.0 to 3.6V	-20 to 70	PLQP0176KB-A		
				R6S72611RP100FP																																					
				R6S72612RB120FP																																					
				R6S72612RP100FP																																					
				R6S72613RB120FP																																					
				R6S72613RP100FP																																					

★ : New product ★★ : Under development
 *F : Flash memory version, L : ROM-less version, M : Mask ROM version, O : One-time PROM version, Qz : QzROM version

SH7260 Series

Application	Device			Memory				CPU				DMA		External Bus Interface		Clock	ADC	DAC	Timer					Watchdog timer	Serial Interface		Fbus	SSU/Special I/O	CAN	Ethernet	USB HOST	USB Function	LCD	I/O Port		External Interrupt Pins	On-Chip Debug Function	Other Functions	Operating Frequency/Supply Voltage	Operating Ambient Temperature (°C)	Package Code	
	Series	Group	Part No.	ROM (bytes)	RAM (bytes)	ROM Type*	Data flash/E2Data flash	Cache Memory	CPU	Basic Instructions	Minimum Instruction Execution Time (ns)	FPU	MMU	DMAC (channels)	DTC/DMACII				Bus State Controller	Bus structure	Real Time Clock	Resolution x Channels	Resolution x Channels		8-bit	16-bit								32-bit	2-Phase Encoder Input							3-Phase Inverter Control
Automotive, Industrial fields	SH7260	SH726A	R5S726ADD216FP**	-	1250K(SRAM) + 64K(high-speed)	L	-	8K(instruction), 8K(data), 4-way set-associative	SH2A-FPU core	112	4.6 (@216MHz)	Yes	-	16	-	Yes	Separate bus (8/16-bit)	Yes	10-bit x 6	-	-	7(MTU2 x 5, CMTx 2)	-	2(shared with MTU2)	1(shared with MTU2)	1	5	-	4	8(RSPI x 2, SPIMulti x 1, SSI x 4, SPDIF x 1)	-	1(Full-Speed)	Full-Speed	-	8	57	17(NMI, IRQx 8, PINT x 8)	Yes	SPIBSC, CDROM Decoder, SRC, SD	216MHz/1.15 to 1.35V (internal), 3.0 to 3.6V (peripheral)	-40 to +85	PLQP0120KA-A
			R5S726AUP216FP**																												2											PLQP0120LA-A
			R5S726A1D216FP**																												-											
			R5S726A2P216FP**																												-											
			R5S726A3D216FP**																												2											
	SH7260	SH726B	R5S726B0D216FP**	-	1250K(SRAM) + 64K(high-speed)	L	-	8K(instruction), 8K(data), 4-way set-associative	SH2A-FPU core	112	4.6 (@216MHz)	Yes	-	16	-	Yes	Separate bus (8/16-bit)	Yes	10-bit x 8	-	-	7(MTU2 x 5, CMTx 2)	-	2(shared with MTU2)	1(shared with MTU2)	1	5	-	4	9(RSPI x 3, SPIMulti x 1, SSI x 4, SPDIF x 1)	-	2(Full-Speed)	Full-Speed	-	12	74	17(NMI, IRQx 8, PINT x 8)	Yes	SPIBSC, CDROM Decoder, SRC, SD	216MHz/1.15 to 1.35V (internal), 3.0 to 3.6V (peripheral)	-40 to +85	PLQP0144KA-A
			R5S726B0P216FP**																												-											
			R5S726B1D216FP**																												2											
			R5S726B1P216FP**																												-											
			R5S726B2P216FP**																												2											

★ : New product ★★ : Under development

*F : Flash memory version, L : ROM-less version, M : Mask ROM version, O : One-time PROM version, Qz : QzROM version

SH-Ether Series

Application	Device			Memory				CPU				DMA		External Bus Interface		Clock	ADC	DAC	Timer					Serial Interface		F-Cbus	SSU/ Special I/O	CAN		Ethernet	USB HOST	USB Function	LCD	I/O Port		External Interrupt Pins	On-Chip Debug Function	Other Functions	Operating Frequency/ Supply Voltage	Operating Ambient Temperature (°C)	Package Code									
	Series	Group	Part No.	ROM (bytes)	RAM (bytes)	ROM Type*	Data flash/ E2Data flash	Cache Memory	CPU	Basic Instructions	Minimum Instruction Execution Time (ns)	FPU	MMU	DMAC (channels)	DTC/DMACII				Bus State Controller	Bus structure	Real Time Clock	Resolution x Channels	Resolution x Channels	8-bit	16-bit			32-bit	2-Phase Encoder Input					3-Phase Inverter Control	Watchdog timer		Clock Sync./ Clock Async.	Clock Sync. Only				Channels	Ethernet	USB HOST	USB Function	Input Only (Numbers)	CMOS I/O (Numbers)	On-Chip Debug	Others	
Communications	SH7615	SH7615	HD6417615ARB	-	8K	-	-	4K	SH2-DSP core	65	-	-	2	-	SRAM/ SDRAM/ DRAM/ Burst ROM	Separate bus (8/16/32-bit)	-	-	-	-	-	4(FRT, TPU x 3)	-	-	-	2	-	-	-	-	-	-	-	29	5(NMI + 4(15 level))	Yes	DSP function, E-DMAC x 2	62.5MHz/ 3.3V	-20 to 75	PLBG0240JA-A										
			HD6417615ARF	-	8K	-	-	4K	SH2-DSP core	65	16 (@62.5MHz)	-	-	-	-	SRAM/ SDRAM/ DRAM/ Burst ROM	Separate bus (8/16/32-bit)	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	29	5(NMI + 4(15 level))	Yes	DSP function, E-DMAC x 2	62.5MHz/ 3.3V	-20 to 75	PLQP0208KA-A										
	SH7618	SH7618	HD6417618ABG100V	-	4K	L	-	-	16K	SH-2 core	62	-	-	-	SRAM/ SDRAM/ Byte control SRAM/ PCMCIA	Separate bus (8/16-bit)	-	-	-	-	-	-	-	-	-	1	-	-	-	-	-	-	-	71	9(NMI + 8)	Yes	E-DMAC x 2	100MHz/ 1.4 to 1.6V, 3.0 to 3.6V (bus)	-40 to 85	PLBG0176GA-A										
			HD6417618ABG100V	-	4K	L	-	-	16K	SH-2 core	62	10 (@100MHz)	-	-	-	SRAM/ SDRAM/ Byte control SRAM/ PCMCIA	Separate bus (8/16-bit)	-	-	-	-	-	-	-	-	-	1	-	-	-	-	-	-	71	9(NMI + 8)	Yes	E-DMAC x 2	100MHz/ 1.4 to 1.6V, 3.0 to 3.6V (bus)	-40 to 85	PLBG0176GA-A										
	SH7619	SH7619	R4S76191B125B2GV	-	16K	-	-	-	16K	SH-2 core	62	-	-	-	SRAM/ SDRAM/ Byte control SRAM/ PCMCIA	Separate bus (8/16/32-bit)	-	-	-	-	-	-	-	-	-	3	-	-	-	-	-	-	-	78	9(NMI + 8)	Yes	E-DMAC x 2	125MHz/ 1.71 to 1.89V, 3.0 to 3.6V (bus)	-20 to 70 -40 to 85	PLBG0176GA-A										
			R4S76191D125B2GV	-	16K	-	-	-	16K	SH-2 core	62	8 (@125MHz)	-	-	-	SRAM/ SDRAM/ Byte control SRAM/ PCMCIA	Separate bus (8/16/32-bit)	-	-	-	-	-	-	-	-	-	3	-	-	-	-	-	-	78	9(NMI + 8)	Yes	E-DMAC x 2	125MHz/ 1.71 to 1.89V, 3.0 to 3.6V (bus)	-20 to 70 -40 to 85	PLBG0176GA-A										
	SH-Ether	SH7710	SH7710	HD6417710BP	-	16K	L	-	-	32K, 4-ways set-associative	SH3-DSP core	160	-	Yes	6(2 of them are available externally)	SRAM/ SDRAM/ Burst ROM/ Byte control SRAM/ PCMCIA	Separate bus (8/16/32-bit)	-	-	-	-	-	-	-	-	-	1	2	-	-	-	-	-	-	24	7(NMI + 4(15 level) or 6)	Yes	DSP function, IP sec. accelerator, E-DMAC x 4 DSP function, E-DMAC x 4	200MHz/ 1.5V(core), 3.3V(I/O)	-20 to 75	PLBG0256GA-A PRQP0256LA-B PRQP0256LA-B PRQP0256LA-B									
				HD6417710F	-	16K	L	-	-	32K, 4-ways set-associative	SH3-DSP core	160	5 (@200MHz)	-	Yes	6(2 of them are available externally)	SRAM/ SDRAM/ Burst ROM/ Byte control SRAM/ PCMCIA	Separate bus (8/16/32-bit)	-	-	-	-	-	-	-	-	-	1	2	-	-	-	-	-	-	24	7(NMI + 4(15 level) or 6)	Yes	DSP function, IP sec. accelerator, E-DMAC x 4 DSP function, E-DMAC x 4	200MHz/ 1.5V(core), 3.3V(I/O)	-20 to 75	PLBG0256GA-A PRQP0256LA-B PRQP0256LA-B								
				HD6417712BP	-	16K	L	-	-	32K, 4-ways set-associative	SH3-DSP core	160	5 (@200MHz)	-	Yes	6(2 of them are available externally)	SRAM/ SDRAM/ Burst ROM/ Byte control SRAM/ PCMCIA	Separate bus (8/16/32-bit)	-	-	-	-	-	-	-	-	-	1	2	-	-	-	-	-	-	24	7(NMI + 4(15 level) or 6)	Yes	DSP function, IP sec. accelerator, E-DMAC x 4 DSP function, E-DMAC x 4	200MHz/ 1.5V(core), 3.3V(I/O)	-20 to 75	PLBG0256GA-A PRQP0256LA-B PRQP0256LA-B								
				HD6417712F	-	16K	L	-	-	32K, 4-ways set-associative	SH3-DSP core	160	5 (@200MHz)	-	Yes	6(2 of them are available externally)	SRAM/ SDRAM/ Burst ROM/ Byte control SRAM/ PCMCIA	Separate bus (8/16/32-bit)	-	-	-	-	-	-	-	-	-	1	2	-	-	-	-	-	-	24	7(NMI + 4(15 level) or 6)	Yes	DSP function, IP sec. accelerator, E-DMAC x 4 DSP function, E-DMAC x 4	200MHz/ 1.5V(core), 3.3V(I/O)	-20 to 75	PLBG0256GA-A PRQP0256LA-B PRQP0256LA-B								
				HD6417713BP	-	16K	L	-	-	32K, 4-ways set-associative	SH3-DSP core	160	5 (@200MHz)	-	Yes	6(2 of them are available externally)	SRAM/ SDRAM/ Burst ROM/ Byte control SRAM/ PCMCIA	Separate bus (8/16/32-bit)	-	-	-	-	-	-	-	-	-	1	2	-	-	-	-	-	-	24	7(NMI + 4(15 level) or 6)	Yes	DSP function, IP sec. accelerator, E-DMAC x 4 DSP function, E-DMAC x 4	200MHz/ 1.5V(core), 3.3V(I/O)	-20 to 75	PLBG0256GA-A PRQP0256LA-B PRQP0256LA-B								
	SH7670	SH7670	SH7670	R5S76700B2008G	-	32K	L	-	-	D cache 8KB, I cache 8KB	SH2A-FPU core	112	yes	-	8(2 of them are available externally)	SRAM/ SDRAM/ Byte control SRAM/ PCMCIA	Separate bus (8/16/32-bit)	-	-	-	-	-	-	-	-	-	1	3	-	-	-	-	-	-	86	9(NMI + 8)	Yes	-	-	-20 to 70 -40 to 85	PRBG0256GA-A									
				R5S76700D1338G	-	32K	L	-	-	D cache 8KB, I cache 8KB	SH2A-FPU core	112	5(@200MHz) 75(@133MHz)	yes	-	8(2 of them are available externally)	SRAM/ SDRAM/ Byte control SRAM/ PCMCIA	Separate bus (8/16/32-bit)	-	-	-	-	-	-	-	-	-	1	3	-	-	-	-	-	-	-	-	86	9(NMI + 8)	Yes	-	-	-20 to 70 -40 to 85	PRBG0256GA-A						
				R5S7670B2008G	-	32K	L	-	-	D cache 8KB, I cache 8KB	SH2A-FPU core	112	5(@200MHz) 75(@133MHz)	yes	-	8(2 of them are available externally)	SRAM/ SDRAM/ Byte control SRAM/ PCMCIA	Separate bus (8/16/32-bit)	-	-	-	-	-	-	-	-	-	1	3	-	-	-	-	-	-	-	-	-	-	86	9(NMI + 8)	Yes	-	-	-20 to 70 -40 to 85	PRBG0256GA-A				
				R5S7670D1338G	-	32K	L	-	-	D cache 8KB, I cache 8KB	SH2A-FPU core	112	5(@200MHz) 75(@133MHz)	yes	-	8(2 of them are available externally)	SRAM/ SDRAM/ Byte control SRAM/ PCMCIA	Separate bus (8/16/32-bit)	-	-	-	-	-	-	-	-	-	1	3	-	-	-	-	-	-	-	-	-	-	-	-	86	9(NMI + 8)	Yes	-	-	-20 to 70 -40 to 85	PRBG0256GA-A		
				R5S76720B2008G	-	32K	L	-	-	D cache 8KB, I cache 8KB	SH2A-FPU core	112	5(@200MHz) 75(@133MHz)	yes	-	8(2 of them are available externally)	SRAM/ SDRAM/ Byte control SRAM/ PCMCIA	Separate bus (8/16/32-bit)	-	-	-	-	-	-	-	-	-	1	3	-	-	-	-	-	-	-	-	-	-	-	-	-	-	86	9(NMI + 8)	Yes	-	-	-20 to 70 -40 to 85	PRBG0256GA-A
				R5S76720D1338G	-	32K	L	-	-	D cache 8KB, I cache 8KB	SH2A-FPU core	112	5(@200MHz) 75(@133MHz)	yes	-	8(2 of them are available externally)	SRAM/ SDRAM/ Byte control SRAM/ PCMCIA	Separate bus (8/16/32-bit)	-	-	-	-	-	-	-	-	-	1	3	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	86	9(NMI + 8)	Yes	-	-	-20 to 70 -40 to 85

★ : New product ★★ : Under development

*F : Flash memory version, L : ROM-less version, M : Mask ROM version, O : One-time PROM version, Qz : QzROM version

SH7239, 7231, 7280 Series

Device				Memory				CPU				DMA		External Bus Interface		Clock	ADC	DAC	Timer				Serial Interface		CAN		I/O Port			On-Chip Debug Function		Other Functions		Operating Frequency / Supply Voltage	Operating Ambient Temperature (°C)	Package Code																																																			
Application	Series	Group	Part No.	ROM (bytes)	RAM (bytes)	ROM Type*	Data flash / E2Data flash	Cache Memory	CPU	Basic Instructions	Minimum Instruction Execution Time (ns)	FPU	MMU	DMAC (channels)	DTC/DMACII	Bus State Controller	Bus structure	Real Time Clock	Resolution x Channels	Resolution x Channels	8-bit	16-bit	32-bit	2-Phase Encoder Input	3-Phase Inverter Control	Watchdog timer	Clock Sync./ Clock Async.	Clock Sync. Only	F-Cbus	SSU / Special I/O	Channels	Ethernet	USB HOST				USB Function	LCD	Input Only (Numbers)	CMOS I/O (Numbers)	External Interrupt Pins	On-Chip Debug	Others																																												
General-purpose	SH7239*	SH7239*	R5F72394ADFP	256K	32K	F	32K (Data flash:FLD)	-	SH2A-FPU core	112	6.25 (@160MHz)	Yes	-	8 (4 of them are available externally)	DTC	SRAM/MPX-I/O	Separate bus (8/16-bit)/ Multiplexed bus (8/16-bit)	-	12-bit x 16	-	-	-	11 (MTU2 x 6, MTU2S x 3, CMT x 2)	-	2 (shared with MTU2)	2 (shared with MTU2, MTU2S)	1	4 (SCIx3, SCIFx1)	-	-	1 (RSPI)	1ch	-	-	-	-	-	-	16	69	8 (NMI + IRQ x 7)	Yes (User debug interface/ Advanced user's debuggers)	-	160MHz/ 3.0 to 3.6V	-40 to 85	PLQP0120KA-A																																									
			R5F72394BDFP	512K	64K											100MHz/ 4.5V to 5.5V																																																																							
			R5F72395BDFP													160MHz/ 3.0 to 3.6V																																																																							
		R5F72395ADFP	512K	64K	6.25 (@160MHz)											10 (@100MHz)	6.25 (@160MHz)																											10 (@100MHz)			160MHz/ 3.0V to 3.6V																																								
		SH7237*	SH7237*	SH7237*	R5F72374ADFP											256K	32K																											F			32K (Data flash:FLD)	-	SH-2A core	91	10 (@100MHz)	-	-	-	DTC	SRAM/MPX-I/O	Separate bus (8/16-bit)/ Multiplexed bus (8/16-bit)	-	12-bit x 16	-	-	-	12 (MTU2 x 6, MTU2S x 3, CMT x 2, TIM32C x 2)	-	1 (CMT2)	4 (shared with MTU2, TIM32C)	2 (shared with MTU2, MTU2S)	1	8 (SCIx4, SCIFx4)	-	-	1ch	-	-	-	-	-	-	-	22	162	25 (NMI + IRQ x 24)	Yes (User debug interface/ Advanced user's debuggers)	KEYC	100MHz/ 3.0 to 3.6V (core, I/O), 1.65 to 1.95 or 3.0 to 3.6V (I/O)	-20 to 85	PLBG0256KA-B
					R5F72374BDFP											512K	64K																																							100MHz/ 4.5V to 5.5V																															
	R5F72375BDFP				160MHz/ 3.0 to 3.6V																																																																																		
	R5F72375ADFP		512K	64K	6.25 (@160MHz)	10 (@100MHz)	6.25 (@160MHz)	10 (@100MHz)	160MHz/ 3.0V to 3.6V																																																																														
	SH7231		SH7231	SH7231	R5F72314LNBG**	768K	32KB+12KB	F	32K (Data flash:FLD)	-	SH2A-FPU core	112	10 (@100MHz)	Yes	-	4 (2 of them are available externally)	DTC	Direct connection to ROM/ SRAM/ SDRAM/ MPX-I/O/ The others is supported	Separate bus (8/16-bit)/ Multiplexed bus (8/16-bit)	-	10-bit x 16	-	-	2 (TIM32C x 2)	1 (CMT2)	4 (shared with MTU2, TIM32C)	2 (shared with MTU2, MTU2S)	1	8 (SCIx4, SCIFx4)	-	-	1ch	-	-	-	-	-	-	-	-	22	162	25 (NMI + IRQ x 24)		Yes (User debug interface/ Advanced user's debuggers)	KEYC										100MHz/ 3.0 to 3.6V (core, I/O), 1.65 to 1.95 or 3.0 to 3.6V (I/O)	-20 to 85																											PLBG0256KA-B			
					R5F72314LDBA**													KEYC																																																																					
		R5F72314LNBA**			KEYC																																																																																		
		R5F72315ANBA**			KEYC																																																																																		
R5F72315ADBA**		KEYC																																																																																					
R5F72315LNBA**		KEYC																																																																																					
SH7280		SH7280	SH7280	R5F72866D100FA	768K	32K	F	-	-	SH-2A core	91	10 (@100MHz)	-	-	8 (4 of them are available externally)	DTC	Direct connection to ROM/ SRAM/ SDRAM/ MPX-I/O/ The others is supported	Separate bus (8/16-bit)/ Multiplexed bus (8/16-bit)	-	12-bit x 12	8-bit x 2	-	11 (MTU2 x 6, MTU2S x 3, CMT x 2)	-	2 (shared with MTU2)	2 (shared with MTU2, MTU2S)	1	5 (SCI x 4, SCIF x 1)	-	-	1ch	-	-	-	-	-	-	-	-	-	14	99	9 (NMI + IRQ x 8)	Yes (User debug interface/ Advanced user's debuggers)	-	100MHz/ 3.0 to 5.5V	-40 to 85	PLQP0176LB-A PLQP0176KB-A PLQP0176LB-A PLQP0176KB-A PLQP0176LB-A PLQP0176KB-A PLQP0176LB-A PLQP0176KB-A PLQP0176LB-A PLQP0176KB-A																																							
				R5F72866D100FP													KEYC																																																																						
				R5F72866N100FA													KEYC																																																																						
				R5F72866N100FP													KEYC																																																																						
				R5F72867D100FA													KEYC																																																																						
				R5F72867D100FP													KEYC																																																																						
SH7285	SH7285	SH7285	R5F7285D100FP	768K	24K	F	-	-	SH-2A core	91	10 (@100MHz)	-	-	8 (4 of them are available externally)	DTC	Direct connection to ROM/ SRAM/ SDRAM/ MPX-I/O/ The others is supported	Separate bus (8/16-bit)/ Multiplexed bus (8/16-bit)	-	12-bit x 8	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-																																
			R5F7285D100FP													KEYC																																																																							
			R5F7285N100FA													KEYC																																																																							
			R5F7285N100FP													KEYC																																																																							
			R5F72866D100FP													KEYC																																																																							
			R5F72866N100FA													KEYC																																																																							

* : New product ** : Under development
 *F : Flash memory version, L : ROM-less version, M : Mask ROM version, O : One-time PROM version, Oz : OzROM version

SH7137, 7146 Series

Application	Device			Memory				CPU				DMA		External Bus Interface		Clock	ADC	DAC	Timer					Watchdog timer	Serial Interface		F-Cbus	SSU/ Special I/O	CAN	Ethernet	USB HOST	USB Function	LCD	I/O Port		External Interrupt Pins	On-Chip Debug Function	Other Functions	Operating Frequency/ Supply Voltage	Operating Ambient Temperature (°C)	Package Code			
	Series	Group	Part No.	ROM (bytes)	RAM (bytes)	ROM Type*	Data flash/ E2Data flash	Cache Memory	CPU	Basic Instructions	Minimum Instruction Execution Time (ns)	FPU	MMU	DMAC (channels)	DTC/DMACII				Bus State Controller	Bus structure	Real Time Clock	Resolution x Channels	Resolution x Channels		8-bit	16-bit								32-bit	2-Phase Encoder Input							3-Phase Inverter Control	Clock Sync./ Clock Async.	Clock Sync. Only
General-purpose	SH7137	SH7137	R5F7137A4D80FPV	256K	16K	F	-	-	SH-2 core	62	12.5 (@80MHz)	-	-	-	DTC	ROM/ SRAM	Separate bus (8-bit)	-	-	-	-	11 (MTU2 x 6, MTU2S x 3, CMT x 2)	-	2 (shared with MTU2)	2 (shared with MTU2, MTU2S)	1	3(SCI)	-	1	1	-	-	-	-	-	16	57	5 (NMI + IRQ x 4)	Yes (User debug interface)	-	80MHz/ 3.0 to 3.6V or 4.0 to 5.5V	-40 to 85	PLQP0100KB-A	
			R5F7137A4N80FPV	256K	16K											12	44																			-40 to 85								
		R5F71364A4D80FPV	256K	16K	12											44	-40 to 85																											
		R5F71323A4D80FPV	128K	8K	16											57	-40 to 85																											
		R5F71324A4D80FPV	256K	16K	16											57	-40 to 85																											
	SH7146	SH7149	SH7149	R5F71494A4D80FPV	256K	8K	F	-	-	SH-2 core	62	12.5 (@80MHz)	-	-	-	DTC	Direct connection to ROM, SRAM is supported	Separate bus (8/16-bit)	-	-	-	-	11 (MTU2 x 6, MTU2S x 3, CMT x 2)	-	2 (shared with MTU2)	2 (shared with MTU2, MTU2S)	1	3(SCI)	-	-	-	-	-	-	-	-	-	63	5 (NMI, IRQ x 4)	Yes (User debug interface)	-	80MHz/ 4.0 to 5.5V	-40 to 85	PLQP0100KB-A
				R5F71494A4N80FPV	256K	8K	M									-	-40 to 85																											
		R5M71494BXXXXFPV	256K	8K	F	-	-40 to 85																																					
		R5F71464A4D80FPV	256K	8K	M	-	-40 to 85																																					
		R5M71464BXXXXFPV	256K	8K	M	-	-40 to 85																																					

★ : New product ★★ : Under development

*F : Flash memory version, L : ROM-less version, M : Mask ROM version, O : One-time PROM version, Qz : QzROM version

SH/Tiny Series (SH7125)

Application	Device			Memory				CPU				DMA		External Bus Interface		Clock	ADC	DAC	Timer					Watchdog timer	Serial Interface		F2Cbus	SSU/Special Serial I/O	CAN Channels	Ethernet	USB HOST	USB Function	LCD	I/O Port		External Interrupt Pins	On-Chip Debug Function	Other Functions	Operating Frequency/Supply Voltage	Operating Ambient Temperature (°C)	Package Code																													
	Series	Group	Part No.	ROM (bytes)	RAM (bytes)	ROM Type*	Data flash/E2Data flash	Cache Memory	CPU	Basic Instructions	Minimum Instruction Execution Time (ns)	FPU	MMU	DMAC (channels)	DTC/DMACII				Bus State Controller	Bus structure	Real Time Clock	Resolution x Channels	Resolution x Channels		8-bit	16-bit								32-bit	2-Phase Encoder Input							3-Phase Inverter Control	Clock Sync./ Clock Async.	Clock Sync. Only	Input Only (Numbers)	CMOS I/O (Numbers)	On-Chip Debug	Others																						
General-purpose	SH/Tiny (SH7125)	SH7125	R5F71250AD50FA	16K	4K	F	-	-	SH-2 core	62	20 (@50MHz)	-	-	-	-	-	-	10-bit x 8	-	8 (MTU2 x 6, CMTx 2)	-	2 (shared with MTU2)	1 (shared with MTU2)	1	3(SCI)	-	-	-	-	-	-	8	37	5(NMI, IRQ x 4)	-40 to 85	PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																																
			R5F71250AD50FP																																-20 to 85	PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																																
			R5F71250AD50NP																																-40 to 85	PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																																
			R5F71250AN50FA																																-20 to 85	PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																																
			R5F71250AN50FP																																-40 to 85	PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																																
			R5F71250AN50NP																																-20 to 85	PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																																
			R5F71251AD50FA																																-40 to 85	PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																																
		R5F71251AD50FP	-20 to 85	PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																																																																
		R5F71251AD50NP	-40 to 85	PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																																																																
		R5F71251AN50FA	-20 to 85	PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																																																																
		R5F71251AN50FP	-40 to 85	PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																																																																
		R5F71251AN50NP	-20 to 85	PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																																																																
		R5F71252D50FA	64K	8K	F	-	-	SH-2 core	62	20 (@50MHz)	-	-	-	-	-	-	-	-	-	10-bit x 8	-	8 (MTU2 x 6, CMTx 2)	-	2 (shared with MTU2)	1 (shared with MTU2)	1	3(SCI)	-	-	-	-	-	8	37	5(NMI, IRQ x 4)	-40 to 85	PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																															
		R5F71252D50FP																																		-20 to 85	PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																															
	R5F71252D50NP	-40 to 85																																		PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																																
	R5F71252N50FA	-20 to 85																																		PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																																
	R5F71252N50FP	-40 to 85																																		PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																																
	R5F71252N50NP	-20 to 85																																		PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																																
	R5F71253D50FA	128K																																		8K	F	-	-	SH-2 core	62	20 (@50MHz)	-	-	-	-	-	-	-	-	-	10-bit x 8	-	8 (MTU2 x 6, CMTx 2)	-	2 (shared with MTU2)	1 (shared with MTU2)	1	2(SCI)	-	-	-	-	-	8	23	4(NMI, IRQ x 3)	-40 to 85	PRQP0064GC-A	PLQP0064KB-A
	R5F71253D50FP		-20 to 85	PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																																																																
	R5F71253D50NP		-40 to 85	PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																																																																
	R5F71253N50FA		-20 to 85	PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																																																																
	R5F71253N50FP		-40 to 85	PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																																																																
	R5F71253N50NP		-20 to 85	PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																																																																
	R5F71253N50NP		-40 to 85	PRQP0064GC-A	PLQP0064KB-A	PVQN0064LB-A																																																																
	R5F71240AD50FP	16K	4K	F	-	-	SH-2 core	62	20 (@50MHz)	-	-	-	-	-	-	-	-	-	10-bit x 8	-	8 (MTU2 x 6, CMTx 2)	-	2 (shared with MTU2)	1 (shared with MTU2)	1	2(SCI)	-	-	-	-	-	8	23	4(NMI, IRQ x 3)	-40 to 85	PRQP0048JA-A	PLQP0048JB-A	PVQN0052LE-A																																
	R5F71240AD50NP																																		-20 to 85	PRQP0048JA-A	PLQP0048JB-A	PVQN0052LE-A																																
	R5F71240AN50FP																																		-40 to 85	PRQP0048JA-A	PLQP0048JB-A	PVQN0052LE-A																																
R5F71241AD50FP	-20 to 85																																		PRQP0048JA-A	PLQP0048JB-A	PVQN0052LE-A																																	
R5F71241AN50NP	-40 to 85																																		PRQP0048JA-A	PLQP0048JB-A	PVQN0052LE-A																																	
R5F71241AN50FP	-20 to 85																																		PRQP0048JA-A	PLQP0048JB-A	PVQN0052LE-A																																	
R5F71242D50FA	64K																																		8K	F	-	-	SH-2 core	62	20 (@50MHz)	-	-	-	-	-	-	-	-	-	10-bit x 8	-	8 (MTU2 x 6, CMTx 2)	-	2 (shared with MTU2)	1 (shared with MTU2)	1	2(SCI)	-	-	-	-	-	8	23	4(NMI, IRQ x 3)	-40 to 85	PRQP0048JA-A	PLQP0048JB-A	PVQN0052LE-A
R5F71242D50NP		-20 to 85	PRQP0048JA-A	PLQP0048JB-A	PVQN0052LE-A																																																																	
R5F71242N50FA		-40 to 85	PRQP0048JA-A	PLQP0048JB-A	PVQN0052LE-A																																																																	
R5F71242N50FP		-20 to 85	PRQP0048JA-A	PLQP0048JB-A	PVQN0052LE-A																																																																	
R5F71242N50NP		-40 to 85	PRQP0048JA-A	PLQP0048JB-A	PVQN0052LE-A																																																																	
R5F71243D50FP		128K	8K	F	-	-	SH-2 core	62	20 (@50MHz)	-	-	-	-	-	-	-	-	-	10-bit x 8	-	8 (MTU2 x 6, CMTx 2)	-	2 (shared with MTU2)	1 (shared with MTU2)	1	2(SCI)	-	-	-	-	-	8	23	4(NMI, IRQ x 3)																																	-40 to 85	PRQP0048JA-A	PLQP0048JB-A	PVQN0052LE-A
R5F71243D50NP																																																																			-20 to 85	PRQP0048JA-A	PLQP0048JB-A	PVQN0052LE-A
R5F71243N50FA	-40 to 85																																		PRQP0048JA-A	PLQP0048JB-A	PVQN0052LE-A																																	
R5F71243N50FP	-20 to 85	PRQP0048JA-A	PLQP0048JB-A	PVQN0052LE-A																																																																		
R5F71243N50NP	-40 to 85	PRQP0048JA-A	PLQP0048JB-A	PVQN0052LE-A																																																																		

★ : New product ★★ : Under development
 *F : Flash memory version, L : ROM-less version, M : Mask ROM version, O : One-time PROM version, Qz : QzROM version

SH7144, 7060, 7047 Series

Application	Device			Memory				CPU				DMA		External Bus Interface		Clock	ADC	DAC	Timer					Watchdog timer	Serial Interface		F-Cbus	SSU/ Special I/O	CAN	Ethernet	USB HOST	USB Function	LCD	I/O Port		External Interrupt Pins	On-Chip Debug Function		Other Functions	Operating Frequency/ Supply Voltage	Operating Ambient Temperature (°C)	Package Code			
	Series	Group	Part No.	ROM (bytes)	RAM (bytes)	ROM Type*	Data flash/ E2Data flash	Cache Memory	CPU	Basic Instructions	Minimum Instruction Execution Time (ns)	FPU	MMU	DMAC (channels)	DTC/DMACII				Bus State Controller	Bus structure	Real Time Clock	Resolution x Channels	Resolution x Channels		8-bit	16-bit								32-bit	2-Phase Encoder Input		3-Phase Inverter Control	Clock Sync./ Clock Async.					Clock Sync. Only	Input Only (Numbers)	CMOS I/O (Numbers)
General-purpose	SH7144	SH7145	HD6417145F50V	256K	8K	L	-	-	SH-2 core	62	20 (@50MHz)	-	4(two of them are available externally)	DTC	Direct connection to ROM/ SRAM is supported	Separate bus (8/16/32-bit)	-	10-bit x 8	-	-	7 (MTU x 5, CMT x 2)	-	2 (shared with MTU)	1 (shared with MTU)	1	4(SCI)	-	-	-	-	-	-	-	8	98	9 (NMI, IRQ x 8)	-	-	50MHz/ 3.0 to 3.6V	-20 to 75	PLQP0144KB-A				
			HD6417145FW50V			F																																		-40 to 85					
			HD64F7145F50V			M																																		-20 to 75					
			HD6437145XXXF			-																																		-40 to 85					
			HD6437145XXXFW			-																																		-40 to 85					
			HD6437145WXXXFW			-																																		-40 to 85					
	SH7144	SH7144	HD6417144F50V	256K	8K	L	-	-	SH-2 core	62	16 (@60MHz)	-	4(two of them are available externally)	DTC	Direct connection to ROM/ SRAM is supported	Separate bus (8/16-bit)	-	10-bit x 8	8-bit x 2	-	5 (TPU x 2, CMT x 2, MMT)	-	4 (shared with TPU)	6 (MMT)	1	3	-	-	-	-	-	-	8	110	9	-	-	60MHz/3.3V (some of external I/O are available at 5V)	-20 to 75	PLQP0176KC-A PLQP0176KD-A					
	HD6417144FW50V	F	-40 to 85																																										
	HD64F7144F50V	M	-20 to 75																																										
	HD6437144WXXXFW	-	-40 to 85																																										
	HD6437144XXXFW	-	-40 to 85																																										
	HD6437144WXXXFW	-	-40 to 85																																										
SH7060	SH7065	HD64F7065AF80V	256K	8K	F	-	-	SH2-DSP core	182	16 (@60MHz)	-	4(two of them are available externally)	-	Direct connection to ROM/SRAM/ DRAM/EDO DRAM is supported	Separate bus (8/16/32-bit)	-	10-bit x 8	8-bit x 2	-	5 (TPU x 2, CMT x 2, MMT)	-	4 (shared with TPU)	6 (MMT)	1	3	-	-	-	-	-	8	110	9	-	-	60MHz/3.3V (some of external I/O are available at 5V)	-20 to 75	PLQP0176KC-A PLQP0176KD-A							
		HD6437065AXXXF			M																																								
SH7047	SH7049	SH7047	HD6437049XXXFW	128K	8K	F	-	-	SH-2 core	62	20 (@50MHz)	-	-	DTC	Direct connection to ROM/ SRAM is supported	Separate bus (8-bit)	-	10-bit x16	-	-	8 (MMTx 1, MTUx 5, CMTx 2)	-	2 (shared with MTU)	2 (MTU, MMT)	1	3(SCI)	-	-	-	-	-	-	16	53	5	-	-	50MHz/5.0V	-20 to 75	PRQP0100KB-A					
			HD64F7047F50V	256K	12K																					Yes (H-UDI)										40MHz/5.0V									
	SH7109	SH7109	HD6437109XXXFW	128K	4K	M	-	-	SH-2 core	62	20 (@50MHz)	-	-	-	Direct connection to ROM/ SRAM is supported	Separate bus (8-bit)	-	10-bit x16	-	-	8 (MMTx 1, MTUx 5, CMTx 2)	-	2 (shared with MTU)	2 (MTU, MMT)	1	2(SCI)	-	-	-	-	-	-	-	-	-	-	-	-	-		-	-	-	-	
	SH7107	SH7107	HD6437107XXXFW	64K	4K																					50MHz/5.0V																			-20 to 75
	SH7105	SH7105	HD6437105XXXFW	256K	8K																					50MHz/5.0V																			-20 to 75

★ : New product ★★ : Under development
 *F : Flash memory version, L : ROM-less version, M : Mask ROM version, O : One-time PROM version, Qz : QzROM version

SH7046 Series

Application	Device			Memory				CPU				DMA		External Bus Interface		Clock	ADC	DAC	Timer					Watchdog timer	Serial Interface		F-Cbus	SSU/ Special Serial I/O	CAN	Ethernet	USB HOST	USB Function	LCD	I/O Port		External Interrupt Pins	On-Chip Debug Function	Other Functions	Operating Frequency/ Supply Voltage	Operating Ambient Temperature (°C)	Package Code	
	Series	Group	Part No.	ROM (bytes)	RAM (bytes)	ROM Type*	Data flash/ E2Data flash	Cache Memory	CPU	Basic Instructions	Minimum Instruction Execution Time (ns)	FPU	MMU	DMAC (channels)	DTC/DMACII				Bus State Controller	Bus structure	Real Time Clock	Resolution x Channels	Resolution x Channels		8-bit	16-bit								32-bit	2-Phase Encoder Input							3-Phase Inverter Control
General-purpose	SH7046		HD64F7046F50V	256K	12K	F	-	-	SH-2 core	62	20 (@50MHz)	-	-	-	-	-	-	10-bit x 12	-	-	8(MTU x 5, CMTx 2, MMT x 1)	-	2(shared with MTU)	1(MTU)	1	2(SCI)	-	-	-	-	-	-	-	-	12	42	5(NMI, IRQ x 4)	-	-	50MHz/4.0 to 5.5V	-20 to 75	PRQP0080JD-A
			HD64F7046FW50V	64K	4K	M																																			-40 to 85	
			HD6437148RXXXF	128K	4K																																				-20 to 75	
			HD6437148RXXXFW	32K	2K																																				-40 to 85	
			HD6437048RXXXF	128K	4K																																				-20 to 75	
			HD6437101XXXFW	64K	4K																																				-40 to 85	
			HD6437108RXXXFW	64K	4K																																				-20 to 75	
			HD6437108RXXXFW	256K	4K																																				-40 to 85	

★ : New product ★★ : Under development
 *F : Flash memory version, L : ROM-less version, M : Mask ROM version, O : One-time PROM version, Qz : QzROM version

SH7040, 7010 Series


Application	Device			Memory				CPU			DMA		External Bus Interface		Clock	ADC	DAC	Timer					Watchdog timer	Serial Interface		F-Cbus	SSU/Special I/O	CAN		Ethernet	USB HOST	USB Function	LCD	I/O Port		External Interrupt Pins	On-Chip Debug Function	Other Functions	Operating Frequency/Supply Voltage	Operating Ambient Temperature (°C)	Package Code																																																																																																																		
	Series	Group	Part No.	ROM (bytes)	RAM (bytes)	ROM Type*	Data flash/E2Data flash	Cache Memory	CPU	Basic Instructions	Minimum Instruction Execution Time (ns)	FPU	MMU	DMAC (channels)				DTC/DMACII	Bus State Controller	Bus structure	Real Time Clock	Resolution x Channels		Resolution x Channels	8-bit			16-bit	32-bit					2-Phase Encoder Input	3-Phase Inverter Control							Clock Sync./Clock Async.	Clock Sync. Only	Channels	Channels	Input Only (Numbers)	CMOS I/O (Numbers)	On-Chip Debug	Others																																																																																																										
General-purpose	SH7040	SH7045	HD64F7045F28V	256K	4K(2K)*	F	-	1K	SH-2 core	62	-	-	4(two of them are available externally)	DTC	Direct connection to ROM/ SRAM/ DRAM is supported	Separate bus (8/16/32-bit)	-	10-bit x 8	-	-	7 (MTU x 5, CMT x 2)	-	2 (shared with MTU)	1 (shared with MTU)	1	2	-	-	-	-	-	-	-	-	8	74	9	-	-	28.7MHz/5.0V	-20 to 75	PRQP0144KB-A																																																																																																																	
			HD64F7045F128V			M																																			-40 to 85	FP-144																																																																																																																	
			HD6437045XXXFI			M																																			-20 to 75	PRQP0144KB-A																																																																																																																	
		HD64F7044F128V	256K	4K(2K)*	F	-																																			1K	SH-2 core	62	-	-	-	-	4(two of them are available externally)	DTC	Direct connection to ROM/ SRAM/ DRAM is supported	Separate bus (8/16-bit)	-	10-bit x 8	-	-	7 (MTU x 5, CMT x 2)	-	2 (shared with MTU)	1 (shared with MTU)	1	2	-	-	-	-	-	-	-	8	74	9	-	-	28.7MHz/5.0V	-20 to 75	PRQP0112JA-A																																																																															
		HD64F7044F28V			M																																																																						-40 to 85	PRQP0112JA-A																																																																															
		HD6437044XXXFI			M																																																																						-20 to 75	PRQP0112JA-A																																																																															
		HD6437043AV16V	128K	4K(2K)*	O																																																																						-	1K	SH-2 core	62	-	-	-	-	4(two of them are available externally)	DTC	Direct connection to ROM/ SRAM/ DRAM is supported	Separate bus (8/16/32-bit)	-	10-bit x 8	-	-	7 (MTU x 5, CMT x 2)	-	2 (shared with MTU)	1 (shared with MTU)	1	2	-	-	-	-	-	-	-	8	74	9	-	-	28.7MHz/5.0V	-20 to 75	PRQP0144KB-A																																												
		HD6477043AF128V			M																																																																																																									-40 to 85	FP-144																																												
		HD6477043AF28V			M																																																																																																									-20 to 75	PRQP0144KB-A																																												
		HD6437042AXXXFI	128K	4K(2K)*	M																																																																																																									-	1K	SH-2 core	62	-	-	-	-	4(two of them are available externally)	DTC	Direct connection to ROM/ SRAM/ DRAM is supported	Separate bus (8/16-bit)	-	10-bit x 8	-	-	7 (MTU x 5, CMT x 2)	-	2 (shared with MTU)	1 (shared with MTU)	1	2	-	-	-	-	-	-	-	8	74	9	-	-	28.7MHz/5.0V	-20 to 75	PRQP0112JA-A									
	HD6437042AXXXFI	M			-40 to 85		PRQP0112JA-A																																																																																																																																																				
	HD6437042AXXXFI	M			-20 to 75		PTQP0120LA-A																																																																																																																																																				
	HD6477042AF128V	128K	4K(2K)*	O	-		1K	SH-2 core	62	-	-	-	-	4(two of them are available externally)	DTC	Direct connection to ROM/ SRAM/ DRAM is supported	Separate bus (8/16/32-bit)	-	10-bit x 8	-	-	7 (MTU x 5, CMT x 2)	-	2 (shared with MTU)	1 (shared with MTU)	1	2	-	-	-	-	-	-	-	8	74	9	-	-	28.7MHz/5.0V																																																																																																									-20 to 75	PRQP0112JA-A									
	HD6477042AF28V			M		-40 to 85																																			PRQP0112JA-A																																																																																																																		
	HD6477042AV16V			M		-20 to 75																																			PTQP0120LA-A																																																																																																																		
	HD6417041AF28V	-	4K(2K)*	L		-																																			1K	SH-2 core	62	-	-	-	-	4(two of them are available externally)	DTC	Direct connection to ROM/ SRAM/ DRAM is supported	Separate bus (8/16/32-bit)	-	10-bit x 8	-	-	7 (MTU x 5, CMT x 2)	-	2 (shared with MTU)	1 (shared with MTU)	1	2	-	-	-	-	-	-	-	-	-	8	74	9	-																																																																							-	28.7MHz/5.0V	-20 to 75	PRQP0144KB-A							
	HD6417041AV16V			M																																																																							-40 to 85	FP-144																																																																															
	HD6437041AXXXFI			M																																																																							-20 to 75	PRQP0144KB-A																																																																															
	HD6417040AF28V	-	4K(2K)*	L																																																																							-	1K	SH-2 core	62	-	-	-	-	4(two of them are available externally)	DTC	Direct connection to ROM/ SRAM/ DRAM is supported	Separate bus (8/16-bit)	-	10-bit x 8	-	-	7 (MTU x 5, CMT x 2)	-	2 (shared with MTU)	1 (shared with MTU)	1	2	-	-	-	-	-	-	-	-	-	8	74	9	-																																						-	28.7MHz/5.0V	-20 to 75	PRQP0112JA-A					
	HD6417040AV16V			M																																																																																																										-40 to 85	PRQP0112JA-A																																												
HD6437040AXXXFI	M			-20 to 75																																																																																																										PTQP0120LA-A																																													
HD6417011VF28V	128K	4K(2K)*	F	-																																																																																																										1K	SH-2 core	62	-	-	-	-	4(two of them are available externally)	DTC	Direct connection to ROM/ SRAM/ DRAM is supported	Separate bus(8/16-bit)	-	10-bit x 8 (Middle speed)	-	-	5(MTU x 3, CMT x 2)	-	2(shared with MTU)	-	-	-	-	-	-	-	-	-	-	-	8	74	7	-	-	28.7MHz/5.0V					-20 to 75	PRQP0112JB-A					
HD647017F28V			M		-40 to 85		PRQP0112JA-A																																																																																																																																																				
HD6437016XXXFI			M		-20 to 75		PRQP0112JA-A																																																																																																																																																				
HD6417014F28V	-	3K(1K)*	L		-		1K	SH-2 core	62	-	-	-	-	4(two of them are available externally)	DTC	Direct connection to ROM/ SRAM/ DRAM is supported	Separate bus(16-bit)	-	10-bit x 8 (High-speed)	-	-	2(TIM1, TIM2)	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-																																																																																																													-	20MHz/3.3V	-	-			
HD6417014R28V			M			-40 to 85																																			PTQP0100KA-A																																																																																																																		
HD6417011VF20V	-	4K	L			-																																			1K	SH-2 core	62	-	-	-	-	4(two of them are available externally)	DTC	Direct connection to ROM/ SRAM/ DRAM is supported	Separate bus(16-bit)	-	10-bit x 7	-	-	2(TIM1, TIM2)	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-																																																																							-	-							-	-	-

* : New product ** : Under development
 *F : Flash memory version, L : ROM-less version, M : Mask ROM version, O : One-time PROM version, Qz : QzROM version

SH7030, 7020 Series

Application	Device			ROM (bytes)	RAM (bytes)	ROM Type*	Data flash/E2Data flash	Cache Memory	CPU	CPU			DMA	External Bus Interface	Clock	ADC	DAC	Timer					Watchdog timer	Serial Interface		I ² Cbus	SSU/Special I/O	CAN Channels	Ethernet	USB HOST	USB Function	LCD	I/O Port		External Interrupt Pins	On-Chip Debug Function	Other Functions	Operating Frequency/Supply Voltage	Operating Ambient Temperature (°C)	Package Code
	Series	Group	Part No.							Basic Instructions	Minimum Instruction Execution Time (ns)	FPU						MMU	DMAC (channels)	DTC/DMACII	Bus State Controller	Bus structure		Real Time Clock	Resolution x Channels								Resolution x Channels	8-bit						
General-purpose	SH7030	SH7034B	HD6417034BVF20V	64K	L				SH-1 core	56		4(two of them are available externally)	Direct connection to ROM/ SRAM/ DRAM is supported	Separate bus(8/16-bit)	10-bit x 8	-	-	5 (ITU)		1(shared with ITU)	1(shared with ITU)	1	2	-	-	-	-	-	-	-	-	8	32	9	-	-		20MHz/3.3V	-20 to 75	PRQP0112JA-A
			HD6417034BVF20V																	-20 to 75	PTQP0120LA-A																			
			HD6417034BXZ0V																	-20 to 75	PRQP0112JA-A																			
			HD6437034BXXXFX																	-20 to 75	PTQP0120LA-A																			
			HD6437034BXXXFXE																	-40 to 85	PTQP0120LA-A																			
			HD6437034BXXXXX																	-20 to 75	PTQP0120LA-A																			
		HD6417034VF12	64K	L					50(@20MHz)				80(@12.5MHz)				50(@20MHz)					1(shared with ITU)	1(shared with ITU)	1	2	-	-	-	-	-	-	8	32	9	-	-		20MHz/5.0V	-20 to 75	PRQP0112JA-A
		HD6417034VF12																																				-20 to 75	PRQP0112JA-A	
		HD6417034VF12																																				-20 to 75	PTQP0120LA-A	
		HD6417034VF12																																				-20 to 75	PTQP0120LA-A	
		HD6417034VF12																																				-20 to 75	PTQP0120LA-A	
		HD6417034VF12																																				-20 to 75	PTQP0120LA-A	
		HD6417034VF12	64K	M																			1 (shared with ITU)	1 (shared with ITU)	1	2	-	-	-	-	-	8	32	9	-	-		20MHz/5.0V, 12.5MHz/3.3V	-20 to 75	PTQP0120LA-A
		HD6437034AXXXXFX																																				-40 to 85	PRQP0112JA-A	
		HD6437034AXXXXFX																																				-20 to 75	PTQP0120LA-A	
HD6437034AXXXXFXI	-40 to 85	PRQP0112JA-A																																						
HD6477034F20V	-20 to 75	PTQP0120LA-A																																						
HD6477034F20V	-20 to 75	PTQP0120LA-A																																						
SH7032	SH7032	SH7032	HD6417032VF20V	4K	L			SH-1 core	56		4(two of them are available externally)	Direct connection to ROM/ SRAM/ DRAM is supported	Separate bus(8/16-bit)	-	-	-	-	5 (ITU)			1	2	-	-	-	-	-	-	8	32	9	-	-		20MHz/5.0V	-20 to 75	PRQP0112JA-A			
HD6417032VF12V			-40 to 85																																PTQP0120LA-A					
HD6417032FI20V			-40 to 85																																PTQP0120LA-A					
SH7020	SH7021	SH7021	HD6437021SXXXX	32K	1K	M			SH-1 core	56		4(two of them are available externally)	Direct connection to ROM/ SRAM/ DRAM is supported	Separate bus(8/16-bit)	-	-	-	-	5 (ITU)		1(shared with ITU)	1(shared with ITU)	1	2	-	-	-	-	-	8	32	9	-	-		20MHz/5.0V, 12.5MHz/3.3V, 20MHz/5.0V	-20 to 75	PTQP0100KA-A		
			HD6437021SXXXXI																																	-40 to 85	PTQP0100KA-A			
			HD6477021X20IV																																	-20 to 75	PTQP0100KA-A			
			HD6477021VX12V																																	-20 to 75	PTQP0100KA-A			
	SH7020	SH7020	SH7020	HD6477021X20IV	1K	L			SH-1 core	56		4(two of them are available externally)	Direct connection to ROM/ SRAM/ DRAM is supported	Separate bus(8/16-bit)	-	-	-	-	5 (ITU)		1(shared with ITU)	1(shared with ITU)	1	2	-	-	-	-	-	8	32	9	-	-		20MHz/5.0V, 12.5MHz/3.3V	-20 to 75	PTQP0100KA-A		
	HD6477020VX12V			-20 to 75																																PTQP0100KA-A				
	HD6417020X20IV			-20 to 75																																PTQP0100KA-A				
	HD6417020X20IV			-20 to 75																																PTQP0100KA-A				
SH7020	SH7020	SH7020	HD6437020SXXXXI	16K	M			SH-1 core	56		4(two of them are available externally)	Direct connection to ROM/ SRAM/ DRAM is supported	Separate bus(8/16-bit)	-	-	-	-	5 (ITU)		1(shared with ITU)	1(shared with ITU)	1	2	-	-	-	-	-	8	32	9	-	-		20MHz/5.0V, 12.5MHz/3.3V	-20 to 75	PTQP0100KA-A			
HD6437020SXXXXX			-40 to 85																																PTQP0100KA-A					
SH7020	SH7020	SH7020	HD6437020SXXXXX	16K	M			SH-1 core	56		4(two of them are available externally)	Direct connection to ROM/ SRAM/ DRAM is supported	Separate bus(8/16-bit)	-	-	-	-	5 (ITU)		1(shared with ITU)	1(shared with ITU)	1	2	-	-	-	-	-	8	32	9	-	-		20MHz/5.0V, 12.5MHz/3.3V	-20 to 75	PTQP0100KA-A			

★ : New product ★★ : Under development
 *F : Flash memory version, L : ROM-less version, M : Mask ROM version, O : One-time PROM version, Qz : QzROM version



*A free evaluation version of the coding tool and flash programming software (Flash Development Toolkit) is provided.

SuperH Family Development Tool Lineup

MCU	Real Time OS	Software Tool	Emulator		Programming Tool
			On-Chip Debugging Emulator	Full-Spec Emulator	Programmer*4
SH4A-MULTI	-	C/C++ Compiler Package for SuperH Family (An integrated development environment*3, compiler and simulator are included.) The emulator-debugger is bundled with the emulator.)	E10A-USB	-	-
SH-4A Core	HI7750/4, HI7700/4*1, HI7300/PX*2			-	E8a*5, HS0008EASF5H*5 *6
SH-4 Core				-	-
SH-3 Core	HI7700/4*1			-	-
SH2A-DUAL	HI7200/MP			-	-
SH-2A Core				E200F	E8a*5, HS0008EASF5H*5 *6
SH-2 Core (including SH/Tiny)	HI7000/4		E200F, E6000H	E8a*5, HS0008EASF5H*5 *6	

*1. Compatible microcontrollers: SH-3, SH3-DSP and SH4AL-DSP

*2. Compatible microcontrollers: SH-4A and SH4AL-DSP

*3. The High-performance Embedded Workshop is provided as an integrated development environment.

*4. This programmer is for Renesas Flash on-board microcontrollers.

*5. The E8a and HS0008EASF5H are usable with the Flash Development Toolkit [R0C0000FDW04R] (Free evaluation version available).

*6. The HS0008EASF5H is used together with the F-ZTAT microcontroller on-board writing program Ver. 5.0 [HS6400FWIW5SR].

*For information about microcontrollers compatible with the emulator or emulator specifications, access the website: http://www.renesas.com/emulation_debugging
Compatible emulators may vary according to the microcontroller part number.

SuperH Tool

Get up and running quickly: Starter kit

Want to start evaluating the SuperH right away? The Renesas Starter Kit is just what you need. It brings together in a single package all the development tools needed for microcontroller evaluation and initial implementation. The control signals from the microcontroller are output to the expansion board interface of the CPU board, allowing connection to the target system under development for easy debugging.

Including:

- SuperH On-board CPU Board
- On-Chip Debugging Emulator E10A-USB for Starter Kit
- Multi region power supply
- Free evaluation version of the C/C++ Compiler Package (with simulator)
- Free evaluation version of the Flash Development Toolkit
- The High-performance Embedded Workshop is provided as an integrated development environment.



Visit this website for information about development environment products.

SuperH Family Development Environment Site

http://www.renesas.com/sh_tools


Partner Alliances

The Alliance Partner Program is a web system that provides Renesas microcontroller users with the latest information about a wide variety of solutions using partner company products and services in coordination with Renesas products.

Over 700 partner companies worldwide provide development tool products and a variety of services for Renesas microcontrollers needed by Renesas customers for product development. Renesas will continue strengthening and expanding its coordination with partner companies in the future and prepare the optimal solutions for our customers.

Renesas Starter Kit for SuperH RISC engine Family

Target Device		Product Name	Part Number
Series	Group		
SH/Tiny	SH/7124, SH7125	Renesas Starter Kit for SH7124	R0K571242S001BE
SH7080	SH7083, SH7084, SH7085, SH7086	Renesas Starter Kit for SH7086	R0K570865S001BE
SH7137	SH7131, SH7132, SH7136, SH7137	Renesas Starter Kit for SH7137	R0K571374S000BE
SH7200	SH7201	Renesas Starter Kit for SH7201	R0K572011S001BE
	SH7203	Renesas Starter Kit+ for SH7203	R0K572030S000BE
SH7210	SH7211	Renesas Starter Kit for SH7211	R0K572115S001BE
SH7216	SH7214, SH7216	Renesas Starter Kit+ for SH7216	R0K572167S000BE
SH7243, SH7280	SH7243, SH7285, SH7286	Renesas Starter Kit for SH7286	R0K572867S000BE
SH7260	SH7262, SH7264	Renesas Starter Kit+ for SH7264	R0K572643S000BE (with Linux CD)
			YR0K572643S000BE-L (without Linux CD)
SH7670	SH7670	Renesas Starter Kit+ for SH7670	R0K576700S000BE



Strong alliances with over 700 partner companies worldwide

Click the following URL to access information about SuperH Family compatible partner products and services.
http://www.renesas.com/sh_partners

Renesas Microcomputer SuperH RISC engine Family Selection Guide

Renesas Electronics Corporation

Notes:

1. All information included in this document is current as of the date this document is issued. Such information, however, is subject to change without any prior notice. Before purchasing or using any Renesas Electronics products listed herein, please confirm the latest product information with a Renesas Electronics sales office. Also, please pay regular and careful attention to additional and different information to be disclosed by Renesas Electronics such as that disclosed through our website.
 2. Renesas Electronics does not assume any liability for infringement of patents, copyrights, or other intellectual property rights of third parties by or arising from the use of Renesas Electronics products or technical information described in this document. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
 3. You should not alter, modify, copy, or otherwise misappropriate any Renesas Electronics product, whether in whole or in part.
 4. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation of these circuits, software, and information in the design of your equipment. Renesas Electronics assumes no responsibility for any losses incurred by you or third parties arising from the use of these circuits, software, or information.
 5. When exporting the products or technology described in this document, you should comply with the applicable export control laws and regulations and follow the procedures required by such laws and regulations. You should not use Renesas Electronics products or the technology described in this document for any purpose relating to military applications or use by the military, including but not limited to the development of weapons of mass destruction. Renesas Electronics products and technology may not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations.
 6. Renesas Electronics has used reasonable care in preparing the information included in this document, but Renesas Electronics does not warrant that such information is error free. Renesas Electronics assumes no liability whatsoever for any damages incurred by you resulting from errors in or omissions from the information included herein.
 7. Renesas Electronics products are classified according to the following three quality grades: "Standard", "High Quality", and "Specific". The recommended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below. You must check the quality grade of each Renesas Electronics product before using it in a particular application. You may not use any Renesas Electronics product for any application categorized as "Specific" without the prior written consent of Renesas Electronics. Further, you may not use any Renesas Electronics product for any application for which it is not intended without the prior written consent of Renesas Electronics. Renesas Electronics shall not be in any way liable for any damages or losses incurred by you or third parties arising from the use of any Renesas Electronics product for an application categorized as "Specific" or for which the product is not intended where you have failed to obtain the prior written consent of Renesas Electronics. The quality grade of each Renesas Electronics product is "Standard" unless otherwise expressly specified in a Renesas Electronics data sheets or data books, etc.
"Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; and industrial robots.
"High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control systems; anti-disaster systems; anti-crime systems; safety equipment; and medical equipment not specifically designed for life support.
"Specific": Aircraft; aerospace equipment; submersible repeaters; nuclear reactor control systems; medical equipment or systems for life support (e.g. artificial life support devices or systems), surgical implantations, or healthcare intervention (e.g. excision, etc.), and any other applications or purposes that pose a direct threat to human life.
 8. You should use the Renesas Electronics products described in this document within the range specified by Renesas Electronics, especially with respect to the maximum rating, operating supply voltage range, movement power voltage range, heat radiation characteristics, installation and other product characteristics. Renesas Electronics shall have no liability for malfunctions or damages arising out of the use of Renesas Electronics products beyond such specified ranges.
 9. Although Renesas Electronics endeavors to improve the quality and reliability of its products, semiconductor products have specific characteristics such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Further, Renesas Electronics products are not subject to radiation resistance design. Please be sure to implement safety measures to guard them against the possibility of physical injury, and injury or damage caused by fire in the event of the failure of a Renesas Electronics product, such as safety design for hardware and software including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult, please evaluate the safety of the final products or system manufactured by you.
 10. Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. Please use Renesas Electronics products in compliance with all applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive. Renesas Electronics assumes no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
 11. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of Renesas Electronics.
 12. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products, or if you have any other inquiries.
- (Note 1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries.
(Note 2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.
-



SALES OFFICES

<http://www.renesas.com>

Refer to "<http://www.renesas.com/>" for the latest and detailed information.

