

Tsi620 Ballmap -- Top View of Pin Assignment (Document 80D7000\_PN003\_05)

	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	
A	No Ball	GPIO[0]	GPIO[1]	GPIO[2]	PCI_AD[0]	PCI_AD[4]	PCI_CBE[0]	PCI_AD[11]	PCI_AD[15]	PCI_STOPn	PCI_FRAMEn	PCI_AD[18]	PCI_AD[22]	PCI_AD[24]	PCI_AD[28]	PCI_PMen	PCI_GNT[1]	PCI_RSTn	PCI_INTBn	PCI_LARBEN	PCI_CLKO[0]	I2C_SLAVE	CLKGEN_PLL_AVSS	CLKGEN_PLL_AVDD	I2C_SA[2]	I2C_SA[5]	
B	GPIO[3]	VSS_IO	GPIO[4]	GPIO[5]	VSS_IO	PCI_AD[2]	PCI_AD[8]	VSS_IO	PCI_AD[13]	PCI_PAR	VSS_IO	PCI_AD[16]	PCI_AD[20]	VSS_IO	PCI_AD[26]	PCI_AD[30]	VSS_IO	PCI_CLKO[1]	PCI_INTAn	VSS_IO	PCI_CLK	I2C_SA[8]	VSS_IO	I2C_SA[4]	VSS_IO	PCI_PLL_AVSS	
C	GPIO[6]	GPIO[7]	GPIO[8]	GPIO[9]	GPIO[10]	PCI_AD[5]	PCI_AD[7]	PCI_AD[9]	PCI_AD[12]	PCI_AD[14]	PCI_TRDYn	PCI_AD[21]	PCI_AD[23]	PCI_IDSEL	PCI_AD[29]	PCI_REQ[2]	PCI_REQ[1]	PCI_CLKO[2]	PCI_INTCn	PCI_RSTDIR	PCI_HOLD_BOOT	I2C_SA[3]	I2C_SCLK	I2C_SD	I2C_SA[0]	PCI_PLL_AVDD	
D	GPIO[11]	VSS_IO	GPIO[12]	GPIO[13]	NC	PCI_AD[1]	PCI_AD[8]	VSS_IO	PCI_CBE[1]	PCI_DEVSELn	VSS_IO	PCI_RDYn	PCI_CBE[3]	VSS_IO	PCI_AD[31]	PCI_REQ[3]	VSS_IO	PCI_GNT[3]	PCI_CLKO[3]	VSS_IO	PCI_PLL_BYPASS	I2C_SEL	NC	TRST_b	VSS_IO	TDI	
E	GPIO[14]	GPIO[15]	GPIO[16]	GPIO[17]	GPIO[18]	PCI_AD[3]	PCI_AD[10]	PCI_M66EN	PCI_SERRn	PCI_PERRn	PCI_CBE[2]	PCI_AD[17]	PCI_AD[19]	PCI_AD[27]	PCI_AD[25]	PCI_REQ[4]	PCI_GNT[2]	PCI_GNT[4]	PCI_CLKO[4]	PCI_INTCn	I2C_DISABLE	I2C_MA	I2C_SA[1]	TMS	TDO	TCK	
F	GPIO[19]	GPIO[20]	GPIO[21]	GPIO[22]	GPIO[23]	VSS_IO	VDD_PCI	VSS_IO	VDD_PCI	VSS_IO	VDD_PCI	VSS_IO	VDD_PCI	VSS_IO	VDD_PCI	VSS_IO	VDD_PCI	VSS_IO	VDD_PCI	VSS_IO	VDD_PCI	VSS	NC	VSS	VSS	BCE	
G	GPIO[24]	VSS_IO	GPIO[25]	VSS_IO	GPIO[26]	VDD_PCI	VSS_IO	VDD_PCI	VSS_IO	VDD_PCI	VSS_IO	VDD_PCI	VSS_IO	VDD_PCI	VSS_IO	VDD_PCI	VSS_IO	VDD_PCI	VSS_IO	VDD_PCI	VSS_IO	BLK_RST_b	VSS_IO	RST_IRQ_b	NC	CHIP_RST_b	
H	GPIO[27]	GPIO[28]	GPIO[29]	GPIO[30]	GPIO[31]	VSS_IO	VDD_PCI	VDD	VDD	VDD	VDD	VDD	VDD	VDD	VDD	VDD	VDD	VDD	VDD	VDD	VSS_IO	VDD_PCI	INT_b	SP_CLK_SEL[0]	SP_CLK_SEL[1]	SP_HOST	SP_MAST_EN
J	SP6_RXD[0]	SP6_RXD[1]	SP6_RXD[2]	SP6_RXD[3]	SP6_RXD[4]	VDD_HSTL	VSS_IO	VDD	VDD	VSS	VDD	VSS	VDD	VSS	VDD	VSS	VDD	VSS	VDD	VDD_PCI	VSS_IO	VDD_PCI	SP_TX_SWAP	SP_RX_SWAP	SP_IO_SPEED[1]	SP_IO_SPEED[0]	
K	SP6_RXD[5]	VSS_IO	SP6_RXD[6]	VSS_IO	SP6_RXD[7]	VSS_IO	VDD_HSTL	VDD	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VDD	VSS_IO	VDD_PCI	SP6_PWRDN	VSS_IO	SP4_PWRDN	VSS_IO	SP3_PWRDN
L	SP6_RXD[8]	SP6_RXD[9]	SP6_RXD[10]	SP6_RXD[11]	VDD_HSTL	VSS_IO	VDD	VDD	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VDD	VDD	VDD_PCI	VSS_IO	SP2_PWRDN	SP1_PWRDN	SP6_PWRDN	SP6_MODE_SEL	SP4_MODE_SEL
M	SP6_RXD[12]	SP6_RXD[13]	SP6_RXD[14]	SP6_RXD[15]	SP6_RXD[16]	VSS_IO	VDD_HSTL	VDD	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VDD	VSS_IO	VDD_PCI	NC	NC	MCES	SP2_MODE_SEL	SP0_MODE_SEL
N	SP6_RXD[16]	VSS_IO	SP6_VREF	VSS_IO	SP6_RXD[17]	VDD_HSTL	VSS_IO	VDD	VDD	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VDD	VDD	VDD_PCI	VSS	VSS	VSS	VSS	VSS	VSS	
P	SP6_RXCLK	SP6_RXD[18]	SP6_RXD[19]	SP6_RXD[20]	SP6_RXD[21]	VSS_IO	VDD_HSTL	VDD	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VDD	VSS	SP_VDD	SP0_RD_n	SP0_RD_p	SP_VDD	SP0_TD_n	SP0_TD_p	
R	SP6_RXD[22]	SP6_RXD[23]	SP6_RXD[24]	SP6_RXD[25]	VDD_HSTL	VSS_IO	VDD	VDD	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VDD	SP_AVDD	VSS	VSS	SP_VDD	VSS	VSS	SP_VDD	VSS
T	SP6_RXD[26]	VSS_IO	SP6_RXD[27]	VSS_IO	SP6_RXD[28]	VSS_IO	VDD_HSTL	VDD	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	SP_AVDD	VSS	SP0_RC_p	SP0_RC_n	SP_VDD	SP0_TC_n	SP0_TC_p
U	SP6_RXD[29]	SP6_RXD[30]	SP6_RXD[31]	SP6_RXD[32]	SP6_RX_ERROR	VDD_HSTL	VSS_IO	VDD	VDD	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VDD	SP_AVDD	VSS	VSS	SP_VDD	SP0_REXT	VSS	SP_VDD	VSS
V	SP6_TXD[0]	SP6_TXD[1]	SP6_TXD[2]	SP6_TXD[3]	SP6_TXD[4]	VSS_IO	VDD_HSTL	VDD	VSS	VDD	VSS	VDD	VSS	VDD	VSS	VDD	VSS	VSS	VSS	SP_AVDD	VSS	SP_VDD	SP0_RB_n	SP0_RB_p	SP_VDD	SP0_TB_p	SP0_TB_n
W	SP6_TXD[5]	VSS_IO	SP6_TXD[6]	VSS_IO	SP6_TXD[7]	VDD_HSTL	NC	VDD	VSS	SP_AVDD	SP_AVDD	SP_AVDD	VSS	SP_AVDD	SP_AVDD	SP_AVDD	VSS	SP_AVDD	SP_AVDD	VSS	VSS	SP_VDD	VSS	VSS	SP_VDD	VSS	
Y	SP6_TXD[10]	SP6_TXD[8]	SP6_TXD[9]	SP6_TXD[10]	SP6_TXD[11]	NC	NC	VSS	SP_AVDD	VSS	VSS	VSS	SP_AVDD	VSS	VSS	VSS	VSS	SP_AVDD	VSS	VSS	VSS	VSS	SP0_RA_p	SP0_RA_n	SP_VDD	SP0_TA_p	SP0_TA_n
AA	SP6_TXD[12]	SP6_TXD[13]	SP6_TXD[14]	SP6_TXD[15]	NC	SP_VDD	VSS	VSS	VSS	VSS	SP_VDD	VSS	VSS	VSS	SP_VDD	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS	VSS
AB	SP6_TXD[16]	VSS_IO	SP6_VREF	VSS_IO	SP6_TXD[16]	NC	SP4_RA_p	SP_VDD	SP4_RB_n	SP_VDD	SP4_RC_p	SP_VDD	SP4_RD_p	SP_VDD	SP2_RA_p	SP_VDD	SP2_RB_p	SP_VDD	SP2_RC_n	SP_VDD	SP2_RD_p	VSS	VSS	VSS	VSS	VSS	
AC	SP6_TXD[17]	SP6_TXD[18]	SP6_TXD[19]	SP6_TXD[20]	SP6_TXD[21]	NC	SP4_RA_n	VSS	SP4_RB_p	SP4_REXT	SP4_RC_n	VSS	SP4_RD_n	VSS	SP2_RA_n	VSS	SP2_RB_n	SP2_REXT	SP2_RC_p	VSS	SP2_RD_n	VSS	VSS	SP_VDD	VSS	VSS	
AD	SP6_TXD[22]	SP6_TXD[23]	SP6_TXD[24]	SP6_TXD[25]	VSS	SP_VDD	VSS	SP_VDD	VSS	SP_VDD	VSS	SP_VDD	VSS	SP_VDD	VSS	SP_VDD	VSS	SP_VDD	VSS	SP_VDD	VSS	SP_VDD	VSS	S_CLK_n	VSS	TCK2_n	VSS
AE	SP6_TXD[26]	VSS_IO	SP6_TXD[27]	VSS_IO	SP6_TXD[28]	VSS	SP4_TA_p	SP_VDD	SP4_TB_n	SP_VDD	SP4_TC_p	SP_VDD	SP4_TD_p	SP_VDD	SP2_TA_p	SP_VDD	SP2_TB_n	SP_VDD	SP2_TC_p	SP_VDD	SP2_TD_p	VSS	S_CLK_p	VSS	TCK2_p	VSS	
AF	SP6_TXD[29]	SP6_TXD[30]	SP6_TXD[31]	SP6_TXD[32]	SP6_PHY_DISABLE	VSS	SP4_TA_n	VSS	SP4_TB_p	VSS	SP4_TC_n	VSS	SP4_TD_n	VSS	SP2_TA_n	VSS	SP2_TB_p	VSS	SP2_TC_n	VSS	SP2_TD_n	VSS	VSS	SP_VDD	VSS	VSS	

Copyright © August 2009 IDT. All rights reserved. Published in Canada.

Disclaimer: IDT assumes no responsibility for the accuracy or completeness of the information presented, which is subject to change without notice. In no event will IDT be liable for any direct, indirect, special, incidental or consequential damages, including lost profits, lost business or lost data, resulting from the use of or reliance upon the information, whether or not IDT has been advised of the possibility of such damages. Mention of non-IDT products or services is for information purposes only and constitutes neither an endorsement nor a recommendation.

Note: NC stands for "no connect." If this device has no connect signals they must be left unconnected.

**Revision History**

August 2009, 80D7000\_PN003\_05 -- There have been no technical changes to the ballmap. The formatting has been update for IDT.

September 2008, 80D7000\_PN003\_04 -- Redefined the following pins as follows:

- M22 N/C
- M23 N/C
- J22 VDD\_PCI
- F22 VSS
- F23 N/C
- F24 VSS
- F25 VSS

October 2007, 80D7000\_PN003\_03 -- Removed the NDA status on the document. There were no technical changes made to this version.

September 2007, 80D7000\_PN003\_02 -- Changed the following pins to no connect: D5, D23, G25, W7, Y6, Y7, AA6, AB6, and AC6.