
RZ/G Verified Linux Package for 64bit kernel

Version 1.0.10

R01TU0283EJ0108

Rev. 1.08

Nov. 15, 2021

Patch application guide

Introduction

This document describes the contents of the “diff” files of RZ/G Verified Linux Package for 64bit kernel (hereinafter referred to as “VLP64”) and instructions to use them.

Please read the “Release Note” of VLP64 v1.0.10 carefully before using this document.

Contents

| | |
|---|---|
| 1. Release Items | 2 |
| 2. Patch Application Guide | 3 |
| 2.1 Patch Application Guide..... | 3 |
| 2.2 Patch Application Guide for HTML5 (Gecko78) | 5 |

1. Release Items

VLP64 is delivered by the files listed in **Table 1**. A develop environment of VLP64 v1.0.8 can be changed to that of VLP64 v1.0.10 by applying the patch files included in diff files without downloading basic packages.

Table 1. RZ/G Verified Linux Package

Diff files for VLP64 v1.0.8 users

| File | Explanation |
|--|--|
| r01tu0283ej0108-rz-g.pdf | This document |
| v108-to-v1010.patch.tar.gz (Evaluation and Product version) (43KB) v108-to-v1010_gecko78.patch.tar.gz (398KB) (*) | Diff files of Yocto recipes compared with VLP64 v1.0.8 |
| v108-to-v1010.oss_packages.7z (220MB) v108-to-v1010_gecko78.oss_packages.7z (320MB) | Diff file of OSS packages compared with VLP64 v1.0.8 |

Basic packages

| File | Explanation |
|---|--|
| rzg2_bsp_eva_v1010.tar.gz (Evaluation version) (65MB) rzg2_bsp_pro_v1010.tar.gz (Product version) (65MB) | Yocto recipe packages (including Multimedia package) |
| oss_pkg_v1010.7z (7.29GB) | Open source software packages |

Basic packages for HTML5 (Gecko) environment

| File | Explanation |
|---|---|
| rzg2_bsp_gecko78_v1010.tar.gz (592KB) (*) | Yocto recipe packages for HTML5 (Gecko78) |
| oss_pkg_gecko78_v1010.7z (1.75GB) (*) | Open source software packages for HTML5 (Gecko78) |

Documents

| File | Explanation |
|--------------------------|--------------------------------|
| r01tu0277ej0112-rz-g.pdf | Release Note |
| r01tu0311ej0110-rz-g.pdf | Release Note for HTML5 (Gecko) |
| r01tu0278ej0110-rz-g.pdf | Component list |

Note: (*) If you want to support Gecko68 instead of Gecko78, please use basic gecko packages from VLP64 v1.0.8 due to no changes.

The above packages are downloaded with the different file names like as "REN_rzg2_bsp_eva_v10x.tar.gz_ESW_2021xxxx.gz". When you use the packages, please rename them to the above file names.

Additional packages

| File | Description |
|---------------------------------------|-----------------------------|
| RTK0EF0045Z9002AZJ-v1.0.10.zip (23MB) | RZ/G2 Group BSP Manual Set. |

Note) Detailed information regarding the configuration (Device tree) and usage of the device drivers contained in this BSP can be downloaded from Renesas.com. Please download the "RZ/G2 Group BSP Manual Set".

<https://www.renesas.com/document/rzg2-group-bsp-manual-set>

2. Patch Application Guide

This chapter describes how to prepare a clean environment of VLP64 v1.0.8 and update it to VLP64 v1.0.10. It is recommended to prepare and use a clean new environment, but if the environment prepared with VLP64 v1.0.8 is being used, it can also be updated with the section 2.1 or 2.2 below. In this case, it is highly recommended to backup whole environment before updating them. If HTML5 (Gecko) is not required, please refer to only the section 2.1. If HTML5 (Gecko) is required, please skip the section 2.1 and refer to only the section 2.2.

Copy all files obtained from Renesas into your home directory prior to the steps below.

2.1 Patch Application Guide

(1) Create a working directory (user_work) at your home directory and decompress Yocto recipe package of v1.0.8

Run the commands below. The name and the place of the working directory can be changed, as necessary. Please replace “eva” with “pro” for the product version.

```
$ mkdir ~/user_work
$ cd ~/user_work
$ tar zxvf ~/rzg2_bsp_eva_v108.tar.gz
```

Note) In case updating existing environment, please revert the patch which enables HDMI with below command if necessary. Please replace “directory” to the path to the directory which stores the patch file.

```
$ patch -R -p1 < directory/0001-BSPv1.0.8-Add-HDMI-support-for-RZ-G2.patch
```

(2) Apply the patch file to Yocto recipes and remove a directory and add a file

Run the commands below.

```
$ cd ~/user_work
$ tar zxvf ~/v108-to-v1010.patch.tar.gz
$ patch -p1 < v108-to-v1010.patch
```

(3) Decompress OSS files of v1.0.10 to “build” directory

Run the commands below. All OSS packages will be decompressed at once with this '7z' command. Please place all oss_pkg_v108.7z files in the same directory before running this '7z' command. 7zipped files are not able to decompress individually.

```
$ cd ~/user_work
$ mkdir build
$ cd build
$ 7z x ~/oss_pkg_v108.7z
$ mv oss_packages downloads (*)
```

(*) From VLP64 v1.0.9-RT, we do not use “oss_packages” for naming downloads directory anymore. We use default Yocto download directory called “downloads”.

(4) Add OSS files

Run the commands below to remove the old files.

```
$ cd ~/user_work/build/downloads
$ rm -rf git2/github.com.renesas-rz.rzg2_flash_writer.git \
git2/github.com.renesas-rz.renesas-u-boot-cip.git \
git2/github.com.OP-TEE.optee_os.git \
git2/github.com.renesas-rcar.optee_os.git* \
git2/github.com.OP-TEE.optee_client.git \
git2/github.com.renesas-rcar.arm-trusted-firmware.git* \
git2/git.trustedfirmware.org.TF-A.trusted-firmware-a.git* \
git2/github.com.ARM-software.arm-trusted-firmware.git* \
git2/github.com.renesas-rz.rzg_trusted-firmware-a.git
```

Run the commands below to add the new files. Copy the compressed OSS diff file to the home directory and decompress the new files.

```
$ cd ~/user_work/build
$ 7z x ~/v108-to-v1010.oss_packages.7z
```

(5) Build new BSP

Now it is ready to build the BSP. Please build it according to the Release Note section 3.1. Note that the below steps in the chapter 3 of the Release Note is not necessary. These steps overwrite your environment.

- (1) Create a working directory (user_work) at your home directory, and decompress Yocto recipe package
- (5) Decompress OSS files to “build” directory

2.2 Patch Application Guide for HTML5 (Gecko78)

(1) Create a working directory (user_work) at your home directory and decompress Yocto recipe package of v1.0.8

Run the commands below. The name and the place of the working directory can be changed, as necessary. Please replace “*eva*” with “*pro*” for the product version.

```
$ mkdir ~/user_work
$ cd ~/user_work
$ tar zxvf ~/rzg2_bsp_eva_v108.tar.gz
$ tar zxvf ~/rzg2_bsp_gecko78_v108.tar.gz (*)
```

Note: (*) If you want to support Gecko68 instead of Gecko78, please use “rzg2_bsp_gecko68_v108.tar.gz”.

Note) In case updating existing environment, please revert the patch which enables HDMI with below command if necessary. Please replace “*directory*” to the path to the directory which stores the patch file.

```
$ patch -R -p1 < directory/0001-BSPv1.0.8-Add-HDMI-support-for-RZ-G2.patch
```

(2) Apply patch files to Yocto recipes

Run the commands below.

```
$ cd ~/user_work
$ tar zxvf ~/v108-to-v1010.patch.tar.gz
$ tar zxvf ~/v108-to-v1010_gecko78.patch.tar.gz (*)
$ patch -p1 < v108-to-v1010.patch
$ patch -p1 < v108-to-v1010_gecko78.patch (*)
```

Note: (*) If you want to support Gecko68 instead of Gecko78, please skip these steps because the basic gecko68 packages are not changed from VLP64 v1.0.8.

(3) Decompress OSS files of v1.0.8 to “build” directory

Run the commands below. All OSS packages will be decompressed at once with this '7z' command. Please place all oss_pkg_v108.7z files and oss_pkg_gecko78_v108.7z files in the same directory before running this '7z' command. 7zipped files are not able to decompress individually.

```
$ cd ~/user_work
$ mkdir build
$ cd build
$ 7z x ~/oss_pkg_v108.7z
$ 7z x ~/oss_pkg_gecko78_v108.7z (*)
$ mv oss_packages downloads (**)
```

Note: (*) If you want to support Gecko68 instead of Gecko78, please use “oss_pkg_gecko68_v108.7z”.

(**) From VLP64 v1.0.9-RT, we do not use “oss_packages” for naming downloads directory anymore.

We use default Yocto download directory called “downloads”.

(4) Add OSS files

Run the commands below to remove the old files.

```
$ cd ~/user_work/build/downloads
$ rm -rf git2/github.com.renesas-rz.rzg2_flash_writer.git \
git2/github.com.renesas-rz.renesas-u-boot-cip.git \
git2/github.com.OP-TEE.optee_os.git \
git2/github.com.renesas-rcar.optee_os.git* \
git2/github.com.OP-TEE.optee_client.git \
git2/github.com.renesas-rcar.arm-trusted-firmware.git* \
git2/git.trustedfirmware.org.TF-A.trusted-firmware-a.git* \
git2/github.com.ARM-software.arm-trusted-firmware.git* \
git2/github.com.renesas-rz.rzg_trusted-firmware-a.git
```

Run the commands below to add the new files. Copy the compressed OSS diff files to the home directory and decompress the new files.

```
$ cd ~/user_work/build
$ 7z x ~/v108-to-v1010.oss_packages.7z
$ 7z x ~/v108-to-v1010_gecko78.oss_packages.7z (*)
```

Note: (*) If you want to support Gecko68 instead of Gecko78, please skip this step because the basic gecko68 packages are not changed from VLP64 v1.0.8.

(5) Build new BSP

Now it is ready to build the BSP. Please build it according to the Release Note section 3.1. Note that the below steps in the chapter 3 of the Release Note is not necessary. These steps overwrite your environment.

- (1) Create a working directory (user_work) at your home directory, and decompress Yocto recipe package
- (5) Decompress OSS files to “build” directory

Website and Support

Renesas Electronics Website

<http://www.renesas.com/>

Inquiries

<http://www.renesas.com/contact/>

All trademarks and registered trademarks are the property of their respective owners.