Date: Mar. 22, 2013

RENESAS TECHNICAL UPDATE

1753, Shimonumabe, Nakahara-ku, Kawasaki-shi, Kanagawa 211-8668 Japan Renesas Electronics Corporation

Product Category	MPU/MCU		Document No.	TN-RX*-A058A/E	N-RX*-A058A/E Rev.			
Title	Changes to Description of DC Characteristics for Analog Power Supply in the RX210 Group		Information Category	Technical Notification				
Applicable Product	RX210 Group	Lot No.	Reference Document	RX210 Group User's N Rev.1.30 (R01UH0037				

This document describes changes to description in Table 42.22 DC Characteristics (21) in RX210 Group User's Manual: Hardware Rev.1.30.

• Page 1496 of 1612

The analog power supply current and reference power supply current are listed by power supply as follows:

Before change

	Item	Symbol	Min.	Тур.	Max.	Unit	Test Conditions
Analog power	During A/D conversion	Al_CC	_	1.0	3.2	mA	
supply current	During D/A conversion (per channel)*1		_	0.25	0.75		
	Temperature sensor		_	60	200	μΑ	
	Waiting for A/D, D/A conversion (all units)		_	0.2	5.0		
Reference	During A/D conversion	I _{REFH} ,	_	0.1	0.2	mA	
power supply	Waiting for A/D, D/A conversion (all units)	I _{REFH0}	_	0.2	0.4	μΑ	
current							

Note: • The values for A/D conversion apply when the sample and hold circuit is not in use.

After change

	Item	Symbol	Min.	Тур.	Max.	Unit	Test Conditions
Analog power	During A/D conversion	I _{AVCC0}	_	1.0	3.2	mA	
supply current	Temperature sensor enabled while waiting for		_	60	200	μΑ	
	A/D conversion						
	During D/A conversion (per channel)	I _{REFH} *1	_	0.25	0.75	mA	
	Waiting for A/D, D/A conversion (all units) *2	_	_	0.2	5.0	μΑ	
Reference power supply current	During A/D conversion	I _{REFH0}	_	0.1	0.2	mA	
	Waiting for A/D conversion		_	0.2	0.4	μA	

Note: • The values for A/D conversion apply when the sample and hold circuit is not in use.

Note 1. The reference power supply current is included in the power supply current value for D/A conversion.

Note 2. The values are the sum of I_{AVCC0} and $I_{\text{REFH.}}$



Note 1. The reference power supply current is included in the power supply current value for D/A conversion.