

RAA278830D

Dual Channel Open-LDI Bridge for Automotive Displays Supporting up to ASIL-B Functional Safety

Description

The [RAA278830D](#) is a highly integrated LCD video processor that integrates many of the features necessary to design an ISO26262 ASIL-B Automotive display system. This includes two LVDS Open-LDI input interfaces, two separate video processing pipes, a versatile On-Screen Display (OSD) which includes both a Font based OSD and a bitmap SPI-OSD, a Q-SPI flash interface, as well as a dual channel LVDS Open-LDI output panel interface. The RAA278830D can support inputs with horizontal resolutions up to 2560 and a pixel clock up to 150MHz. The RAA278830D's video processing capability includes arbitrary H/V scaling, panoramic scaling, image mirroring, image adjustment and enhancement, 10-bit gamma and dither, and many more video processing features. In addition, the RAA278830D has new, improved image diagnostic capabilities to determine if the input video is frozen or corrupted.

The RAA278830D feature set, versatility, and ISO26262 ASIL-B functional safety design makes it an ideal solution for safety critical Automotive LCD display applications.

Features

- Video Input Support
 - Supports two channels Open-LDI inputs up to 150MHz in each channel
 - Supports VESA and JEIDA format
- TFT Panel Support
 - Supports two channels Open-LDI outputs up to 104MHz in each channel
 - Supports VESA and JEIDA format
 - Supports 3, 4, 6 or 8 bits per pixel up to 16.8 million colors with built-in dithering engine
- Font Based On Screen Display
 - Four window font OSD with bordering / shadow
 - 20KB programmable font RAM and 1024 display RAM
 - 1/2/3/4 bits/pixel
 - Supports variable width (12/16), height (2~32)
- SPI Flash Based On Screen Display
 - 9 bitmap based OSD windows in two layers through SPI Flash memory interface
 - Supports blending between layers and video
 - Supports 4/6/8 bits/pixel
 - Supports up to 142MHz SPI clock frequency
- SPI Flash Interface
 - Quad SPI flash interface for SPI-OSD and fast boot register programming
 - Fast boot register programming triggered by HW reset, register and SAFEIN pin transition
- Image Processing
 - High quality scaler with both up/down and panorama / water-glass scaling support
 - Programmable brightness, contrast, saturation, hue and sharpness
 - Supports programmable cropping of input video and graphics
 - Independent RGB gain and offset controls
 - Programmable 10-bit Gamma correction for each color
- Clock Generation
 - Spread spectrum PLL integrated to each scaler path
 - Programmable modulation frequency and spread width
- Functional Safety (FuSA)
 - Designed to support ISO26262 ASIL-B
 - Supports I²C/SPI host interface protection by CRC
 - Supports Two Input video measurement engines for Timing measurement, Input video loss detection, Phase, Luminance and RGB Min/Max measurement
 - Supports Frame CRC, and Frame Counter checking in embedded line data
 - Supports Video path CRC checker in every stage of video pipe
 - Supports up to 34 sub-window CRC checking for Telltale Icon checking
 - Supports Clock Monitor for all input, output and internal clocks
 - Supports LVDS-TX serializer checker by internal de-serializer
 - Supports LVDS-TX toggle check
 - Supports Register CRC checking
 - Supports Parity checker for OSD, Gamma memories

- Supports LBIST at power up
- Supports SAFEIN pin input for auto SM
- Supports 50 Block Measurement for Luminance, Phase
- Miscellaneous
 - Fast Mode Plus I²C host interface up to 1.2Mbps with optional CRC8 protection
 - SPI host interface up to 25MHz with optional CRC8 protection
 - Secondary host interface by pin sharing
 - I²C or SPI with full arbitration between hosts
 - Up to 2 x 10-bit PWMs
 - GPIOs
 - 1.2V internal operation
 - 1.8/3.3V I/O support
 - Single 27MHz crystal
 - 72-pin QFN with exposed thermal pad

Applications

- Automotive Display systems
- Digital Instrument Cluster display
- Heads Up Display systems

Notice

1. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation or any other use of the circuits, software, and information in the design of your product or system. Renesas Electronics disclaims any and all liability for any losses and damages incurred by you or third parties arising from the use of these circuits, software, or information.
 2. Renesas Electronics hereby expressly disclaims any warranties against and liability for infringement or any other claims involving patents, copyrights, or other intellectual property rights of third parties, by or arising from the use of Renesas Electronics products or technical information described in this document, including but not limited to, the product data, drawings, charts, programs, algorithms, and application examples.
 3. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
 4. You shall be responsible for determining what licenses are required from any third parties, and obtaining such licenses for the lawful import, export, manufacture, sales, utilization, distribution or other disposal of any products incorporating Renesas Electronics products, if required.
 5. You shall not alter, modify, copy, or reverse engineer any Renesas Electronics product, whether in whole or in part. Renesas Electronics disclaims any and all liability for any losses or damages incurred by you or third parties arising from such alteration, modification, copying or reverse engineering.
 6. Renesas Electronics products are classified according to the following two quality grades: "Standard" and "High Quality". The intended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below.
 - "Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; industrial robots; etc.
 - "High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control (traffic lights); large-scale communication equipment; key financial terminal systems; safety control equipment; etc.
- Unless expressly designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not intended or authorized for use in products or systems that may pose a direct threat to human life or bodily injury (artificial life support devices or systems; surgical implantations; etc.), or may cause serious property damage (space system; undersea repeaters; nuclear power control systems; aircraft control systems; key plant systems; military equipment; etc.). Renesas Electronics disclaims any and all liability for any damages or losses incurred by you or any third parties arising from the use of any Renesas Electronics product that is inconsistent with any Renesas Electronics data sheet, user's manual or other Renesas Electronics document.
7. No semiconductor product is absolutely secure. Notwithstanding any security measures or features that may be implemented in Renesas Electronics hardware or software products, Renesas Electronics shall have absolutely no liability arising out of any vulnerability or security breach, including but not limited to any unauthorized access to or use of a Renesas Electronics product or a system that uses a Renesas Electronics product. RENESAS ELECTRONICS DOES NOT WARRANT OR GUARANTEE THAT RENESAS ELECTRONICS PRODUCTS, OR ANY SYSTEMS CREATED USING RENESAS ELECTRONICS PRODUCTS WILL BE INVULNERABLE OR FREE FROM CORRUPTION, ATTACK, VIRUSES, INTERFERENCE, HACKING, DATA LOSS OR THEFT, OR OTHER SECURITY INTRUSION ("Vulnerability Issues"). RENESAS ELECTRONICS DISCLAIMS ANY AND ALL RESPONSIBILITY OR LIABILITY ARISING FROM OR RELATED TO ANY VULNERABILITY ISSUES. FURTHERMORE, TO THE EXTENT PERMITTED BY APPLICABLE LAW, RENESAS ELECTRONICS DISCLAIMS ANY AND ALL WARRANTIES, EXPRESS OR IMPLIED, WITH RESPECT TO THIS DOCUMENT AND ANY RELATED OR ACCOMPANYING SOFTWARE OR HARDWARE, INCLUDING BUT NOT LIMITED TO THE IMPLIED WARRANTIES OF MERCHANTABILITY, OR FITNESS FOR A PARTICULAR PURPOSE.
 8. When using Renesas Electronics products, refer to the latest product information (data sheets, user's manuals, application notes, "General Notes for Handling and Using Semiconductor Devices" in the reliability handbook, etc.), and ensure that usage conditions are within the ranges specified by Renesas Electronics with respect to maximum ratings, operating power supply voltage range, heat dissipation characteristics, installation, etc. Renesas Electronics disclaims any and all liability for any malfunctions, failure or accident arising out of the use of Renesas Electronics products outside of such specified ranges.
 9. Although Renesas Electronics endeavors to improve the quality and reliability of Renesas Electronics products, semiconductor products have specific characteristics, such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Unless designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not subject to radiation resistance design. You are responsible for implementing safety measures to guard against the possibility of bodily injury, injury or damage caused by fire, and/or danger to the public in the event of a failure or malfunction of Renesas Electronics products, such as safety design for hardware and software, including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult and impractical, you are responsible for evaluating the safety of the final products or systems manufactured by you.
 10. Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. You are responsible for carefully and sufficiently investigating applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive, and using Renesas Electronics products in compliance with all these applicable laws and regulations. Renesas Electronics disclaims any and all liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
 11. Renesas Electronics products and technologies shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations. You shall comply with any applicable export control laws and regulations promulgated and administered by the governments of any countries asserting jurisdiction over the parties or transactions.
 12. It is the responsibility of the buyer or distributor of Renesas Electronics products, or any other party who distributes, disposes of, or otherwise sells or transfers the product to a third party, to notify such third party in advance of the contents and conditions set forth in this document.
 13. This document shall not be reprinted, reproduced or duplicated in any form, in whole or in part, without prior written consent of Renesas Electronics.
 14. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products.

(Note1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its directly or indirectly controlled subsidiaries.

(Note2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.

(Disclaimer Rev.5.0-1)

Corporate Headquarters

TOYOSU FORESIA, 3-2-24 Toyosu,
Koto-ku, Tokyo 135-0061, Japan
www.renesas.com

Trademarks

Renesas and the Renesas logo are trademarks of Renesas Electronics Corporation. All trademarks and registered trademarks are the property of their respective owners.

Contact Information

For further information on a product, technology, the most up-to-date version of a document, or your nearest sales office, please visit:
www.renesas.com/contact/