

APPLICATION NOTE

R01AN0588EJ0101

Rev. 1.01 Mar. 2, 2012

SH7455 Group, SH7456 Group

Data Communication Using the DRO and DRI

Abstract

This document describes sample code for performing data communication using the direct RAM output interface (DRO) and direct RAM input interface (DRI) in the SH7455 Group and SH7456 Group (hereinafter referred to collectively as the SH7455).

Products

SH7455 Group, SH7456 Group

When using this application note with other Renesas MCUs, careful evaluation is recommended after making modifications to comply with the alternate MCU. In addition, although the sample code presented in this application note has been confirmed to operate as intended, refer to the latest version of the hardware manual and perform a thorough evaluation before using.



Contents

1.	Specific	ations	. 3
2.	Confirm	ed Operation Conditions	. 5
3.	Referen	ce Application Note	. 5
4.	Hardwa	re	. 5
4	.1 Pin	s Use	. 5
5.	Software	9	. 6
5	.1 Ope 5.1.1	eration Overview Overview of DRO and DRI Settings	
	5.1.2	Loop-Back Communication	. 7
5	5.1.3 .2 File	Data Communication between Evaluation Boards	
		istants	
-		ucture/Union List	
		iables	
-		ictions	
-		wcharts	
	5.8.1	main Processing	
	5.8.2	ParameterInitExec Processing	
	5.8.3 5.8.4	ToggleSWRead Processing	
	5.8.5	OutputEnableCtrl Processing	
	5.8.6	InputInitCtrl Processing	
	5.8.7	InputEnableCtrl Processing	
	5.8.8	ProcessingStatusCtrl Processing	
	5.8.9	DroInit Processing	
	5.8.10 5.8.11	DroStart Processing	
	5.8.12	Drilnit Processing	
	5.8.13	DriStart Processing	
	5.8.14	DriInputStatus Processing	27
6.	Referen	ce Documents	28



1. Specifications

The sample code uses the DRI to capture data output by the DRO. It can be used to perform loop-back communication on a single SH7455 evaluation board or data communication between two evaluation boards. DRO and DRI initialization, DRO data output, and DRI data capture are controlled by toggle switches mounted on the evaluation board. Table 1.1 lists the peripheral functions and their applications, table 1.2 lists control details for the toggle switches, and figures 1.1 and 1.2 show usage examples. For details on the functions of the pins shown in the figures, see table 4.1.

Table 1.1 Peripheral Functions and Their Applications

Table 1.2 Toggle Switch Control Details

Peripheral Function	Application
DRO (direct RAM output interface)	Outputs data from the SH7455 on-chip SHwyRAM.
DRI (direct RAM input interface)	Captures parallel data to the SH7455 on-chip SHwyRAM.

Toggle Switch	Input	Control Details
S7 "H" DRI initialization enable		DRI initialization enable
	"L"	DRI initialization disable
S6	"H"	DRO initialization enable
	"L"	DRO initialization disable
S5	"H"	DRI data capture enable
	"L"	DRI data capture disable
S4	"H"	DRO data output enable
	"L"	DRO data output disable



Figure 1.1 Usage Example: Loop-Back Communication



SH7455 Group, SH7456 Group

Data Communication Using the DRO and DRI



Figure 1.2 Usage Example: Data Communication between Evaluation Boards



2. Confirmed Operating Conditions

The sample code accompanying this application note has been run and confirmed under the conditions below.

Item	Contents
MCU	SH7455 Group, SH7456 Group
Operating frequencies	Input clock: 20 MHz
	CPU clock (lck): 160 MHz
	SHwy clock (SHck): 80 MHz
	Peripheral clock (Pck): 40 MHz
	Peripheral A clock (PAck): 80 MHz
Operating voltage	Vcc = PLLVcc = AVcc = 5 V, Vdd = 1.5 V
Operating mode	Single-chip mode
Integrated development	Renesas Electronics
environment	High-performance Embedded Workshop Version 4.09.00.007 (HEW)
C/C++ compiler	Renesas Electronics
	C/C++ compiler package for SuperH RISC engine family V.9.04 Release 00
	Options: The following options are the HEW default settings.
	-cpu=sh4a -object="\$(CONFIGDIR)\\$(FILELEAF).obj" -debug -gbr=auto
	-chgincpath -errorpath -global_volatile=0 -opt_range=all -infinite_loop=0
	-del_vacant_loop=0 -struct_alloc=1 -nologo
Sample code version	Version 1.00
Evaluation board used	SH7455 evaluation board
	(product No.: R0K474552C000BR/R0K474552C010BR)

3. Reference Application Note

For additional information associated with this document, refer to the following application note.

SH7455 Group/SH7456 Group Register Definition Header File (R01AN0355EJ0101)

4. Hardware

4.1 Pins Used

Table 4.1 lists the pins used and their functions.

Table 4.1 Pins Used and Their Functions

Pin Name	I/O	Description
PH7/DDC07 to PH0/DDC00	Input	DRI input data
PK5/DINC4	Input	DRI input event signal
PH15/DROD7 to PH8/DROD0	Output	DRO output data bus
PL2/DROWR	Output	DRO output data strobe
PA7 to PA4	Input	Level input for toggle switches S7 to S4



5. Software

5.1 Operation Overview

The sample code uses the DRI to capture 256 bytes of user-defined data (in the sample code, byte data with values from H'00 to H'FF) output by the DRO. Toggle switches S7 to S4 on the evaluation board are used to perform loop-back communication on a single evaluation board or data communication between two evaluation boards. Toggle switch S7 controls DRI initialization, toggle switch S6 controls DRO initialization, toggle switch S5 controls DRI data capture, and toggle switch S4 controls DRO data output. The description below provides an overview of the DRO and DRI settings used in the sample code and explains loop-back communication and data communication between evaluation boards.

Note: The sample code contains sections that perform an infinite loop. In actual use, processing should be added as needed to specify a duration limit for each infinite loop and to exit the loop afterward.

5.1.1 Overview of DRO and DRI Settings

Tables 5.1 and 5.2 provide an overview of the DRO and DRI settings used in the sample code.

Item	Description
Transfer format	Parallel output with strobe
Access area	SHwyRAM: Output of data in the area from H'1800 1000 to H'1800 10FF
Output data width	8 bits
Transfer rate	10Mbytes/s
Strobe polarity	"H" active
Timing adjustment	2 Pck selected for setup and hold
Interrupt request	Interrupt request mask (disabled)

Table 5.1 Overview of DRO Settings

ltem	Description
Channel	DRI channel 2 (DRI2)
Input to DRI2	Pins DINC4 and DDC07 to DDC00
Operating frequency	80 MHz (PAck = 80 MHz)
Transfer format	Clock-synchronous parallel input
Access area	SHwyRAM: Capture data in the area from H'1800 0000 to H'1800 00FF
Data capture bus width	8 bits
Event counter	Not used
Bank switching function	DRI2 address counter 0 selected
Data capture event	DIN4 event detection
Data capture edge	Falling edge
Capture timing adjustment	Default (PAck rising edge at event detection)
function	
Decimation control function	Not used
Special modes	Not used

Table 5.2 Overview of DRI Settings



SH7455 Group, SH7456 Group

5.1.2 Loop-Back Communication

Using a single evaluation board, 256 bytes of user-defined data are output by the DRO and captured by the DRI. A description of the loop-back communication operating procedure and an overview of the operations performed are provided below. Figure 5.1 shows a timing chart.

To begin, set the input level of toggle switches S7 to S4 to "L" and then power on the evaluation board. After power-on, sequentially change the input level of toggle switches S7, S6, S5, and S4 to "H", in that order. The sample code operations that occur when these steps are performed are as follows.

(1) DRI Initialization

When toggle switch S7 is moved to the "H" level, the following processes are performed once:

- Enabling of clock supply to the DRI
- Initialization of ports and control block used by the DRI
- (2) DRO Initialization

When toggle switch S6 is moved to the "H" level, the following processes are performed once:

- Enabling of clock supply to DRO
- Initialization of ports and output control block used by the DRO

DROWR is selected as the port pin function, and the DRO strobe polarity select bit is set to "H" active. With these settings, DROWR outputs a "L" level signal when data has not been output.

(3) DRI Data Capture Enable

When toggle switch S5 is moved to the "H" level, DRI data capture is enabled. The DRI event detection method is set to the falling edge of an external signal input to the DRI (DINC4).

(4) DRO Data Output Enable

When toggle switch S4 is moved to the "H" level, DRO data output is enabled.

(5) DRO Data Output/DRI Data Capture (Continuous Operation Controlled by Hardware)

After items (1) to (4) above are processed, data output and capture take place repeatedly for 256 bytes. In synchronization with the rising edge of DROWR, the DRO outputs 256 bytes of SHwyRAM data from pins DROD7 to DROD0, 1 byte at a time. DRO operation ends after data output is completed. When the DRI detects the falling edge of DINC4, it captures 1 byte of data from pins DDC07 to DDC00 to the SHwyRAM, and this is repeated for 256 bytes. DRI operation ends after data capture is completed.





Figure 5.1 Timing Diagram of Loop-Back Communication



Data Communication Using the DRO and DRI

5.1.3 Data Communication between Evaluation Boards

When two evaluation boards are used, 256 bytes of user-defined data are output by the DRO-side evaluation board and captured by the DRI-side evaluation board. A description of the switch operating procedure for data communication between evaluation boards and an overview of the operations performed are provided below. Figure 5.2 shows a timing chart.

[DRO-Side Evaluation Board]

Set the input level of toggle switches S7 to S4 to "L" and then power on the evaluation board. After power-on, sequentially change the input level of toggle switches S6 and S4 to "H", in that order. Before changing the input level of toggle switch S4 to "H", make sure toggle switch S5 on the DRI-side evaluation board is set to "H" level. The sample code operations that occur when these steps are performed are described below.

(O-1) DRO Initialization

When toggle switch S6 is moved to the "H" level, the following processes are performed once:

- Enabling of clock supply to DRO
- Initialization of ports and output control block used by the DRO

DROWR is selected as the port pin function, and the DRO strobe polarity select bit is set to "H" active. With these settings, DROWR outputs a "L" level signal when data has not been output.

(O-2) DRO Data Output Enable Standby

The DRO data output disabled state is maintained while toggle switch S4 is set to "L" level.

(O-3) DRO Data Output Enable

When toggle switch S4 is moved to the "H" level, DRO data output is enabled.

(O-4) DRO Data Output (Continuous Operation Controlled by Hardware)

After items (O-1) to (O-3) above are processed, the DRO outputs 256 bytes of SHwyRAM data, 1 byte at a time, from pins DROD7 to DROD0 in synchronization with the rising edge of DROWR. DRO operation ends after data output is completed.

[DRI-Side Evaluation Board]

Set the input level of toggle switches S7 to S4 to "L" and then power on the evaluation board. After power-on, sequentially change the input level of toggle switches S7 and S5 to "H", in that order. Before changing the input level of toggle switch S5 to "H", make sure toggle switch S6 on the DRO-side evaluation board is set to "H" level. The sample code operations that occur when these steps are performed are described below.

(I-1) DRI Initialization

When toggle switch S7 is moved to the "H" level, the following processes are performed once:

- Enabling of clock supply to DRI
- Initialization of ports and output control block used by the DRI

(I-2) DRI Data Capture Enable Standby

The DRI data capture disabled state is maintained while toggle switch S5 is set to "L" level.

(I-3) DRI Data Capture Enable

When toggle switch S5 is moved to the "H" level, DRI data capture is enabled. The DRI event detection method is set to the falling edge of an external signal input to the DRI (DINC4).

(I-4) DRI Data Capture (Continuous Operation Controlled by Hardware)

After items (I-1) to (I-3) above are processed, the DRI detects the falling edge of DINC4, it captures 1 byte of data from pins DDC07 to DDC00 to the SHwyRAM, and this is repeated for 256 bytes. DRI operation ends after data capture is completed.



SH7455 Group, SH7456 Group

Data Communication Using the DRO and DRI



Figure 5.2 Timing Chart of Data Communication between Evaluation Boards



5.2 File Composition

Table 5.3 lists the files used in the sample code. Files not generated by the integrated development environment should not be listed in this table.

Table 5.3 Files Used in the Sample Code

File Name	Outline	Remarks
dri.c	DRI control program	
dri.h	DRI include headers for external referencing	
dro.c	DRO control program	
dro.h	DRO include headers for external referencing	
main.c	Main function program	
sh7455_iodefine_20101029.h	SH7455 Group/SH7456 Group register definition header file	

5.3 Constants

Table 5.4 lists the constants used in the sample code.

Table 5.4 Constants Used in the Sample Code

Constant Name	Setting Value	Contents
DRI_EVENT_NO_INPUT	H'0	No input
DRI_EVENT_RISING_EDGE	H'1	Rising edge detection
DRI_EVENT_FALLING_EDGE	H'2	Falling edge detection
DRI_EVENT_BOTH_EDGE	H'3	Both edges detection
DRI_EVENT_DETECTION	DRI_EVENT_FALLING_EDGE	DRI event detection method
DRI_ACQUISITION_TIMING	H'0	Duration (PAck) from data capture
		event detection to data capture
DRI_DST_ADDR	H'1800 0000	SHwyRAM address for storing data
		captured by DRI
DRI_INPUT_INCOMPLETION	H'0	DRI data capture incomplete
DRI_INPUT_COMPLETION	H'1	DRI data capture complete
DRO_DRI_NUM_OF_DATA	H'100	DRO/DRI data transfer count
DRO_L_ACTIVE	H'0	"L" active
DRO_H_ACTIVE	H'1	"H" active
DRO_STROBE_POL	DRO_H_ACTIVE	DRO strobe polarity
DRO_SETUP_TIME	H'2	Output data setup time (Pck)
DRO_HOLD_TIME	H'2	Output data hold time (Pck)
DRO_SRC_ADDR	H'1800 1000	SHwyRAM address for storing DRO
		output data
DRO_OUTPUT_INCOMPLETION	H'0	DRO data output incomplete
DRO_OUTPUT_COMPLETION	H'1	DRO data output complete
EXEC_PROHIBITION	H'0	Execution disabled
EXEC_COMPLETION	H'1	Execution complete
PROCESSING_INCOMPLETION	H'0	Processing incomplete
PROCESSING_COMPLETION	H'1	Processing complete
TOGGLE_SWITCH_S7	PORT.PADR.BIT.PA7DR*1	PA 7 (toggle switch S7) input
TOGGLE_SWITCH_S6	PORT.PADR.BIT.PA6DR*1	PA 6 (toggle switch S6) input
TOGGLE_SWITCH_S5	PORT.PADR.BIT.PA5DR*1	PA 5 (toggle switch S5) input
TOGGLE_SWITCH_S4	PORT.PADR.BIT.PA4DR* ¹	PA 4 (toggle switch S4) input

Note: *1 Pointer to port A data register (PADR) (address: H'FFFF 5002).

(See the SH7455 Group/SH7456 Group peripheral function register definition file.)



5.4 Structure/Union List

Figure 5.3 shows the structures and unions used in the sample code.

```
typedef struct{
                                          /* Structure for storing DRO initialization parameters */
    unsigned short usStrPol;
                                          /* Strobe polarity */
                                          /* Setup time */
    unsigned short usSetupTime;
    unsigned short usHoldTime;
                                          /* Hold time */
    unsigned long ulSrcAddr;
                                          /* Transfer source SHwyRAM address */
    unsigned long ulNumOfData;
                                          /* Output data count */
}DROINIT;
typedef struct{
                                          /* Structure for storing DRI initialization parameters */
                                          /* Event detection method */
    unsigned short usEvtDet;
                                          /* Capture timing */
    unsigned short usDataAcqTime;
    unsigned long ulDstAddr;
                                          /* Transfer destination SHwyRAM address */
    unsigned long ulNumOfData;
                                          /* Capture event count */
}DRIINIT;
```

Figure 5.3 Structures/Unions Used in Sample Code



5.5 Variables

Table 5.5 lists the global variables.

Table 5.5 Global Variables

Туре	Variable Name	Contents	Function Used
unsigned char	gucDroInitFlag	DRO initialization flag 0: Execution disabled 1: Execution complete	OutputInitCtrl
unsigned char	gucDroOutputStartFlag	DRO data output start flag 0: Execution disabled 1: Execution complete	OutputEnableCtrl, ProcessingStatus
unsigned char	gucDriInitFlag	DRI initialization flag 0: Execution disabled 1: Execution complete	InputInitCtrl
unsigned char	gucDriInputStartFlag	DRI data capture start flag 0: Execution disabled 1: Execution complete	InputEnableCtrl, ProcessingStatus
unsigned char	gucProcessingFlag	Processing status flag 0: Processing incomplete 1: Processing complete	main, ProcessingStatus
DROINIT	gstDroInitVal	DRO initialization parameter structure	ParameterInitExec, OutputInitCtrl
DRIINIT	gstDriInitVal	DRI initialization parameter structure	ParameterInitExec, InputInitCtrl
unsigned short	gusToggleSW7Lv	Toggle switch 7 state 0: "L" level 1: "H" level	ToggleSWRead, InputInitCtrl
unsigned short	gusToggleSW6Lv	Toggle switch 6 state 0: "L" level 1: "H" level	ToggleSWRead, OutputInitCtrl
unsigned short	gusToggleSW5Lv	Toggle switch 5 state 0: "L" level 1: "H" level	ToggleSWRead, InputEnableCtrl
unsigned short	gusToggleSW4Lv	Toggle switch 4 state 0: "L" level 1: "H" level	ToggleSWRead, OutputEnableCtrl



5.6 Functions

Table 5.6 lists the functions.

Table 5.6 Functions

Function Name	Outline
ParameterInitExec	Make initial settings.
ToggleSWRead	Read toggle switch states.
OutputInitCtrl	Control data output initialization.
OutputEnableCtrl	Control data output processing start.
InputInitCtrl	Control initialization of data input processing.
InputEnableCtrl	Control data input processing start.
ProcessingStatus	Get processing status.
DroInit	Initialize DRO.
DroStart	Start DRO data output.
DroOutputStatus	Get DRO data output status.
Drilnit	Initialize DRI.
DriStart	Start DRI data capture.
DriInputStatus	Get DRI data capture status.

5.7 Function Specifications

The following tables list the sample code function specifications.

ParameterInitExec

Outline	Make initial settings.
Headers	dro.h, dri.h, sh7455_iodefine_20101029.h, typedefine.h
Declaration	void ParameterInitExec(void)
Description	This function initializes the ports used by toggle switches S7 to S4, initializes the global variables, creates the output data, and the SHwyRAM area to which data will be captured is cleared to 0.
Arguments	None
Returned value	None
Remarks	

ToggleSWRead	
Outline	Read toggle switch states.
Header	sh7455_iodefine_20101029.h
Declaration	void ToggleSWRead(void)
Description	This function reads the input levels of toggle switches S7 to S4 from the input ports and updates the variables indicating the states of toggle switches S7 to S4.
Arguments	None
Returned value	None
Remarks	



OutputInitCtrl	
Outline	Control data output initialization.
Header	dro.h
Declaration	void OutputInitCtrl(void)
Description	• This function controls execution of function DroInit according to the value of the DRO initialization flag and the state of toggle switch S6.
	 After execution of function DroInit completes, this function sets the DRO initialization flag to "execution complete".
Arguments	None
Returned value	None
Remarks	

OutputEnableCtrl	
Outline	Control data output processing start.
Header	dro.h
Declaration	void OutputEnableCtrl(void)
Description	 This function controls execution of function DroStart according to the value of the DRO initialization flag, the DRO data output start flag, and the state of toggle switch S4. After execution of function DroStart completes, this function sets the DRO data output start flag to "execution complete".
Arguments	None
Returned value Remarks	None

InputInitCtrl	
Outline	Control data input processing initialization.
Header	dri.h
Declaration	void InputInitCtrl(void)
Description	 This function controls execution of function Drilnit according to the value of the DRI initialization flag and the state of toggle switch S7. After execution of function Drilnit completes, this function sets the DRI initialization flag to "execution complete".
Arguments	None
Returned value Remarks	None

InputEnableCtrl	
Outline	Control data input processing start.
Header	dri.h
Declaration	void InputEnableCtrl(void)
Description	 This function controls execution of function DriStart according to the value of the DRI initialization flag, the DRI data capture start flag, and the state of toggle switch S5. After execution of function DriStart completes, this function sets the DRI data capture start flag to "execution complete".
Arguments	None
Returned value Remarks	None



ProcessingStatus	
Outline	Get processing status.
Headers	dro.h, dri.h, typedefine.h
Declaration	void ProcessingStatus (void)
Description	 This function executes functions DroOutputStatus and DriInputStatus.
	 When processing completes, this function sets the processing status flag to "processing complete".
Arguments	None
Returned value	None
Remarks	
DroInit	
Outline	Initialize DRO.
Headers	dro.h, sh7455_iodefine_20101029.h, typedefine.h
Declaration	void DroInit(DROINIT* stDroInitVal)
Description	 This function starts supply of the clock to the DRO.
	• This function initializes the ports used by the DRO and the DRO output control block.
Arguments	1st argument: stDroInitVal: Pointer to the structure for storing the DRO initialization parameters
Returned value	None
Remarks	• In order to set the DRO address counter register (DROADRCT), this function clears
	bits 31 to 19, 1, and 0, to 0, in ulDstAddr, a member of structure stDroInitVal.
	 ulSrcAddr, a member of structure stDroInitVal, should be set to a multiple of 32.
DroStart	
Outline	Start DRO data output.
Headers	dro.h, sh7455_iodefine_20101029.h
Declaration	void DroStart (void)
Description	Enables DRO output.
Arguments	None
Returned value	None
Remarks	
DroOutputStatus	
Outline	Get DRO data output status.
Headers	dro.h, sh7455_iodefine_20101029.h, typedefine.h
Declaration	int DroOutputStatus(void)
Description	• When data output equal to the transfer count is completed, this function returns a value of DRO_OUTPUT_COMPLETION (1).
	 When data output is incomplete, this function returns a value of DRO_OUTPUT_INCOMPLETION (0).
Arguments	None
Returned value	Data output complete: DRO_OUTPUT_COMPLETION (1)
	Data output incomplete: DRO_OUTPUT_INCOMPLETION (0)
Remarks	/



Drilnit	
Outline	Initialize DRI.
Headers	dri.h, sh7455_iodefine_20101029.h, typedefine.h
Declaration	void Drilnit(DRIINIT* stDrilnitVal)
Description	This function starts supply of the clock to the DRI.
-	• This function initializes the ports used by the DRI and the DRI control block.
Arguments	1st argument: stDriInitVal: Pointer to the structure for storing the DRI initialization
•	parameters
Returned value	None
Remarks	• In order to set the DRI2 address counter 0 (DRI2ADR0CT) register, this function
	clears to 0 bits 31 to 19, 1, and 0 in ulDstAddr, a member of structure stDrilnitVal.
	• ulNumOfData, a member of structure stDriInitVal, should be set to a multiple of 32.
DriStart	
Outline	Start DRI data capture
Headers	dri.h, sh7455_iodefine_20101029.h, typedefine.h
Declaration	void DriStart(DRIINIT* stDriInitVal);
Description	Selects the event detection method for external signals input to the DRI.
Arguments	1st argument: stDriInitVal: Pointer to the structure for storing the DRI initialization
	parameters
Returned value	None
Remarks	
DriInputStatus	
Outline	Get DRI data capture status
Headers	dri.h, sh7455_iodefine_20101029.h, typedefine.h
Declaration	int DriInputStatus (void)
Description	 When data capture equal to the event count is completed, this function returns a value of DRI_INPUT_COMPLETION (1).
	 When data capture is incomplete, this function returns a value of DRI_INPUT_INCOMPLETION (0).
Arguments	None
Returned value	Data capture complete: DRI_INPUT_COMPLETION (1)
	 Data capture incomplete: DRI_INPUT_INCOMPLETION (0)

Remarks



5.8 Flowcharts

5.8.1 main Processing



Figure 5.4 main Processing



5.8.2 ParameterInitExec Processing



Figure 5.5 ParameterInitExec Processing

5.8.3 ToggleSWRead Processing



Figure 5.6 ToggleSWRead Processing

5.8.4 OutputInitCtrl Processing





5.8.5 OutputEnableCtrl Processing







5.8.6 InputInitCtrl Processing



Figure 5.9 InputInitCtrl Processing

5.8.7 InputEnableCtrl Processing







5.8.8 ProcessingStatus Processing



Figure 5.11 ProcessingStatus Processing



5.8.9 DroInit Processing



Figure 5.12 DroInit Processing



5.8.10 DroStart Processing



Figure 5.13 DroStart Processing

5.8.11 DroOutputStatus Processing



Figure 5.14 DroOutputStatus Processing



5.8.12 Drilnit Processing







SH7455 Group, SH7456 Group

Data Communication Using the DRO and DRI

А DRI2DDEN register ← H'0000 00FF Enable data input to DRI DD7EN bit to DD0EN bit = 1 : Enable DD07 to DD00 input. DRI2TRMCNT register ← H'09 Make DRI transfer : Select DRI2 address counter 0. ADSL bit = 00b control settings ADMD bit = 1 : Reload mode : Enable operation. DRST bit = 1 DRI2DCAPNUM ← H'100 Set data capture event count DCAPNUM bit = H'100 : Set data capture event count to 256. Check for underflow of Read DRI2TRMCT register. : 0: Underflow DRI transfer counter DRI2ADR0CT register*¹ ← H'0000 0000 Set DRI address counter DRIAD0 bit = 0: Transfer destination SHwyRAM address to H'1800 0000. DRI2ADR0RLD register - H'0000 0000 Set DRI address counter DRIADORLD bit = 0 : Set DRI2ADR0CT register reload value to 0. reload value DRI2DECiRLD register (i = 0 to 5) ← H'0000*² Set event counter reload value Set value after reset (initial value). DRI2DECiCNT register (i = 0 to 5) \leftarrow H'00*² Set event counter Set value after reset (initial value). DRI2DSELCNT register \leftarrow H'00*² Make data decimation Set value after reset (initial value). control setting DRI2DEVTCNT register \leftarrow H'00*^2 Set value after reset (initial value). Select data decimation event Read DRI2TRMCT register. : 0: Underflow Check for underflow of DRI transfer counter DRI2DCAPCNT register ← H'0201 Make data capture DTMSL bit = 0000b : Select default as data capture timing. control settings : Enable writing to DCPEN bit/DEXSL bit. DWRPR bit = 0 DCPSL bit = 10b : Select DIN4 event detection as capture event. DWDSL bit = 00b Select 8 bits as input data bus width. DDSSL bit = 00b Select "prohibited source not selected" as event for clearing DEXSL bit to 0. DEXSL bit = 000b : Select "external source not selected" as event for setting DCPEN bit to 1. DCPEN bit*1 = 1 : Enable data capture. return Notes: *1 Always perform this step when the DRI2TRMCT register is in the underflow (H'0000 0000: counter stopped) state. *2 When using the decimation control function, set an appropriate value.





5.8.13 DriStart Processing



Figure 5.17 DriStart Processing

5.8.14 DriInputStatus Processing



Figure 5.18 DrilnputStatus Processing



6. Reference Documents

SH7455 Group, SH7456 Group User's Manual: Hardware, Rev.1.10 (R01UH0030EJ0110) The latest version can be downloaded from the Renesas Electronics website.

Website and Support

Renesas Electronics Website <u>http://www.renesas.com/</u>

Inquiries

http://www.renesas.com/inquiry



Revision History

SH7455 Group, SH7456 Group Data Communication Using the DRO and DRI

Rev.	Date	Descrip	tion
ILEV.	Date	Page	Summary
1.00	Nov. 2,2011	—	First edition issued
1.01	Mar. 2, 2012		Template is changed

All trademarks and registered trademarks are the property of their respective owners.

General Precautions in the Handling of MPU/MCU Products

The following usage notes are applicable to all MPU/MCU products from Renesas. For detailed usage notes on the products covered by this manual, refer to the relevant sections of the manual. If the descriptions under General Precautions in the Handling of MPU/MCU Products and in the body of the manual differ from each other, the description in the body of the manual takes precedence.

- 1. Handling of Unused Pins
 - Handle unused pins in accord with the directions given under Handling of Unused Pins in the manual.
 - The input pins of CMOS products are generally in the high-impedance state. In operation with an unused pin in the open-circuit state, extra electromagnetic noise is induced in the vicinity of LSI, an associated shoot-through current flows internally, and malfunctions occur due to the false recognition of the pin state as an input signal become possible. Unused pins should be handled as described under Handling of Unused Pins in the manual.
- 2. Processing at Power-on

The state of the product is undefined at the moment when power is supplied.

— The states of internal circuits in the LSI are indeterminate and the states of register settings and pins are undefined at the moment when power is supplied.

In a finished product where the reset signal is applied to the external reset pin, the states of pins are not guaranteed from the moment when power is supplied until the reset process is completed. In a similar way, the states of pins in a product that is reset by an on-chip power-on reset function are not guaranteed from the moment when power is supplied until the power reaches the level at which resetting has been specified.

- 3. Prohibition of Access to Reserved Addresses
 - Access to reserved addresses is prohibited.
 - The reserved addresses are provided for the possible future expansion of functions. Do not access
 these addresses; the correct operation of LSI is not guaranteed if they are accessed.
- 4. Clock Signals

After applying a reset, only release the reset line after the operating clock signal has become stable. When switching the clock signal during program execution, wait until the target clock signal has stabilized.

- When the clock signal is generated with an external resonator (or from an external oscillator) during a reset, ensure that the reset line is only released after full stabilization of the clock signal. Moreover, when switching to a clock signal produced with an external resonator (or by an external oscillator) while program execution is in progress, wait until the target clock signal is stable.
- Differences between Products Before changing from one product to another, i.e. to one with a different type number, confirm that the change will not lead to problems.
 - The characteristics of MPU/MCU in the same group but having different type numbers may differ because of the differences in internal memory capacity and layout pattern. When changing to products of different type numbers, implement a system-evaluation test for each of the products.

	Notice
1.	All information included in this document is current as of the date this document is issued. Such information, however, is subject to change without any prior notice. Before purchasing or using any Renesas
	Electronics products listed herein, please confirm the latest product information with a Renesas Electronics sales office. Also, please pay regular and careful attention to additional and different information the sale of
	be disclosed by Renesas Electronics such as that disclosed through our website. Renesas Electronics does not assume any liability for infringement of patents, copyrights, or other intellectual property rights of third parties by or arising from the use of Renesas Electronics products or
	technical information described in this document. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or
	others.
	You should not alter, modify, copy, or otherwise misappropriate any Renesas Electronics product, whether in whole or in part. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible fo
	rescriptions of actuals, software and other teaces minimized in its design of your equipment. Renease Electronics assumes no responsibility for any losses and application features of the incorporations of these circuits, software, and information in the design of your equipment. Renease Electronics assumes no responsibility for any losses included by our or third parties and singling from the
	use of these circuits, software, or information.
5.	When exporting the products or technology described in this document, you should comply with the applicable export control laws and regulations and follow the procedures required by such laws and
	regulations. You should not use Renesas Electronics products or the technology described in this document for any purpose relating to military applications or use by the military, including but not limited to
	the development of weapons of mass destruction. Renesas Electronics products and technology may not be used for or incorporated into any products or systems whose manufacture, use, or sale is
	prohibited under any applicable domestic or foreign laws or regulations.
	Renesas Electronics has used reasonable care in preparing the information included in this document, but Renesas Electronics does not warrant that such information is error free. Renesas Electronics assumes no liability whatsoever for any damages incurred by you resulting from errors in or omissions from the information included herein.
	assumes no nativity whatsoever for any damages incurred by you resulting non-errors in or oninssions non-me information included nerein. Renesas Electronics products are classified according to the following three quality grades: "Standard", "High Quality", and "Specific". The recommended applications for each Renesas Electronics produc
	depends on the product's quality grade, as indicated below. You must check the quality grade of each Renessa Electronics product before using it in a particular application. You may not use any Renessa
	Electronics product for any application categorized as "Specific" without the prior written consent of Renesas Electronics. Further, you may not use any Renesas Electronics product for any application for
	which it is not intended without the prior written consent of Renesas Electronics. Renesas Electronics shall not be in any way liable for any damages or losses incurred by you or third parties arising from the
	use of any Renesas Electronics product for an application categorized as "Specific" or for which the product is not intended where you have failed to obtain the prior written consent of Renesas Electronics.
	The quality grade of each Renesas Electronics product is "Standard" unless otherwise expressly specified in a Renesas Electronics data sheets or data books, etc.
	Standard*: Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools;
	personal electronic equipment; and industrial robots. High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control systems; anti-disaster systems; anti-crime systems; safety equipment; and medical equipment not specifically
	High Quality:: I ransportation equipment (automobiles, trains, ships, etc.); traffic control systems; anti-disaster systems; anti-crime systems; safety equipment; and medical equipment not specifically designed for life support.
	Specific': A licraft; aerospace equipment; submersible repeaters; nuclear reactor control systems; medical equipment or systems for life support (e.g. artificial life support devices or systems), surgical
	implantations, or healthcare intervention (e.g. excision, etc.), and any other applications or purposes that pose a direct threat to human life.
3.	rou should use the Renesas Electronics products described in this document within the range specified by Renesas Electronics, especially with respect to the maximum rating, operating supply voltage
	range, movement power voltage range, heat radiation characteristics, installation and other product characteristics. Renesas Electronics shall have no liability for malfunctions or damages arising out of the
	use of Renesas Electronics products beyond such specified ranges.
	Although Renesas Electronics endeavors to improve the quality and reliability of its products, semiconductor products have specific characteristics such as the occurrence of failure at a certain rate and
	malfunctions under certain use conditions. Further, Renesas Electronics products are not subject to radiation resistance design. Please be sure to implement safety measures to guard them against the possibility of physical injury, and injury or damage caused by fire in the event of the failure of a Renesas Electronics product, such as safety design for hardware and software including but not limited to
	recommy or product upper, and nearly to damage caused by non-interference of the manage of a construction of the const
	please evaluate the safety of the final products or system manufactured by you.
10.	Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. Please use Renesas Electronics
	products in compliance with all applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive. Renesas Electronics assume:
	no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
11.	no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of Renesas Electronics.
11. 12.	no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of Renesas Electronics. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products, or if you have any other inquiries.
11. 12. (Not	no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of Renesas Electronics. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products, or if you have any other inquiries. a 1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries.
11.	no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of Renesas Electronics. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products, or if you have any other inquiries. a 1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries.
11. 12. (Not	no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of Renesas Electronics. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products, or if you have any other inquiries. a 1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries.
11. 1 12. (Not (Not	no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of Renesas Electronics. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products, or if you have any other inquiries. 1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries. 2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics. ES OFFICES Renesas Electronics Corporation http://www.renesas.corporation
11. 12. (Not (Not AL efer	no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of Renesas Electronics. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products, or if you have any other inquiries. a) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries. a) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics. Renesas Electronics Corporation Renesas Electronics Corporation http://www.renesas.com/" for the latest and detailed information. Base Electronics America Inc.
11. 12. (Not (Not AL efer 880	no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of Renesas Electronics. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products, or if you have any other inquiries. a) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries. a) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics. Renesas Electronics Corporation http://www.renesas.com/" for the latest and detailed information. Sas Electronics America Inc. Scott Bouldward Santa Clara, CA 95050-2554, U.S.A.
AL afer 880 ane 880 ane 880 ane 880 ane 880 ane 880 ane 880 ane 880 ane 880 ane 880 ane ane ane ane ane ane ane ane	no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of Renesas Electronics. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products, or if you have any other inquiries. a) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries. a) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics. ESOFFICES Renesas Electronics Corporation http://www.renesas.com/" for the latest and detailed information. Base Electronics America Inc. Scott Boulevard Santa Clara, CA 95050-2554, U.S.A. 1-408-588-6000, Fax: +1-408-588-6130 Base Electronics Conduct
AL Sefer 01 01 01 01 01 01 01 01 01 01	no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of Renesas Electronics. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products, or if you have any other inquiries. 1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries. 2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics. EXECUTE: Renesas Electronics Corporation to "http://www.renesas.com/" for the latest and detailed information. Sas Electronics America Inc. South Boulevant School-25564 , U.S.A. -1-408-588-6000, Fax: +1-408-588-6130 Sas Electronics Canada Limited Nettorics Canada Limited Nettorics Canada Limited
AL 80 80 11. 12. Not Not AL 91:	no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of Renesas Electronics. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products, or if you have any other inquiries. a) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries. a) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics. Renesas Electronics Corporation Renesas Electronics Corporation to "http://www.renesas.com/" for the latest and detailed information. Sas Electronics America Inc. Scott Bouldward Santa Clara, CA 95050-2554, U.S.A. 1-408-588-6000, Fax: +1-408-588-6130 Sas Electronics Corporation Bis Electronics Conta Limited Nicholson Road , Newmarket, Ontario L3Y 9C3, Canada 1-305-589-5441, Fax: +1-303-589-32220 Sas Electronics Europe Limited
AL AL afer 80 91:	no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of Renesas Electronics. Please contact a Renesas Electronics sales office if you have any questions regarding the information constained in this document or Renesas Electronics products, or if you have any other inquiries. a) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries. a) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics. EXECUTO: Renesas Electronics Corporation Renesas Electronics Corporation to "http://www.renesas.com/" for the latest and detailed information. Base Electronics America Inc. Scott Boulevard Santa Clara, CA 95050-2554, U.S.A. 1-408-588-61000, Fax: 1-1408-588-6130 Base Electronics Canada Limited Nicholson Road, Newmarket, Onlario L3Y 9C3, Canada 1-305-898-5411, Fax: 1-308-588-3220 Bas Electronics Europe Limited Nicholson Road, Bourne End, Buckinghamshire, SL8 5FH, U.K
AL AL Solution AL Solution AL Solution AL Solution Solution AL Solution So	no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of Renesas Electronics. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products, or if you have any other inquiries. a) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries. a) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics. Renesas Electronics Corporation to "http://www.renesas.com/" for the latest and detailed information. Base Electronics America Inc. Scott Boulevant Santa Clara, CA 95050-2554, U.S.A. 1-408-588-6000, Fax: +1-408-588-6130 Base Electronics Conda Limited Nicholson Road, Newmarket, Ontario LSY 9C3, Canada 1-905-588-5000, Fax: +1-408-588-6130 Base Electronics Conda Limited Nicholson Road, Newmarket, Ontario LSY 9C3, Canada 1-905-588-5000, Fax: +1-408-588-5030 Base Electronics Europe Limited Nectors Road, Reverse Enditioner Substrates States Stat
AL AL Solution	no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations. Please contact a Renessas Electronics sales office if you have any questions regarding the information contained in this document or Renessas Electronics products, or if you have any other inquiries. 1) "Renessas Electronics" as used in this document means Renessas Electronics Corporation and also includes its majority-owned subsidiaries. 2) "Renessas Electronics product(s)" means any product developed or manufactured by or for Renessas Electronics. 2) "Renessas Electronics product(s)" means any product developed or manufactured by or for Renessas Electronics. 2) "Renessas Electronics product(s)" means any product developed or manufactured by or for Renessas Electronics. 2) "Renessas Electronics Comportation. 2) "Renessas Electronics Comportation. 2) The product developed or manufactured by or for Renessas Electronics. 2) The product developed or manufactured by or for Renessas Electronics. 2) The product developed or manufactured by or for Renessas Electronics. 2) The product developed or manufactured by or for Renessas Electronics. 2) The product developed or manufactured by or for Renessas Electronics. 2) The product developed or manufactured by or for Renessas Electronics. 2) The product developed or manufactured by or for Renessas Electronics. 2) The product developed or manufactured by or for Renessas Electronics. 2) The product developed or manufactured by or for Renessas Electronics. 2) The product developed or for Renessas Electronics Comportation. 3) The product developed or developed or manufactured by or for Renessas Electronics Comportation. 3) The product developed or for Renessas Electronics Comports and the product developed or Renessas Electronics Electronics Europe Comports and the prod
AL AL afer ane ane ane ane ane ane ane ane	no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of Renesas Electronics. Please contact a Renesas Electronics sues of this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries. 2) "Renesas Electronics are used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries. 2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics. ESCOFFICES Renesas Electronics Corporation http://www.renesas.com " for the latest and detailed information. to "http://www.renesas.com" for the latest and betailed betailed of the solution of the solution of the solution of th
AL Not AL offer ene 80 01 1: + ene 80 01 1: + ene 80 1: + ene 1:	no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of Renesas Electronics. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products, or if you have any other inquiries. 1) "Renesas Electronics aread in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries. 2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics. ES OFFICES Renesas Electronics Corporation of August Section Sectio
AL Not AL offer 880 11: + ene 01 11: + ene 01: + ene 000 1: + ene 01: + ene 01: + ene 0 1: + ene 0 1: + ene 0: + + + + + + + + + + + + + + + + + +	no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of Renesas Electronics products, or if you have any questions regarding the information contained in this document or Renesas Electronics products, or if you have any other inquiries. a) "Renesas Electronics are used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries. a) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics. Renesas Electronics product(s) " means any product developed or manufactured by or for Renesas Electronics. Renesas Electronics Corporation http://www.renesas.ccm/" for the latest and detailed information. Institution: America Inc. Soort Bouleward Santa Clarz, CA 95050-2554, U.S.A. 1-408-588-6000, Fax: +1-408-588-6130 Sas Electronics Canada Limited Nicholson Road, Newmarket, Ontario L3Y 9C3, Canada 1-905-889-5041, Fax: +1-905-588-3220 sas Electronics Europe Limited Meadow, Millboard Road, Bourne End, Buckinghamshire, SL8 5FH, U.K 4+1282-585-100, Fax: +4+21-828-585-900 sas Electronics Europe Limited Meadow, Millboard Road, Bourne End, Buckinghamshire, SL8 5FH, U.K 4+1282-585-100, Fax: +4+21-6503-1327 sas Electronics Cling Co., Ltd. Discretion Science SCING College sas Electronics Cling Co., Ltd. Discretion Science SCING College sas Electronics Cling Co., Ltd. Discretion Science SCING College sas Electronics College sas Electronics Cling Co., Ltd. sas Electronics Cling Co., Ltd. Discretion Cling Co., Ltd.
AL (Not (Not AL afer ane 380 bl:	no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of Renesas Electronics, or if you have any other inquiries. 1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries. 2) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries. 2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics. 2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics. 2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics. 2) "Renesas Electronics Corporation Developed or manufactured by or for Renesas Electronics. 2) "Renesas Electronics accord" for the latest and detailed information. 2) "Thtp://www.renesas.com/" for the latest and detailed information. 2) Bettornics Canada Limited 2) Notes 30: Table 2:
AL AL AL AL AL AL AL AL AL AL	no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations. This document may not be reproduced or diplicated, in any form, in whole or in part, without prior wither occurrent of Renessas Electronics products, or if you have any other inquiries. 1) "Renessas Electronics" as used in this document means Renessas Electronics Corporation and also includes its majority-owned subsidiaries. 2) "Renessas Electronics product(s)" means any product developed or manufactured by or for Renessas Electronics. 2) "Renessas Electronics product(s)" means any product developed or manufactured by or for Renessas Electronics. 2) "Renessas Electronics product(s)" means any product developed or manufactured by or for Renessas Electronics. 2) "Renessas Electronics accounts" for the latest and detailed information. 2) Thitp://www.renessas.com/" for the latest and detailed information. 2) Satt Boulevard Santa Clara, CA 95050-2554, U.S.A. 1-408-588-6000, Fax: 1-44-065-88-6100 2) Satt Boulevard Santa Clara, CA 95050-2554, U.S.A. 1-408-588-6000, Fax: 1-41-405-888-6130 2) Satt Beteronics Canada Limited 1) Nonchos Regular, Newmarkel, Chartino L3 YG-3, Canada 2) Satt Beteronics Canada Limited 1) Meadow, Milliboard Road, Bourne End, Buckinghamshire, SLB 5FH, U.K 44-1282-585-1000, Fax: 4-14-028-585-500 2) Satt Beteronics Chinad CL, Ud 20 or Quantum Plaza, No.27 ZhiChun,Lu Haldian District, Beijing 100083, P.R.China 80-13-0355, Fax: +89-21-4503-1327 2) Satt Beteronics (Shanghai) Co., Ltd. 20 or Quantum Plaza, No.27 ZhiChun,Lu Haldian District, Shanghai 200120, China 80-13-0357, Fax: +89-21-4503-7889 / 7889 2) Satt Satt Shanghai) Co., Ltd. 20 JS, AZA, Charter, No.1238 JP. Pudong District, Shanghai 200120, China 80-213-577, Talts, Fax: +89-214-5889 / 7889 / 7889 2) Satt Satt Shanghai) Co., Ltd. 2) JS, AZA, Charter, No.1238 JP. Pudong District, Shanghai 200120, China 8) Satt Satt Shanghai) Co., Ltd. 2) JS, AZA, Charter, No.2138 JP. Azed, JS, AZA 2) Satt Satt Shan
AL (Not (Not AL (Not AL (Not AL (Not AL (Not (Not AL (Not	no lability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior withen consent of Renesas Electronics products, or if you have any other inquiries. 1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries. 2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics. 2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics. 2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics. 2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics. 2) The velocity of the latest and detailed information. 2) The velocity of the latest and detailed information. 2) Sett Boulevard Santa Clara, CA 99050-2554, U.S.A. 1-408-588-4000. Neuromatic, Ontario 1.37 9C3, Canada 2) Sett Electronics Canada Limited 2) Monolson Road, Neurem End, Duckinghamshire, SLB 5FH, U.K. 44-1282-585-1000. Neurostical, Surger End, Buckinghamshire, SLB 5FH, U.K. 44-1282-585-1001. Fax: +1-408-588-4030. 2) Set Electronics Europe Limited 2) Meadow, Millibaard Road, Bourne End, Buckinghamshire, SLB 5FH, U.K. 44-1282-585-10742. Chal. 2) Construction, Fax: +4-1282-585-300. 2) Set Electronics (Shanghar) Co., Ltd. 2) Or Quantum Plaza, No.27 2) Thorhung Latadian District, Beijing 100083, P.R.China 86-11-282-287-779 2) Set Electronics (Shanghar) Co., Ltd. 2) Or Quantum Plaza, No.27 2) Thorhung Latadian District, Beijing 100083, P.R.China 86-12-327-71915, Fax: +86-21-3887-7689. Texes 2) Set Electronics (Shanghar) Co., Ltd. 2) Or Quantum Plaza, No.27 2) Thorhung Latadian District, Beijing 100083, P.R.China 86-12-327-71915, Fax: +86-21-3887-7689. Texes 2) Set Electronics (Shanghar) Co., Ltd. 2) Sot, To: Kinty,
AL (Not AL afer ane afer ane afer ane afer ane afer ane afer afe	no lability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations. This document may not be reproduced or duplicated, in any form, in whole or in part, withou prior witten consent of Renease Electronics products, or if you have any other inquiries. 1) "Renease Electronics" as used in this document means Renease Electronics Corporation and also includes its majority-owned subsidiaries. 2) "Renease Electronics product(s)" means any product developed or manufactured by or for Renease Electronics. The Constraint of the
ALL ALL ALL ALL ALL ALL ALL ALL	no lability for damages or losses occurring as a result of your noncomplance with applicable laws and regulations. This document may not be reproduced or duplicated, in any form, in whole or in part, withou prior witten contenter of the initial contenter of the meases Electronics products, or if you have any other inquiries. Pages conteal a fease sofication you beave any questions regarding the information contained in this document or Reneases Electronics products, or if you have any other inquiries. Pages conteal results and the analysis of the product developed or manufactured by or for Renesses Electronics. Pages conteal results and developed or manufactured by or for Renesses Electronics. Pages conteal results and developed or manufactured by or for Renesses Electronics. Pages conteal results and developed or manufactured by or for Renesses Electronics. Pages conteal results and developed or manufactured by or for Renesses Electronics. Pages conteal results and developed or manufactured by or for Renesses Electronics. Pages conteal results and developed or manufactured by or for Renesses Electronics. Pages conteal results and developed or manufactured by or for Renesses Electronics. Pages conteal results and developed or manufactured by or for Renesses Electronics. Pages Conteal results and developed or manufactured by or for Renesses Electronics. Pages Conteal results and developed or manufactured by or for Renesses Electronics. Pages Conteal results and developed or manufactured by or for Renesses Electronics. Pages Conteal results and developed or manufactured by or for Renesses Electronics. Pages Conteal results and developed or manufactured by or for Renesses Electronics. Pages Conteal results and developed or manufactured by or for Renesses Electronics. Pages Conteal results and developed or manufactured by or for Renesses Electronics. Pages Conteal results and developed or manufactured by or for Renesses Electronics. Pages Conteal results and developed or manufactured by or for Renesses Electronics.