

To our customers,

---

## Old Company Name in Catalogs and Other Documents

---

On April 1<sup>st</sup>, 2010, NEC Electronics Corporation merged with Renesas Technology Corporation, and Renesas Electronics Corporation took over all the business of both companies. Therefore, although the old company name remains in this document, it is a valid Renesas Electronics document. We appreciate your understanding.

Renesas Electronics website: <http://www.renesas.com>

April 1<sup>st</sup>, 2010  
Renesas Electronics Corporation

Issued by: Renesas Electronics Corporation (<http://www.renesas.com>)

Send any inquiries to <http://www.renesas.com/inquiry>.

# RENESAS TECHNICAL UPDATE

Nippon Bldg., 2-6-2, Ohte-machi, Chiyoda-ku, Tokyo 100-0004, Japan  
Renesas Technology Corp.

Product Category	MPU&MCU		Document No.	TN-H8*-A376A/E	Rev.	1.00
Title	Error Correction of the Pin Assignments in the H8SX/1653 Group Hardware Manual		Information Category	Technical Notification		
Applicable Product	H8SX/1653 Group	Lot No.	Reference Document	H8SX/1653 Group Hardware Manual (REJ09B0219-0100, Rev. 1.0)		
		All lots				

Thank you for your consistent patronage of Renesas semiconductor products.

We would like to inform you of the error correction in Figure 1.2 Pin Assignments in the H8SX/1653 Group Hardware Manual.

## [Before change]




Figure 1.2 Pin Assignments

## [After change]




Figure 1.2 Pin Assignments