TEConcept

RA, RX, RL78 Ecosystem Partner Solution **TEConcept IO-Link V1.1.3 Stacks**



Solution Summary


TEConcept provides IO-Link Stacks V1.1.3 for IO-Link master and device. IO-Link Master Stack V1.1.3 supporting e.g. CCE4510 PHY including IO-Link SMI interface. IO-Link Device Stack V1.1.3 including driver to IO-Link PHY ZIOL2401 and CCE4502 for manufacturing IO-Link compliant Devices with optional parameter handler. Available for RA Family, RL78 Family or RX Family MCUs.

Features/Benefits


- API reference manual and demo application included
- Supports all mandatory features of the IO-Link specification at all COM speeds
- Option support for IO-Link profiles, e.g. Device firmware update
- · Royalty-free license, one year maintenance

Diagrams/Graphics

IO-Link Device stack



IO-Link Master stack



Target Markets and Applications

- Industrial Automation
- IO-Link Devices

PLC

Sensors

Remote/IO

Actuators

https://teconcept.de/en/io-link/produkte/

TEConcept

Who are we?

TEConcept is an engineering office that offers services for commercial and industrial partners. Our services include:

- · Consulting, Development support
- Software / Hardware design

Know-How

- · Industrial communication, especially IO-Link
- Digital signal processing
- · embedded Software
- · Graphical User Interfaces
- Short-range radio communication

IO-Link Competence and Test Center

- · Consulting, Conformance testing
- · IO-Link product development
- · Reference designs

IO-Link Products

- IO-Link Master / Device stacks
- IO-Link Firmware Update
- · IODD-Designer
- IO-Link V1.1.3 Device Tester,
- IO-Link V1.1.3 Master Tester
- · EMC Test Master,
- EMC V1.1.3Test Device
- IO-Link V1.1.3 Physical Layer Tester
- USB 1 and 4-port master (modules)
- · IO-Link Diagnosis Tool
- IO-Link Safety Master Tester (in preparation)
- IO-Link Control Tool (Parameterization)

TEConcept GmbH Wentzingerstr. 21 79106 Freiburg Germany

Phone: +49 761 21443640 Fax: +49 761 21443631

www.teconcept.de

