

HA-2640, HA-2645

4MHz, High Supply Voltage Operational Amplifiers

FN2904 Rev 6.00 August 7, 2015

HA-2640 and HA-2645 are monolithic operational amplifiers which are designed to deliver unprecedented dynamic specifications for a high voltage internally compensated device. These dielectrically isolated devices offer very low values for offset voltage and offset current coupled with large output voltage swing and common mode input voltage.

For maximum reliability, these amplifiers offer unconditional output overload protection through current limiting and a chip temperature sensing circuit. This sensing device turns the amplifier "off", when the chip reaches a certain temperature level.

These amplifiers deliver $\pm 35 \text{V}$ common mode input voltage range, $\pm 35 \text{V}$ output voltage swing, and up to $\pm 40 \text{V}$ supply range for use in such designs as regulators, power supplies, and industrial control systems. 4MHz gain bandwidth and $5 \text{V}/\mu \text{s}$ slew rate make these devices excellent components for high performance signal conditioning applications. Outstanding input and output voltage swings coupled with a low 5nA offset current make these amplifiers excitation designs.

Features

| • | Output Voltage Swing ±35 |
|---|-------------------------------------|
| • | Supply Voltage |
| • | Offset Current. 5n/ |
| • | Bandwidth |
| • | Slew Rate |
| • | Common Mode Input Voltage Range ±35 |

Output Overload Protection

Applications


- · Industrial Control Systems
- · Power Supplies
- · High Voltage Regulators
- Resolver Excitation
- · Signal Conditioning

Ordering Information


| PART NUMBER | PART MARKING | TEMP. RANGE (°C) | PACKAGE | PKG. DWG. # |
|---|--------------|------------------|-----------------|-------------|
| HA2-2640-2 | HA2-2640-2 | -55 to 125 | 8 Pin Metal Can | T8.C |
| HA7-2640-2 | HA7-2640-2 | -55 to 125 | 8 Ld CERDIP | F8.3A |
| HA2-2645-5 (No longer available or supported) | HA2-2645-5 | 0 to 75 | 8 Pin Metal Can | T8.C |
| HA7-2645-5 (No longer available or supported) | HA7-2645-5 | 0 to 75 | 8 Ld CERDIP | F8.3A |

Pinouts

HA-2640/2645 (CERDIP) TOP VIEW



HA-2640/2645 (METAL CAN) TOP VIEW



(TO-99 CASE VOLTAGE = FLOATING)

Absolute Maximum Ratings

Operating Conditions

| Temperature Range | |
|-------------------|--------------------|
| HA-2640-2 | -55°C to 125°C |
| HA-2645-5 | 0°C to 75°C |

Thermal Information

| Thermal Resistance (Typical, Note 1) | θ_{JA} (°C/W) | θ_{JC} (oC/W) |
|---------------------------------------|----------------------|----------------------|
| CERDIP Package | 135 | 50 |
| Metal Can Package | 165 | 80 |
| Maximum Junction Temperature | | 175°C |
| Maximum Storage Temperature Range . | 65 | oC to 150°C |
| Maximum Lead Temperature (Soldering 1 | 0s) | 300°C |
| | | |

CAUTION: Stresses above those listed in "Absolute Maximum Ratings" may cause permanent damage to the device. This is a stress only rating and operation of the device at these or any other conditions above those indicated in the operational sections of this specification is not implied.

NOTE:

1. θ_{JA} is measured with the component mounted on an evaluation PC board in free air.

Electrical Specifications $V_{SUPPLY} = \pm 40V$, $R_L = 5k\Omega$, Unless Otherwise Specified


| | | TEMP | HA-2640-2 | | | HA-2645-5 | | | |
|---------------------------------------|--------------------------------------|------|-----------|-----|-----|-----------|-----|-----|-------|
| PARAMETER | TEST CONDITIONS | (°C) | MIN | TYP | MAX | MIN | TYP | MAX | UNITS |
| INPUT CHARACTERISTICS | | | <u>'</u> | | | | | | |
| Offset Voltage | | 25 | - | 2 | 4 | - | 2 | 6 | mV |
| | | Full | | - | 6 | - | - | 7 | mV |
| Average Offset Voltage Drift | | Full | - | 15 | - | - | 15 | - | μV/ºC |
| Bias Current | | 25 | - | 10 | 25 | - | 12 | 30 | nA |
| | | Full | - | - | 50 | - | - | 50 | nA |
| Offset Current | | 25 | - | 5 | 12 | - | 15 | 30 | nA |
| | | Full | - | - | 35 | - | - | 50 | nA |
| Input Resistance (Note 2) | | 25 | 50 | 250 | - | 40 | 200 | - | ΜΩ |
| Common Mode Range | | Full | ±35 | - | - | ±35 | - | - | V |
| TRANSFER CHARACTERISTICS | S | | | | | | | | |
| Large Signal Voltage Gain | $V_{OUT} = \pm 30V$ | 25 | 100 | 200 | - | 100 | 200 | - | kV/V |
| | | Full | 75 | - | - | 75 | - | - | kV/V |
| Common Mode Rejection Ratio | V _{CM} = ±20V | Full | 80 | 100 | - | 74 | 100 | - | dB |
| Minimum Stable Gain | | 25 | 1 | - | - | 1 | - | - | V/V |
| Unity Gain Bandwidth | V _{OUT} = 90mV | 25 | - | 4 | - | - | 4 | - | MHz |
| OUTPUT CHARACTERISTICS | | | | | | | | | |
| Output Voltage Swing | | Full | ±35 | - | - | ±35 | - | - | V |
| Output Current | $R_L = 1k\Omega$ | 25 | ±12 | ±15 | - | ±10 | ±12 | - | mA |
| Output Resistance | Open Loop | 25 | - | 500 | - | - | 500 | - | Ω |
| Full Power Bandwidth (Note 3) | $V_{OUT} = \pm 35V$ | 25 | - | 23 | - | - | 23 | - | kHz |
| TRANSIENT RESPONSE A _V = + | 1, $C_L = 50 pF$, $R_L = 5 k\Omega$ | | | | | | | | |
| Rise Time | $V_{OUT} = \pm 200 \text{mV}$ | 25 | - | 60 | 135 | - | 60 | 135 | ns |
| Overshoot | $V_{OUT} = \pm 200 \text{mV}$ | 25 | - | 15 | 30 | | 15 | 40 | % |
| Slew Rate | | 25 | ±3 | ±5 | - | ±2.5 | ±5 | - | V/μs |
| POWER SUPPLY CHARACTER | ISTICS | • | | | | | | 1 | |
| Supply Current | | 25 | - | 3.2 | 3.8 | - | 3.2 | 4.5 | mA |
| Supply Voltage Range | | Full | ±10 | - | ±40 | ±10 | - | ±40 | V |
| Power Supply Rejection Ratio | V _S = ±10V to ±40V | Full | 80 | 90 | - | 74 | 90 | - | dB |

NOTES:


- 2. This parameter is based upon design calculations.
- 3. Full Power Bandwidth guaranteed based upon slew rate measurement: FPBW = S.R./2πV_{PEAK}; V_{PEAK} = 35V.




Schematic Diagram



Test Circuits and Waveform








NOTE: Tested offset adjustment range is $|V_{OS}| + 1mV|$ minimum referred to output. Typical range is $\pm 20mV$ with $R_T = 10k\Omega$.

FIGURE 2. SUGGESTED V_{OS} ADJUSTMENT AND COMPENSATION HOOK UP

Test Circuits and Waveform (Continued)



Vertical = 10V/Div., Horizontal = $5\mu s/Div.$

NOTE: $R_L = 5k\Omega$, $C_L = 50pF$, $T_A = 25^oC$, $V_S = \pm 40V$ FIGURE 3. VOLTAGE FOLLOWER PULSE RESPONSE

Typical Performance Curves $V_S = \pm 40V$, $T_A = 25^{\circ}C$, Unless Otherwise Specified




FIGURE 4. INPUT BIAS AND OFFSET CURRENT vs TEMPERATURE




FIGURE 6. NORMALIZED AC PARAMETERS vs TEMPERATURE




FIGURE 5. INPUT NOISE CHARACTERISTICS




FIGURE 7. OPEN LOOP FREQUENCY RESPONSE



Typical Performance Curves $V_S = \pm 40V$, $T_A = 25^{\circ}C$, Unless Otherwise Specified (Continued)




FIGURE 8. NORMALIZED AC PARAMETERS vs SUPPLY VOLTAGE AT 25°C




FIGURE 9. OPEN LOOP FREQUENCY RESPONSE FOR VARIOUS VALUES OF CAPACITORS FROM COMPENSATION PIN TO GROUND




FIGURE 10. OUTPUT VOLTAGE SWING vs FREQUENCY




FIGURE 11. OUTPUT CURRENT CHARACTERISTIC




FIGURE 12. SUPPLY CURRENT vs SUPPLY VOLTAGE




FIGURE 13. OUTPUT VOLTAGE SWING vs SUPPLY VOLTAGE

Die Characteristics

SUBSTRATE POTENTIAL (Powered Up):

Unbiased

TRANSISTOR COUNT:


76

PROCESS:

HV200 Bipolar Dielectric Isolation

Metallization Mask Layout

HA-2640, HA-2645



Revision History

The revision history provided is for informational purposes only and is believed to be accurate, but not warranted. Please go to the web to make sure that you have the latest revision.

| DATE | REVISION | CHANGE |
|----------------|----------|--|
| August 7, 2015 | FN2904.6 | Page 1, Ordering Information table: HA2-2645-5 and HA7-2645-5 no longer available or supported. Added Revision History and About Intersil. |

About Intersil

Intersil Corporation is a leading provider of innovative power management and precision analog solutions. The company's products address some of the largest markets within the industrial and infrastructure, mobile computing and high-end consumer markets.


For the most updated datasheet, application notes, related documentation and related parts, please see the respective product information page found at www.intersil.com.

You may report errors or suggestions for improving this datasheet by visiting www.intersil.com/ask.

Reliability reports are also available from our website at www.intersil.com/support



Metal Can Packages (Can)



NOTES:


- (All leads) Øb applies between L1 and L2. Øb1 applies between L2 and 0.500 from the reference plane. Diameter is uncontrolled in L1 and beyond 0.500 from the reference plane.
- 2. Measured from maximum diameter of the product.
- 3. α is the basic spacing from the centerline of the tab to terminal 1 and β is the basic spacing of each lead or lead position (N -1 places) from α , looking at the bottom of the package.
- 4. N is the maximum number of terminal positions.
- 5. Dimensioning and tolerancing per ANSI Y14.5M 1982.
- 6. Controlling dimension: INCH.

T8.C MIL-STD-1835 MACY1-X8 (A1) 8 LEAD METAL CAN PACKAGE

| | INC | HES | MILLIN | | |
|--------|-----------------|-------|----------|-------|-------|
| SYMBOL | MIN | MAX | MIN MAX | | NOTES |
| Α | 0.165 | 0.185 | 4.19 | 4.70 | - |
| Øb | 0.016 | 0.019 | 0.41 | 0.48 | 1 |
| Øb1 | 0.016 | 0.021 | 0.41 | 0.53 | 1 |
| Øb2 | 0.016 | 0.024 | 0.41 | 0.61 | - |
| ØD | 0.335 | 0.375 | 8.51 | 9.40 | - |
| ØD1 | 0.305 | 0.335 | 7.75 | 8.51 | - |
| ØD2 | 0.110 | 0.160 | 2.79 | 4.06 | - |
| е | 0.200 | BSC | 5.08 BSC | | - |
| e1 | 0.100 | BSC | 2.54 BSC | | - |
| F | - | 0.040 | - | 1.02 | - |
| k | 0.027 | 0.034 | 0.69 | 0.86 | - |
| k1 | 0.027 | 0.045 | 0.69 | 1.14 | 2 |
| L | 0.500 | 0.750 | 12.70 | 19.05 | 1 |
| L1 | - | 0.050 | - | 1.27 | 1 |
| L2 | 0.250 | - | 6.35 | - | 1 |
| Q | 0.010 | 0.045 | 0.25 | 1.14 | - |
| α | 45° BSC | | 45° BSC | | 3 |
| β | 45 ⁰ | BSC | 45° BSC | | 3 |
| N | 8 | 3 | 8 | | 4 |

Rev. 0 5/18/94

Ceramic Dual-In-Line Frit Seal Packages (CERDIP)



NOTES:

- Index area: A notch or a pin one identification mark shall be located adjacent to pin one and shall be located within the shaded area shown. The manufacturer's identification shall not be used as a pin one identification mark.
- The maximum limits of lead dimensions b and c or M shall be measured at the centroid of the finished lead surfaces, when solder dip or tin plate lead finish is applied.
- Dimensions b1 and c1 apply to lead base metal only. Dimension M applies to lead plating and finish thickness.
- Corner leads (1, N, N/2, and N/2+1) may be configured with a partial lead paddle. For this configuration dimension b3 replaces dimension b2.
- 5. This dimension allows for off-center lid, meniscus, and glass overrun
- 6. Dimension Q shall be measured from the seating plane to the base plane.
- 7. Measure dimension S1 at all four corners.
- 8. N is the maximum number of terminal positions.
- 9. Dimensioning and tolerancing per ANSI Y14.5M 1982.
- 10. Controlling dimension: INCH

F8.3A MIL-STD-1835 GDIP1-T8 (D-4, CONFIGURATION A) 8 LEAD CERAMIC DUAL-IN-LINE FRIT SEAL PACKAGE

| | INC | HES | MILLIM | | |
|--------|-------|------------------|----------|------------------|-------|
| SYMBOL | MIN | MAX | MIN MAX | | NOTES |
| Α | - | 0.200 | - | 5.08 | - |
| b | 0.014 | 0.026 | 0.36 | 0.66 | 2 |
| b1 | 0.014 | 0.023 | 0.36 | 0.58 | 3 |
| b2 | 0.045 | 0.065 | 1.14 | 1.65 | - |
| b3 | 0.023 | 0.045 | 0.58 | 1.14 | 4 |
| С | 0.008 | 0.018 | 0.20 | 0.46 | 2 |
| c1 | 0.008 | 0.015 | 0.20 | 0.38 | 3 |
| D | = | 0.405 | = | 10.29 | 5 |
| E | 0.220 | 0.310 | 5.59 | 7.87 | 5 |
| е | 0.100 | BSC | 2.54 BSC | | - |
| eA | 0.300 | BSC | 7.62 | - | |
| eA/2 | 0.150 | BSC | 3.81 | - | |
| L | 0.125 | 0.200 | 3.18 | 5.08 | - |
| Q | 0.015 | 0.060 | 0.38 | 1.52 | 6 |
| S1 | 0.005 | - | 0.13 | - | 7 |
| α | 90° | 105 ⁰ | 90° | 105 ⁰ | - |
| aaa | - | 0.015 | - | 0.38 | - |
| bbb | = | 0.030 | - 0.76 | | - |
| ccc | - | 0.010 | - | 0.25 | - |
| M | - | 0.0015 | - 0.038 | | 2, 3 |
| N | 8 | 3 | 8 | 8 | |

Rev. 0 4/94

© Copyright Intersil Americas LLC 2001-2015. All Rights Reserved. All trademarks and registered trademarks are the property of their respective owners.

For additional products, see www.intersil.com/en/products.html

Intersil products are manufactured, assembled and tested utilizing ISO9001 quality systems as noted in the quality certifications found at www.intersil.com/en/support/qualandreliability.html

Intersil products are sold by description only. Intersil may modify the circuit design and/or specifications of products at any time without notice, provided that such modification does not, in Intersil's sole judgment, affect the form, fit or function of the product. Accordingly, the reader is cautioned to verify that datasheets are current before placing orders. Information furnished by Intersil is believed to be accurate and reliable. However, no responsibility is assumed by Intersil or its subsidiaries for its use; nor for any infringements of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of Intersil or its subsidiaries.

For information regarding Intersil Corporation and its products, see www.intersil.com

