CUSTOMER DESIGN-IN FLOWCHART GUIDELINE FOR i.MX6Q/D BASED PLATFORM WITH DA9063

ASSESSMENT: CUSTOMER REQUIREMENTS




Purpose: guideline aimed to make the best choice of HW platform, SW platform and DA9063B OTP variants for an i.MX6 Q/D based platform

Scope: DA9063B variants and i.MX6 Q/D processors

Reference documentation from DIALOG customer portal https://support.diasemi.com:

- DA9063_iMX6 standard variant factsheet
- AN-PM-027 DA9063 power management for iMX6 platforms V1.0
- DA9063_iMX6Q_schematic_BOM_example




CUSTOMER DESIGN-IN FLOWCHART GUIDELINE FOR i.MX 6Q/D BASED PLATFORM WITH DA9063B

DECISION: Choose the best DA9063B OTP variant



FREESCALE SABRE BASED SYSTEM SOLUTION

GENERIC BASIC SYSTEM SOLUTION



IMPORTANT NOTICE AND DISCLAIMER

RENESAS ELECTRONICS CORPORATION AND ITS SUBSIDIARIES ("RENESAS") PROVIDES TECHNICAL SPECIFICATIONS AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS OR IMPLIED, INCLUDING, WITHOUT LIMITATION, ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NON-INFRINGEMENT OF THIRD-PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for developers who are designing with Renesas products. You are solely responsible for (1) selecting the appropriate products for your application, (2) designing, validating, and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, or other requirements. These resources are subject to change without notice. Renesas grants you permission to use these resources only to develop an application that uses Renesas products. Other reproduction or use of these resources is strictly prohibited. No license is granted to any other Renesas intellectual property or to any third-party intellectual property. Renesas disclaims responsibility for, and you will fully indemnify Renesas and its representatives against, any claims, damages, costs, losses, or liabilities arising from your use of these resources. Renesas' products are provided only subject to Renesas' Terms and Conditions of Sale or other applicable terms agreed to in writing. No use of any Renesas resources expands or otherwise alters any applicable warranties or warranty disclaimers for these products.

(Disclaimer Rev.1.01 Jan 2024)

Corporate Headquarters

TOYOSU FORESIA, 3-2-24 Toyosu, Koto-ku, Tokyo 135-0061, Japan www.renesas.com

Trademarks

Renesas and the Renesas logo are trademarks of Renesas Electronics Corporation. All trademarks and registered trademarks are the property of their respective owners.

Contact Information

For further information on a product, technology, the most up-to-date version of a document, or your nearest sales office, please visit www.renesas.com/contact-us/.